SERVICE MANUAL

AUDIO & VIDEO MINI COMPONENT SYSTEM

P-757



- AV-757
  STEREO INTEGRATED AMPLIFIER
- TX-757
  FM/AM STEREO TUNER & TIMER
- CDC-757/ VCDC-757
  MULTI COMPACT DISC PLAYER
  / VIDEO COMPACT DISC PLAYER
- DD-757
  STEREO DOUBLE CASSETTE DECK

P-747



- AX-747
  STEREO INTEGRATED AMPLIFIER
- TX-747
  FM/AM STEREO TUNER & TIMER
- CDC-757/ VCDC-757
  MULTI COMPACT DISC PLAYER
  / VIDEO COMPACT DISC PLAYER
- DD-757
  STEREO DOUBLE CASSETTE DECK

Sherwood®

■ CONTENTS ■

■ AV-757/AX-747 ■

■ TX-757/TX-747 ■

■ CDC-757/VCDC-757 ■

■ DD-757 ■

▪ AV-757/AX-747 ▪

SAFETY PRECAUTION

WARNING

Before servicing this unit, familiarize yourself with the following precautions:

1. Many electrical and mechanical parts in this chassis have special safety characteristics that often pass unnoticed and the protection afforded by them cannot necessarily be obtained by using replacement components rated for higher voltage wattage, etc. Replacement parts that have these special safety characteristics are identified in this manual and its supplements: electrical components having such features are identified by ⚠ in the schematic diagram and the parts list.

   Before replacing any of these components, read the parts list in this manual carefully. The use of substitute replacement parts that do not have the same safety characteristics as specified in the parts list may create shock, fire, or other hazards.

2. Before returning the set to the customer, always do an AC leakage current check on the exposed metal parts of the cabinet, such as terminals, screw heads, and metal overlays, to be sure the set is safe to operate danger of electrical shock. Plug the AC line cord directly into a 120 V AC outlet (120 V AC version only). (Do not use a line isolation transformer during this check.) Be sure your AC voltmeter has a sensitivity of 5000 Ω per volt or greater. Then connect a 1500 Ω 10 watt resistor, paralleled by a 0.15 μF 150 V AC capacitor, between a known good earth ground (such as a water pipe, or conduit) and the exposed metalic parts, one at a time. Measure the AC voltage across the combination of a 1500 Ω resistor and a 0.15 μF capacitor. Reverse the AC plug at the AC outlet and repeat AC voltage measurements for each exposed metalic part. Voltage measured must not exceed 0.75 V RMS. This corresponds to 0.2 mA AC. Any value exceeding this limit constitutes a potential shock hazard and must be corrected immediately.

At 5000 Ω per volt or greater sensitivity,
the reading should not exceed 0.75 V.



Place the probe on each exposed metalic part.

SYSTEM CONNECTIONS

- Do not plug the AC input cord the AC outlet when plugging and unplugging connection cords.
- Make connections firmly and correctly according to the channel (Left and Right), polarity (+ and -) and connector(system 1 to 4). If not, it can cause loss of sound, noise or damage to unit.
- Be sure to use speakers of impedance 6 Ω .
- Place the AM loop antenna as far as possible from this system, TV, speaker cords and AC input cord and set it to a direction for the best reception.
- If the reception is poor with the AM loop antenna, an AM outdoor antenna can be used without the AM loop antenna.
- If the sound quality is poor with the FM indoor antenna, connect an FM outdoor antenna instead of the FM indoor antenna.
- If the electricity fails or the AC input cord is leaved unplugged for more then 15 days, the memorized contents are all cleared. So you should memorize them again.

■ P-747 ■



■ P-757 ■


1 ANTENNA TERMINALS
FM indoor antenna
AM loop antenna
2 VCR2 INPUT JACKS
3 VCR1 IN/OUT JACKS
6 SYSTEM CONNECTOR 3
DD-757
7 SYSTEM CONNECTOR 4
CDC/VCDC-757
8 SYSTEM CONNECTOR 2
TX-757
10 AC INPUT CORD
AV-757
9 SYSTEM CONNECTOR 1

4 VIDEO MONITOR OUTPUT



5 REAR SPEAKER TERMINALS



6 SYSTEM CONNECTOR 3

DD-757

7 SYSTEM CONNECTOR 4

CDC/VCDC-757

8 SYSTEM CONNECTOR 2

TX-757

10 AC INPUT CORD

AV-757

9 SYSTEM CONNECTOR 1

11 CENTER SPEAKER TERMINALS



12 FRONT SPEAKER TERMINALS



13 SUBWOOFER PREOUT JACK

Comect it to the input jack of subwoofer amplifier.

SPECIFICATIONS

FRONT SECTION

Description	Unit	Nominal	Limit
RMS. output power <stereo mode> Input: VIDEO, THD < 0.5%, 6 ohms load both channels driven at 1 kHz	W	≥ 53	≥ 50
<surround mode: AV-757 only> THD < 0.5%, 6 ohms load single channels driven at 1 kHz	W	≥ 33	≥ 30
Total Harmonic Distortion	%	≤ 0.2	≤ 0.2
Signal to Noise Ratio (IHF-A WTD), Input shorted	dB	≥ 85	≥ 80
Channel Separation with 4.7 kohms terminated. Input: VIDEO, 1 kHz	dB	≥ 50	≥ 50
Channel Unbalance, Input: VIDEO, 1 kHz	dB	≤ 1	≤ 2
Frequency Response at -3 dB	Hz	10 ~ 60 k	20 ~ 40 k
X-Bass compensation at 80 Hz	dB	8 ± 2	8 ± 3
EQ Control (60, 150, 400, 1 k, 2.4 k, 6 k, 15 k) Hz	dB	10 ± 2	10 ± 3
Headphone Output at Rated PWR, 50 W Headphone Impedance: 68 ohms	mV	1200 ± 200	1200 ± 300

CENTER SECTION (AV-757 ONLY)

Description	Unit	Nominal	Limit
RMS. output power THD < 0.5%, 6 ohms, 1 kHz Only center channel driven	W	≥ 33	≥ 30
Signal to Noise Ratio (IHF-A WTD), Input shorted Input: 350 mV	dB	≥ 78	≥ 73
Frequency Response at -3 dB, Wide mode	Hz	20 ~ 18 k	50 ~ 15 k

REAR SECTION (AV-757 ONLY)

Description	Unit	Nominal	Limit
RMS output power THD < 0.7%, 12 ohms load Only rear channel driven at 1 kHz	W	≥ 18	≥ 15
Signal to Noise Ratio (IHF-A WTD), Input shorted Input: 350 mV, Delay time: 20 ms	dB	≥ 85	≥ 80
Frequency Response at -3 dB	Hz	80 ~ 7 k	100 ~ 6 k

General

Power consumption

Model \ Version	A	D	PT INDO	KS
P-747		230 W	260 W	230 W
P-757	140 W	350 W	380 W	240 W

Dimensions (HxWxD)

AV-757/AX-747: 274 × 117 × 280 mm (10-3/4 × 4-11/18 × 11 inches)
DD-757: 274 × 117 × 280 mm (10-3/4 × 4-11/18 × 11 inches)
TX-757/TX-747: 274 × 87 × 280 mm (10-3/4 × 3-3/7 × 11 inches)
CDC-757/VCDC-757: 274 × 87 × 320 mm
(10-3/4 × 3-3/7 × 12-10/16 inches)

Weight (Net)	(AV-757+DD-757+TX-757+CDC-757/VCDC-757): 14.7 kg (32.407 lbs) (AX-747+DD-757+TX-747+CDC-757/VCDC-757): 14.7 kg (32.407 lbs)
Power Supplies	A: 120 V 60 Hz, USA & Canada version D: 230 V 50 Hz, Europe version B: 110/220 V 50/60 Hz, Multi area version (PT INDO) KS: 220 V 60 Hz, Korea version

Note : Nominal specs represent the design specs. All units should be able to approximate these. Some will exceed and some may drop slightly below these specs. Limit specs represent the absolute worst condition that still might be considered acceptable ; in no case should a unit fail to meet limit specs. This manual is based on the EUROPE Standard wiring diagram, and information on regional component variations through use of parts list. Design and specifications are subject to change without notice for improvement.

BLOCK DIAGRAM I

Model No. : AX-747



BLOCK DIAGRAM II

Model No. : AV-757



DISASSEMBLY PROCEDURES

REFER TO PAGES 17 AND 24.

[1] COVER TOP REMOVAL
Remove 6 screws ⓐ and then remove the Cover Top ❷.

[2] FRONT PANEL ASSEMBLY REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Remove the Card Cable from wafer (CNT303) on the Main P.C.Board (PCB3).
3. Remove the Card Cable from wafer (CNT101) on the Volume P.C.Board (PCB4).
4 Disconnect (CNT102) from the EQ P.C.Board (PCB1).
5. Remove 7 screws ⓑ and then remove the Front Panel Assembly AA.

[3] VOLUME P.C.BOARD (PCB4) REMOVAL.
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Remove the Front Panel Assembly AA, referring to the previous step [2].
3. Disconnect (CNT501) from the Volume P.C. Board (PCB4).
4. Pull out the Volume Knob ⓬ with Volume LED P.C.Board (PCB6).
5. Remove 2 screws ⓒ and then remove the Volume P.C.Board (PCB4).

[4] FRONT P.C.BOARD (PCB2) REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Do steps [2] and [3].
3. Remove 7 screws ⓓ and then remove the Front P.C.Board (PCB2) by pressing the hooks around it outward.

[5] HEADPHONE P.C.BOARD (PCB5) REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Remove the Front Panel Assembly AA, referring to the previous step [2].
3. Remove a screw ⓔ and then remove the Headphone P.C.Board (PCB5).

[6] EQ P.C.BOARD (PCB1) REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Remove the Card Cable from wafer (CNT101) on the EQ P.C.Board (PCB1).
3. Disconnect (CNT102) from the EQ P.C.Board (PCB1).
4. Remove a screw ⓕ and then remove the EQ P.C.Board (PCB1).

[7] VOLTAGE SELECTOR P.C.BOARD (PCB7) REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Disconnect (CNT801 and CNT802) from the Voltage Selector P.C.Board (PCB7).
3. Remove a screw ⓖ and then remove the Voltage Selector P.C.Board (PCB7).

[8] CHASSIS BACK REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Disconnect (CNT306 and CNT309) from the Main P.C.Board (PCB3).
3. Remove 12 screws ⓗ and then remove the Chassis Back ㉗ . (at AV-757)
Remove 8 screws ⓗ and then remove the Chassis Back ㉗ . (at AX-747)

[9] MAIN P.C.BOARD (PCB3) REMOVAL
1. Remove the Cover Top ❷, referring to the previous step [1].
2. Do steps [6] and [8].
3. Remove Card cable from wafer (CNT308) on the Main P.C.Board (PCB3).
4. Disconnect (CNT301 and CNT302) from the Main P.C.Board (PCB3).
5. Remove 3 screws ⓘ.
6. Remove the Fastener ㉒ and then remove the Main P.C.Board (PCB3).

CIRCUIT DESCRIPTION

CPU(IC201):μPD78042

1. Pin Description



2. Block Diagram



3. Input and Output Terminal Functions

Pin No.	Symbol	Description
1~7	DIGIT 7~DIGIT 1	Output for grid.
8	Vdd	+5 V power supply.
9	H/P MUTE	Output for headphone mute. Output, high level under the following conditions. 1. When power is turned on or off. 2. When headphone plug is inserted. 3. When "-∞ mute signal" is received from the commander. 4. When function is changed.
10	SURR. MUTE <AV-757 ONLY>	Output for surround mute. Output, low level under the following conditions. 1. When power is turned off. 2. When headphone plug is inserted. 3. When "-∞ mute signal" is received from the commander. 4. When function is changed. 5. When surround mode is turned off.
11	CENTER MUTE <AV-757 ONLY>	Output for center mute. Output, low level under the following conditions. 1. When power is turned off. 2. When headphone plug is inserted. 3. When "-∞ mute signal" is received from the commander. 4. When function is changed. 5. When center mode is turned off.
12	MAIN MUTE	Output for left and right chanels mute. Output, low level under the following conditions. 1. When power is turned off. 2. When headphone plug is inserted. 3. When "-∞ mute signal" is received from the commander. 4. When function is changed.
13	H/P IN	Input for detecting headphone. When headphone is plugged or unplugged, input is high or low level.
14/15	CLK/DATA	CLK/DATA output to LC7522.
16	AMP BIAS	Output for bias control. When 3 seconds elapses after "power on", "H" and at "power off", "L".
17	RESET	Input to reset u-com.
18	PROTECTION	Input for protection. At "protection on", "L" and at "protection off", "H".
19	SUBWOOFER MUTE	Output for subwoofer preout mute. Output, low level under the following conditions. 1. When power is turned on or off. 2. When function is changed. 3. When "-∞ mute signal" is received from the commander. 4. When headphone plug is inserted.
20	A-Vss	This pin provides the analog ground potential.
21	RELAY	Output for relay control. At "power on", "H" and at "power off", "L".
22~28	EQ DISPLAY INPUT	Input for EQ display.
29	A-Vdd	+5 V power supply.
30	A-Vref	Reference voltage.
31	GND	Ground

Pin No.	Symbol	Description
32	OPEN	Not used !
33	Vss	This pin provides the ground potential.
34/35	X1/X2	Input and output for crystal oscillator.
36~38	PRESET A,B USER LED	Output to light up preset A, B or user LED. When selecting the desired mode, the corresponding output is "H".
39~43	PRESET 1,2,3,4,5 LED	Output to light up preset 1, 2, 3, 4 or 5 LED. When selecting the desired mode, the corresponding output is "H".
44	X-BASS LED	Output to light up X-BASS LED. At "x-bass on", "H" and at "x-bass off", "L".
45	P/D	Input for power down. (At "L", it is active)
46	DIGI-LINK	Input/Output for controlling digi-link.
47	GND	Ground
48	Vss	This pin provides the ground potential.
49~51	KEY INPUT	Input data for key scan.
52	Vdd	+5 V power supply.
53	OPEN	Not used !
54	X-BASS CONTROL	Output for X-BASS control. At "x-bass on", "L" and "x-bass off", "H".
55/56	VOL. UP/DOWN	Output to control volume motor.
57	VOL. LED	Output to light up volume LED. At "power on", "H", and at "power off", "L".
58	EQ DEFEAT LED	Output to light up EQ defeat LED. At "EQ defeat on", "H" and at "EQ defeat off", "L".
59	SEG p	Output for segment.
60	SEG a	Output for segment.
61~65	SEG b~SEG f	Output, for segment, and data output for key scan.
66~70	SEG g~SEG m	Output for segment.
71	Vload	-30 V power supply of the FL controller.
72	SEG n	Output for segment.
73~80	DIGIT 15~DIGIT 8	Output for grid.

MECHANICAL PARTS LIST

Ref. No.	Description	Part No.	Q'ty	Version
	PACKAGE			
	Box Carton (AV-757)	049605258201	1	KS
	Box Carton (AX-747)	049605258202		KS
	Box Carton (AV-757)	049605258206	1	A,D,PTINDO
	Box Carton (AX-747)	049605258205	1	A,D,PTINDO
	Cushion Poly	9722041210	1	
	Film Soft PE	9715000120	1	
	CABINET & CHASSIS			
1	Volume, Motor	3228020010	1	
2	Cover, Top	046123017811	1	
3	FIP, 15BW16Y	2328130931	1	
4	Switch, Tact	4658003710	16	
5	Jack, Phone	4438005510	1	
6	Indicator, LED	8555051310	3	
7	Button, Power	048545181011	1	
8	Body, Front	048521009711	1	
9	Window, Display	048553023511	1	
10	Panel, Front (AV-757)	048602019811	1	
(10)	Panel, Front (AX-747)	048602019812	1	
11	Badge, INKEL	048535045411	1	KS
(11)	Badge, SHERWOOD	048535045421	1	A,D,PT INDO
12	Knob, Volume	048643007611	1	
13	Button, Function	048543070011	1	
14	Button, EQ, Left	048545131111	1	
15	Button, EQ, Right	048545131121	1	
16	Button, EQ, Up/Down	048543070111	1	
17	Rubber Sponge	6715012010	1	
18	⚠ Power Transformer, 220 V, 60 Hz	2828100851	1	KS
(18)	⚠ Power Transformer, 230 V, 50 Hz	2828100931	1	D
(18)	⚠ Power Transformer, 110/220V, 50/60Hz	2828100921	1	PT INDO
(18)	⚠ Power Transformer, 120 V, 60 Hz	2828100951	1	A
19	Spacer, PCB	6705004220	1	
20	Chassis, Main	6121614910	1	
21	Rubber Foot	6035104410	2	
22	Fastener	6528301710	1	
23	Cushion, Foot	6715021230	2	
24	Terminal, Speaker, 4P (AV-757 ONLY)	4408105410	2	
25	Terminal, Speaker, 2P (AV-757 ONLY)	4408107010	1	
26	Fan, DC Brushless	5518103310	1	
27	Chassis, Back (AV-757)	046102044511	1	KS
(27)	Chassis, Back (AX-747)	046102044411	1	KS
(27)	Chassis, Back (AV-757)	046102044521	1	A
(27)	Chassis, Back (AX-747)	046102044421	1	A
(27)	Chassis, Back (AV-757)	046102044551	1	D
(27)	Chassis, Back (AX-747)	046102044451	1	D
(27)	Chassis, Back (AV-757)	046102044591	1	PT INDO
(27)	Chassis, Back (AX-747)	046102044491	1	PT INDO
28	Connector, Lead Ass'y	4358615503	1	
29	⚠ Cord, AC Power	4308009310	1	KS
(29)	⚠ Cord, AC Power	4308009220	1	A
(29)	⚠ Cord, AC Power	4308009520	1	D,PT INDO
30	Stopper, Connector	6518002210	1	
31	Stopper, Cord AC power	6518002310	1	
32	Plate, Ground	6165143510	1	A,D,KS
(32)	Switch, Slide	4618006510	1	PT INDO
33	Heatsink, Power	7503067220	1	
34	Heatsink, Regulator	7505206230	3	
35	Adapter	4428300410	1	PT INDO
(35)	Not Used !			A,D,KS
36	Jack RCA, 1P	4438113720	1	A,D,PT INDO
(36)	Not Used !			KS
	HARDWARE KIT			
S1	Screw, #B BTT 3x8B (AV-757)	8179130063	30	
(S1)	Screw, #B BTT 3x8B (AX-747)	8179130063	26	
S2	Screw, #B WPTT 3x6Y	8179230061	11	
S3	Screw, Heatsink AV-757)	8195000310	12	
(S3)	Screw, Heatsink (AX-747)	8195000310	6	
S4	Screw, #2 WPTC 3x10Y	8159230101	2	
S5	Screw, #2 WPTC 3x16Y	8159230161	1	
S6	Screw, Mecha	8155001210	1	
S7	Screw, #2 FTC 3x8B	8129230083	5	
S8	Screw, BSAM 4x8B	8109440083	4	
S9	Screw, BM 4x30B	8009140303	2	
S10	Screw, Ground	8155000710	2	D
(S10)	Not Used !			A,KS,PT INDO
N1	Nut, HEX Flanged M4Y	8209540011	1	

Ref. No.	Description	Part No.	Q'ty	Version
	MISCELLANEOUS			
	Card Cable, 21P, 220mm	4118621225	1	
	Card Cable, 21P, 120mm	4118621129	1	
PCB1	P.C.Board EQ	4005012710	1	
PCB2	P.C.Board Front	4005012700	1	
PCB3	P.C.Board Main	4001002800	1	
PCB4	P.C.Board Headphone	4001002820	1	
PCB5	P.C.Board Volume	4001002840	1	
PCB6	P.C.Board Volume LED	4001002830	1	
PCB7	P.C.Board Voltage	4001002810	1	

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol ⚠ in the parts list are of special significance to safety. When replacing a component identified with ⚠ , use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.

EXPLODED VIEW

Model No. : AX-747/AV-757

KS



29 CORD AC POWER 4308009310 1

A



29 CORD AC POWER 4308009220 1

D



29 CORD AC POWER 4308009520 1

PT-INDO



35 ADAPTER 4428300410 1
29 CORD AC POWER 4308009520 1

KS. A. D.



32 PLATE GROUND 6165143510 1

PT-INDO



32 SW SLIDE(VOL) 4618006510 1

PT-INDO. A. D.



36 JACK RCA 1P 4438113720 1

*** REMARK**
This marks (▭) is applied for only AV-757.

PRINTED CIRCUIT BOARDS

Model No. : AX-747/AV-757

EQ(PCB1)



FRONT(PCB2)



MAIN(PCB3)



VOLUME(PCB4)



VOLTAGE SEL. (PCB7)



HEADPHONE(PCB5)



VOLUME LED(PCB6)



ELECTRICAL PARTS LIST

PRODUCT SAFETY NOTICE : Products marked with ⚠ have special characteristics important to safety.
If you replace any of these components, read carefully the product safety notice in this manual.
Don't degrade the safety of the product through improper servicing.
Resistor/Capacitor tolerance – D : (±0.5%), J : (±5%), K : (±10%), M : (±20%), Z : +80, – 20%)

Ref. No.	Description						Part No.	Q'ty	Version
PCB1	**ASSEMBLY P.C.BOARD EQ**								
	CAPACITORS								
C102	Ceramic Tubular	100	pF	50 V	M		3519101935	1	
C103/C104	Electrolytic SG	4.7	uF	50 V	M		3479347971	2	
C105	Ceramic Tubular	100	pF	50 V	M		3519101935	1	
C107-C109	Electrolytic SG	4.7	uF	50 V	M		3479347971	3	
C111/C112	Electrolytic SG	0.33	uF	50 V	M		3479333871	2	
C113/C114	Electrolytic SG	47	uF	16 V	M		3479347031	2	
C115	Electrolytic SG	22	uF	25 V	M		3479222041	1	
C116/C117	Electrolytic SG	47	uF	16 V	M		3479347031	2	
C118	Ceramic Tubular	820	pF	50 V	J		3519821935	1	
C119	Ceramic Tubular	100	pF	50 V	M		3519101935	1	
C120	Ceramic Tubular	470	pF	50 V	J		3519471935	1	
C121	Electrolytic SG	47	uF	16 V	M		3479347031	1	
C122	Electrolytic SG	4.7	uF	50 V	M		3479347971	1	
C123	Ceramic Tubular	820	pF	50 V	J		3519821935	1	
C124	Ceramic Tubular	100	pF	50 V	M		3519101935	1	
C125	Ceramic Tubular	470	pF	50 V	J		3519471935	1	
C126	Electrolytic SG	4.7	uF	50 V	M		3479347971	1	
C127	Electrolytic SG	47	uF	16 V	M		3479347031	1	
C128	Electrolytic SG	47	uF	16 V	M		3479347031	1	A,D,PT INDO KS
(C128)	Not Used !							1	A,D,PT INDO KS
C129/C130	Mylar	0.0033	uF	100 V	J		3679332120	2	
C131/C132	Ceramic Tubular	330	pF	50 V	J		3519331935	2	
C133	Electrolytic SG	47	uF	16 V	M		3479347031	1	A,D,PT INDO KS
(C133)	Not Used !							1	A,D,PT INDO KS
C134/C135	Mylar	0.0082	uF	100 V	J		3679822120	2	
C136/C137	Ceramic Tubular	820	pF	50 V	J		3519821935	2	
C138/C139	Mylar	0.02	uF	100 V	J		3679203120	2	
C140/C141	Mylar	0.0022	uF	100 V	J		3679222120	2	
C142/C143	Electrolytic SG	47	uF	16 V	M		3479347031	2	
C144/C145	Mylar	0.0047	uF	100 V	J		3679472120	2	
C146/C147	Mylar	0.047	uF	100 V	J		3679473120	2	
C148/C149	Electrolytic SG	47	uF	16 V	M		3479347031	2	
C150	Ceramic Tubular	100	pF	50 V	M		3519101935	1	
C151/C152	Electrolytic SG	0.1	uF	50 V	M		3479310871	2	
C153/C154	Mylar	0.015	uF	100 V	J		3679153120	2	
C155/C156	Electrolytic SG	0.22	uF	50 V	M		3479322871	2	
C157/C158	Mylar	0.0047	uF	100 V	J		3679472120	2	
C159/C160	Electrolytic SG	0.68	uF	50 V	M		3479368871	2	
C161/C162	Mylar	0.1	uF	63 V	K		3679104297	2	
C163/C164	Electrolytic SG	47	uF	16 V	M		3479347031	2	
C165/C166	Ceramic Tubular	330	pF	50 V	J		3519331935	2	
C167	Ceramic Tubular	150	pF	50 V	J		3519151935	1	
C168	Electrolytic SG	22	uF	25 V	M		3479222041	1	A,D,PT INDO KS
(168)	Not Used !								
C169	Electrolytic SG	1	uF	50 V	M		3479310971	1	
C170	Electrolytic SG	2.2	uF	50 V	M		3479322971	1	
C171	Ceramic Tubular	47	pF	50 V	J		3519470935	1	
C172	Electrolytic SG	2.2	uF	50 V	M		3479322971	1	
C173	Ceramic Tubular	330	pF	50 V	J		3519331935	1	
C174	Electrolytic SG	1	uF	50 V	M		3479310971	1	
C175	Ceramic Tubular	330	pF	50 V	J		3519331935	1	
C176	Ceramic Tubular	150	pF	50 V	J		3519151935	1	
C177	Ceramic Tubular	47	pF	50 V	J		3519470935	1	
C178	Ceramic Tubular	100	pF	50 V	M		3519101935	1	A,D,PT INDO KS
(C178)	Not Used !								
C179/C180	Electrolytic SG	2.2	uF	50 V	M		3479322971	2	
C181-C184	Electrolytic SG	4.7	uF	50 V	M		3479347971	4	
C185-C187	Ceramic Tubular	0.047	uF	50 V	F		3519473935	3	
	CONNECTORS								
CNT102	Wafer, 4P						4428516310	1	
CNT103	Wafer, 15P						4428561520	1	
CNT104	Wafer, 9P						4428509820	1	
	DIODES								
D101/D102	1N4148, Switching						2058322101	2	
D103/D104	Zener, UZ 6.8 BSC						2258599121	2	
	INTEGRATED CIRCUITS								
IC101	LC7522						2168017122	1	
IC102-IC104	KIA4559S/KIA75559S						2168206103	3	

Ref. No.	Description						Part No.	Q'ty	Version
IC105	KIA4559S/KIA75559S						2168206103	1	A,D,PT INDO KS
(IC105)	Not Used !								
IC106	KIA4559S/KIA75559S						2168206103	1	
	TRANSISTORS								
Q101/Q102	KTC3198Y, NPN						2208606104	2	
Q103	DTC114YS						2208622106	1	A,D,PT INDO KS
(Q103)	Not Used !								
Q104	DTA114YS/KRM107M						2238006103	1	A,D,PT INDO KS
(Q104)	Not Used !								
Q105/Q106	KTC3198Y, NPN						2208606104	2	
Q107	KTD1302, NPN						2208606112	1	A,D,PT INDO KS
(Q107)	Not Used !								
Q108-Q121	KTC3198Y, NPN						2208606104	4	
Q122	DTA114YS/KRM107M						2238006103	1	
Q123	DTC114YS						2208622106	1	
Q124	KTC3198Y, NPN						2208606104	1	
	RESISTORS								
R101	Carbon Film	6.2	kohm	1/5 W	J		3069622970	1	
R102	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R103	Metal Film	270	ohm	1/5 W	J		3029271970	1	
R104	Carbon Film	6.8	kohm	1/5 W	J		3069682970	1	
R105/R106	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R107	Carbon Film	6.2	kohm	1/5 W	J		3069622970	1	
R108	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R109	Metal Film	270	ohm	1/5 W	J		3029271970	1	
R110	Carbon Film	6.8	kohm	1/5 W	J		3069682970	1	
R111/R112	Metal Film	1.5	kohm	1/5 W	J		3029152970	2	
R113/R114	Carbon Film	47	kohm	1/5 W	J		3069473970	2	
R115/R116	Metal Film	100	ohm	1/5 W	J		3029101970	2	
R117	Metal Film	4.7	kohm	1/5 W	J		3029472970	1	A,D,PT INDO KS
(R117)	Not Used !								
R118/R119	Metal Film	3.3	kohm	1/5 W	J		3029332970	2	
R120	Metal Film	220	ohm	1/5 W	J		3029221970	1	
R121	Carbon Film	470	kohm	1/5 W	J		3069474970	1	
R122/R123	Metal Film	10	ohm	1/5 W	J		3029100970	2	
R124	Carbon Film	8.2	kohm	1/5 W	J		3069822970	1	
R125	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R126	Metal Film	3.9	kohm	1/5 W	J		3029392970	1	
R127	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R128	Metal Film	4.7	ohm	1/5 W	J		3029479970	1	
R129-R131	Metal Film	1	kohm	1/5 W	J		3029102970	3	A,D,PT INDO KS
(R129-R131)	Not Used !								
R132/R133	Metal Film	3.3	kohm	1/5 W	J		3029332970	2	
R134	Carbon Film	8.2	kohm	1/5 W	J		3069822970	1	
R135	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R136	Metal Film	3.9	kohm	1/5 W	J		3029392970	1	
R137	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R138	Metal Film	4.7	ohm	1/5 W	J		3029479970	1	
R139	Metal Film	1	kohm	1/5 W	J		3029102970	1	A,D,PT INDO KS
(R139)	Not Used !								
R140/R141	Metal Film	100	ohm	1/5 W	J		3029101970	2	A,D,PT INDO KS
(R140/R141)	Not Used !								
R142	Metal Film	3.3	kohm	1/5 W	J		3029332970	1	A,D,PT INDO KS
(R142)	Not Used !								
R143	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R144	Metal Film	390	ohm	1/5 W	J		3029391970	1	
R145	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R146	Metal Film	1	kohm	1/5 W	J		3029102970	1	
R147	Metal Film	390	ohm	1/5 W	J		3029391970	1	
R148	Metal Film	1	kohm	1/5 W	J		3029102970	1	
R149/R150	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R151	Carbon Film	820	kohm	1/5 W	J		3069824970	1	
R152	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R153	Carbon Film	820	kohm	1/5 W	J		3069824970	1	
R154	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R155/R156	Metal Film	390	ohm	1/5 W	J		3029391970	2	
R157/R158	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R159/R160	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R161/R162	Carbon Film	820	kohm	1/5 W	J		3069824970	2	
R163	Metal Film	390	ohm	1/5 W	J		3029391970	1	
R164	Metal Film	470	ohm	1/5 W	J		3029471970	1	

Ref. No.	Description						Part No.	Q'ty	Version
R165/R166	Carbon Film	15	kohm	1/5 W	J		3069153970	2	
R167/R168	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R169	Carbon Film	47	kohm	1/5 W	J		3069473970	1	
R170/R171	Metal Film	390	ohm	1/5 W	J		3029391970	2	
R172/R173	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R174/R175	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R176	Metal Film	180	ohm	1/5 W	J		3029181970	1	
R177/R178	Carbon Film	820	kohm	1/5 W	J		3069824970	2	
R179/R180	Carbon Film	15	kohm	1/5 W	J		3069153970	2	
R181/R182	Metal Film	390	ohm	1/5 W	J		3029391970	2	
R183/R184	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R185/R186	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R187/R188	Carbon Film	820	kohm	1/5 W	J		3069824970	2	
R189/R190	Carbon Film	15	kohm	1/5 W	J		3069153970	2	
R191/R192	Metal Film	390	ohm	1/5 W	J		3029391970	2	
R193/R194	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R195	Carbon Film	27	kohm	1/5 W	J		3069273970	1	
R196/R197	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R198	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R199	Carbon Film	820	kohm	1/5 W	J		3069824970	1	
R900	Carbon Film	820	kohm	1/5 W	J		3069824970	1	
R901/R902	Carbon Film	15	kohm	1/5 W	J		3069153970	2	
R903/R904	Metal Film	390	ohm	1/5 W	J		3029391970	2	
R905/R906	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R907/R908	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R909/R910	Metal Film	100	ohm	1/5 W	J		3029101970	2	
R911/R912	Carbon Film	820	kohm	1/5 W	J		3069824970	2	
R913/R914	Carbon Film	15	kohm	1/5 W	J		3069153970	2	
R915/R916	Metal Film	1	kohm	1/5 W	J		3029102970	2	
R917/R918	Metal Film	390	ohm	1/5 W	J		3029391970	2	
R919/R920	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R921/R922	Carbon Film	820	kohm	1/5 W	J		3069824970	2	
R923/R924	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R925	Metal Film	1	kohm	1/5 W	J		3029102970	1	
R926	Carbon Film	8.2	kohm	1/5 W	J		3069822970	1	
R927	Carbon Film	220	kohm	1/5 W	J		3069224970	1	
R928	Carbon Film	8.2	kohm	1/5 W	J		3069822970	1	
R929	Carbon Film	100	kohm	1/5 W	J		3069104970	1	A,D,PT INDO KS
(R929)	Not Used !								
R930	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R931	Metal Film	1.5	kohm	1/5 W	J		3029152970	1	
R932/R933	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R934	Metal Film	1	kohm	1/5 W	J		3029102970	1	
R935	Carbon Film	8.2	kohm	1/5 W	J		3069822970	1	
R936	Carbon Film	220	kohm	1/5 W	J		3069224970	1	
R937	Carbon Film	8.2	kohm	1/5 W	J		3069822970	1	
R938	Metal Film	1	kohm	1/5 W	J		3029102970	1	A,D,PT INDO KS
(R938)	Not Used !								
R939	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R940	Metal Film	1.5	kohm	1/5 W	J		3029152970	1	
R942	Metal Film	1	kohm	1/5 W	J		3029102970	1	
R945	Metal Film	4.7	kohm	1/5 W	J		3029472970	1	
R946	Metal Film	3.3	kohm	1/5 W	J		3029332970	1	
R947	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R948	Carbon Film	27	kohm	1/5 W	J		3069273970	1	
R949	Metal Film	330	ohm	1/5 W	J		3029331970	1	
R950	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
	MISCELLANEOUS								
36	Jack RCA, 1P						4438113720	1	A,D,PT INDO KS
(36)	Not Used !								
PCB2	**ASSEMBLY P.C.BOARD FRONT**								
	CAPACITORS								
C202	Ceramic Tubular	470	pF	50 V	J		3519471935	1	
C203/C204	Mylar	0.0047	uF	100 V	J		3679472120	2	
C205/C206	Electrolytic SG	47	uF	16 V	M		3479347031	2	
C207	Ceramic Tubular	0.047	uF	50 V	F		3519473935	1	
C208	Mylar	0.033	uF	100 V	J		3679331120	1	
C209	Electrolytic SG	1	uF	50 V	M		3479310971	1	
C210/C211	Electrolytic SG	10	uF	50 V	M		3479310071	2	
C212	Mylar	0.033	uF	100 V	J		3679331120	1	
C213/C214	Mylar	0.015	uF	100 V	J		3679153120	2	
C215	Mylar	0.1	uF	100 V	J		3679332120	1	
C216/C217	Mylar	0.0056	uF	100 V	J		3679562120	2	
C218	Electrolytic SG	10	uF	50 V	M		3479310071	1	

Ref. No.	Description						Part No.	Q'ty	Version
C219	Electrolytic	0.047	uF	5.5 V			3439247315	1	
C220	Mylar	0.1	uF	100 V	J		3679332120	1	
C221	Electrolytic SG	10	uF	50 V	M		3479310071	1	
C222/C223	Mylar	0.0022	uF	100 V	J		3679222120	2	
C224/C225	Electrolytic SG	10	uF	50 V	M		3479310071	2	
C226/C227	Electrolytic SG	0.22	uF	50 V	M		3479322871	2	
C228/C229	Ceramic Tubular	820	pF	50 V	J		3519821935	2	
C230	Electrolytic SG	10	uF	50 V	M		3479310071	1	
C231	Electrolytic SG	0.47	uF	50 V	M		3479347971	1	
C232	Electrolytic SG	4.7	uF	50 V	M		3479347971	1	
	CONNECTORS								
CNT201	Wafer, FPC, 21P						4428526330	1	
CNT202	Wafer, 10P						4428810996	1	
	DIODES								
D201	Zener, UZ 5.1 BSB						2258599103	1	
D202-D218	1N4148, Switching						2058322101	17	
D219	Zener, UZ 6.2BSB						2258599105	1	
D220	Zener, UZ 7.5 BSC						2258599130	1	
D221	1N4148, Switching						2058322101	1	
LED201-203	LED, SLR-34URCF25, Red						2371124701	3	
LED204-208	LED, SLR-34GCF25, Green						2371124301	5	
LED209/210	LED, SLR-34URCF25, Red						2371124701	2	
	INTEGRATED CIRCUITS								
IC201	uPD78042						2139313111	1	
IC202/203	KA324						2168000113	2	
	TRANSISTORS								
Q201-Q212	DTC114YS						2208622106	12	
	RESISTORS								
R200	Metal Film	3.3	ohm	1/5 W	J		3029339970	1	
R201	Carbon Film	22	kohm	1/5 W	J		3069223970	1	
R202	Carbon Film	220	kohm	1/5 W	J		3069224970	1	
R203	Metal Film	270	ohm	1/5 W	J		3029271970	1	
R204/R205	Carbon Film	10	kohm	1/5 W	J		3069103970	2	
R206	Metal Film	3.3	ohm	1/5 W	J		3029339970	1	
R208	Carbon Film	10	kohm	1/5 W	J		3069103970	1	
R209/R210	Carbon Film	100	kohm	1/5 W	J		3069104970	2	
R211/R212	Carbon Film	62	kohm	1/5 W	J		3069623970	2	
R213	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R214	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R215/R216	Metal Film	3.3	kohm	1/5 W	J		3029332970	2	
R217	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R218	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R219	Carbon Film	100	kohm	1/5 W	J		3069104970	1	
R220/R221	Carbon Film	20	kohm	1/5 W	J		3069203970	2	
R222	Metal Film	3.3	kohm	1/5 W	J		3029332970	1	
R223	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R224	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R225	Carbon Film	62	kohm	1/5 W	J		3069623970	1	
R226	Metal Film	3.3	kohm	1/5 W	J		3029332970	1	
R227	Carbon Film	62	kohm	1/5 W	J		3069623970	1	
R228	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R229	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R230/R231	Carbon Film	20	kohm	1/5 W	J		3069203970	2	
R232/R233	Carbon Film	62	kohm	1/5 W	J		3069623970	2	
R235	Metal Film	270	ohm	1/5 W	J		3029271970	1	
R236/R237	Carbon Film	62	kohm	1/5 W	J		3069623970	2	
R238	Metal Film	270	ohm	1/5 W	J		3029271970	1	
R239	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R240-R242	Carbon Film	62	kohm	1/5 W	J		3069623970	3	
R243	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R244	Carbon Film	62	kohm	1/5 W	J		3069623970	1	
R245	Metal Film	3.3	kohm	1/5 W	J		3029332970	1	
R246	Carbon Film	62	kohm	1/5 W	J		3069623970	1	
R247	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R248	Metal Film	100	ohm	1/5 W	J		3029101970	1	
R249/R250	Carbon Film	20	kohm	1/5 W	J		3069203970	2	
R251	Carbon Film	75	kohm	1/5 W	J		3069753970	1	
R252	Metal Film	3.3	kohm	1/5 W	J		3029332970	1	
R253	Carbon Film	15	kohm	1/5 W	J		3069153970	1	
R254/R255	Metal Film	100	ohm	1/5 W	J		3029101970	2	
R256	Carbon Film	20	kohm	1/5 W	J		3069203970	1	
R257	Carbon Film	680	kohm	1/5 W	J		3069684970	1	

Ref. No.	Description	Part No.	Q'ty	Version
R259	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R260	Carbon Film 20 kohm 1/5 W J	3069203970	1	
R262-R266	Metal Film 270 ohm 1/5 W J	3029271970	5	
R267	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R268	Carbon Film 100 kohm 1/5 W J	3069104970	1	
R269	Carbon Film 12 kohm 1/5 W J	3069123970	1	
	MISCELLANEOUS			
X-TAL201	Crystal, CST4.19MHz	3938101880	1	
3	FIP, 15BW16Y	2328130931	1	
4	Switch, Tact	4658003710	16	
PCB3	**ASSEMBLY P.C.BOARD MAIN**			
	CAPACITORS			
C301	Electrolytic SG 47 uF 50 V M	3479347071	1	
C302-C304	Not Used !			
C305	Mylar 0.047 uF 100 V J	3679473120	3	
C306	Not Used !			
C307	Electrolytic SG 10 uF 50 V M	3479310071	1	
C308	Mylar 0.047 uF 100 V J	3679473120	1	
(C308)	Not Used ! (AX-747)			
C309	Mylar 0.047 uF 100 V J	3679473120	1	
C310	Electrolytic HS 4700 uF 50 V M	3419547225	1	
C311	Mylar 0.047 uF 100 V J	3679473120	1	
(C311)	Not Used ! (AX-747)			
C312-C315	Mylar 0.047 uF 100 V J	3679473120	4	
C316	Ceramic Tubular 220 pF 50 V J	3519221935	1	
(C316)	Not Used ! (AX-747)			
C317	Ceramic Tubular 220 pF 50 V J	3519221935	1	
C318	Mylar 0.047 uF 100 V J	3679473120	1	
C319	Electrolytic SD 4700 uF 25 V M	3409347248	1	
C321	Electrolytic HS 4700 uF 50 V M	3419547225	1	
C322	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
(C322)	Not Used ! (AX-747)			
C323	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
C325	Electrolytic SG 2200 uF 25 V M	3409322249	1	
C326	Electrolytic SG 10 uF 50 V M	3479310071	1	
(C326)	Not Used ! (AX-747)			
C327	Mylar 0.047 uF 100 V J	3679473120	1	
C328	Ceramic Tubular 220 pF 50 V J	3519221935	1	
C329	Ceramic Tubular 220 pF 50 V J	3519221935	1	
(C329)	Not Used ! (AX-747)			
C330	Electrolytic SG 1 uF 50 V M	3479310971	1	
C331	Mylar 0.047 uF 100 V J	3679473120	1	
(C331)	Not Used ! (AX-747)			
C332	Electrolytic SG 100 uF 16 V M	3479310131	1	
C333	Ceramic Tubular 470 pF 50 V J	3519471935	1	
C334	Electrolytic SG 220 uF 16 V M	3479322131	1	
C335	Mylar 0.047 uF 100 V J	3679473120	1	
C337	Ceramic Tubular 220 pF 50 V J	3519221935	2	
(C337)	Not Used ! (AX-747)			
C338	Ceramic Tubular 220 pF 50 V J	3519221935	2	
C339	Electrolytic SG 10 uF 50 V M	3479310071	1	
(C339)	Not Used ! (AX-747)			
C340/C341	Electrolytic SG 10 uF 50 V M	3479310071	2	
C342	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
(C342)	Not Used ! (AX-747)			
C343	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
C344	Ceramic Tubular 220 pF 50 V J	3519221935	2	
(C344)	Not Used ! (AX-747)			
C345	Ceramic Tubular 220 pF 50 V J	3519221935	2	
C346	Ceramic Tubular 12 pF 50 V J	3519120935	1	
(C346)	Not Used ! (AX-747)			
C347	Ceramic Tubular 3.3 pF 50 V J	3519033935	1	
(C347)	Not Used ! (AX-747)			
C348	Mylar 0.047 uF 100 V J	3679473120	1	
(C348)	Not Used ! (AX-747)			
C349	Electrolytic SA 470 uF 6.3 V M	3479247111	1	
C350/C351	Electrolytic SG 10 uF 50 V M	3479310071	2	
C352	Ceramic Tubular 12 pF 50 V J	3519120935	2	
C353	Ceramic Tubular 12 pF 50 V J	3519120935	2	
(C353)	Not Used ! (AX-747)			
C354	Ceramic Tubular 27 pF 50 V J	3519270935	1	
(C354)	Not Used ! (AX-747)			
C355	Ceramic Tubular 3.3 pF 50 V J	3519033935	1	
C356/C357	Electrolytic SG 47 uF 16 V M	3479347031	2	

Ref. No.	Description	Part No.	Q'ty	Version
(C356/C357)	Not Used ! (AX-747)			
C358	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
(C358)	Not Used ! (AX-747)			
C359	Ceramic Tubular 3.3 pF 50 V J	3519033935	1	
(C359)	Not Used ! (AX-747)			
C360	Electrolytic SG 0.47 uF 50 V M	3479347971	1	
(C360)	Not Used ! (AX-747)			
C361	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
(C361)	Not Used ! (AX-747)			
C362	Ceramic Tubular 27 pF 50 V J	3519270935	1	
C363	Not Used ! (AX-747)			
C364/C365	Electrolytic SG 0.47 uF 50 V M	3479347971	2	
C366	Ceramic Tubular 27 pF 50 V J	3519270935	1	
C367	Ceramic Tubular 470 pF 50 V J	3519471935	1	
(C367)	Not Used ! (AX-747)			
C368	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
C369	Electrolytic SG 0.47 uF 50 V M	3479347971	1	
(C369)	Not Used ! (AX-747)			
C370	Ceramic Tubular 12 pF 50 V J	3519120935	1	
C371/C372	Ceramic Tubular 470 pF 50 V J	3519471935	2	
C373	Ceramic Tubular 3.3 pF 50 V J	3519033935	1	
C374	Ceramic Tubular 470 pF 50 V J	3519471935	1	
(C374)	Not Used ! (AX-747)			
C375	Ceramic Tubular 0.001 uF 50 V M	3519102935	1	
C376/C377	Electrolytic SG 47 uF 16 V M	3479347031	2	
C378-C379	Not Used !			
C381	Ceramic Tubular 0.1 uF 50 V F	3519104935	1	
C382	Not Used !			
	CONNECTORS			
CNT201	Wafer, FPC, 21P	4428526330	1	
CNT301	Wafer LV, 3P	4428525790	1	
CNT302	Wafer, 3P	4428505710	1	
CNT304	Wafer, 6P	4428505810	1	
CNT306	Wafer, 2P	4428508210	1	
CNT307	Wafer, 15P	4428551520	1	
CNT309	Wafer, 15P	4428525360	1	
	DIODES			
D301	1N4148, Switching	2058322101	1	
D302	Zener, UZ 30.0 BSD	2258599128	1	
D303	Zener, UZ 6.2 BSB	2258599105	1	
D304-D312	1N4003, Rectifier	2258128002	9	
D313	1N5402, Rectifier	2058100136	1	
D314	1N4148, Switching	2058322101	1	
(D314)	Not Used ! (AX-747)			
D315	1N5402, Rectifier	2058100136	1	
D316	1N4148, Switching	2058322101	1	
D317/D318	1N5402, Rectifier	2058100136	2	
D319	Zener, UZ 11.0 BSC	2258599122	1	
D320-D324	1N4148, Switching	2058322101	5	
(D320-D324)	Not Used ! (AX-747)			
D325	1N4148, Switching	2058322101	1	
(D325)	Not Used ! (AX-747)			
D326	1N4148, Switching	2058322101	1	
D327	1N4148, Switching	2058322101	1	
(D327)	Not Used ! (AX-747)			
D328	Zener, UZ 11.0 BSC	2258599122	1	
D329	Zener, UZ 5.1 BSB	2258599103	1	
D330-D335	1N4148, Switching	2058322101	6	
D336	Zener, UZ 27 BSC	2258599115	1	
(D336)	Not Used ! (AX-747)			
D337/D338	1N4148, Switching	2058322101	2	
D339	Zener, UZ 27 BSC	2258599115	1	
	INTEGRATED CIRCUITS			
IC301	KTB1367Y/2SB1367Y, NPN	2028106109	1	
IC302	KA7912, Regulator	2168602113	1	
IC303	KA7805, Regulator	2108499104	1	
	COILS			
L301/L302	Inductor, 0.5 uH	2648001010	2	
(L301/L302)	Not Used ! (AX-747)			
L303/L304	Inductor, 0.5 uH	2648001010	2	
	TRANSISTORS			
Q301	MPSA56Y, PNP	2208206113	1	

Ref. No.	Description	Part No.	Q'ty	Version
Q302	DTC114YS	2208622106	1	
Q303	KSC2690, NPN	2008602102	1	
(Q303)	Not Used ! (AX-747)			
Q304	KSC2690, NPN	2008602102	1	
Q305	KSA1220, PNP	2008202101	1	
Q306	KSA1220, PNP	2008202101	1	
(Q306)	Not Used ! (AX-747)			
Q307	KTC3198Y, NPN	2208606104	1	
Q308	KTC3198Y, NPN	2208606104	1	
(Q308)	Not Used ! (AX-747)			
Q309	KTC3198Y, NPN	2208606104	1	
Q311	KSA1220, PNP	2008202101	1	
(Q311)	Not Used ! (AX-747)			
Q312	KSA1220, PNP	2008202101	1	
Q314/Q315	KTC3198Y, NPN	2208606104	2	
Q316	MPSA56Y, PNP	2208206113	1	
Q317	KTC3198Y, NPN	2208606104	1	
Q318	KSC2690, NPN	2008602102	1	
(Q318)	Not Used ! (AX-747)			
Q319	KSC2690, NPN	2008602102	1	
Q320/Q321	KTC3198Y, NPN	2208606104	2	
Q322	DTC114YS	2208622106	1	
(Q322)	Not Used ! (AX-747)			
Q323	DTA114YS/KRM107M	2238006103	1	
Q324	KTA1024, PNP	2208206115	1	
(Q324)	Not Used ! (AX-747)			
Q325	DTA114YS/KRM107M	2238006103	1	
(Q325)	Not Used ! (AX-747)			
Q326	DTC114YS	2208622106	1	
Q327	DTA114YS/KRM107M	2238006103	1	
Q328	KTC3198Y, NPN	2208606104	1	
Q329	KTC3198Y, NPN	2208606104	1	
(Q329)	Not Used ! (AX-747)			
Q330	KTD1302, NPN	2208606112	1	
(Q330)	Not Used ! (AX-747)			
Q331	KTA1024, PNP	2208206115	1	
(Q331)	Not Used ! (AX-747)			
Q332	KTA1024, PNP	2208206115	1	
Q333	KTC3206, NPN	2208606118	1	
Q334/Q335	KTC3206, NPN	2208606118	2	
(Q334/Q335)	Not Used ! (AX-747)			
Q336	KTC3198Y, NPN	2208606104	1	
(Q336)	Not Used ! (AX-747)			
Q337	KTC3198Y, NPN	2208606104	1	
Q338	KTC3198Y, NPN	2208606104	1	
(Q338)	Not Used ! (AX-747)			
Q339/Q340	KTC3198Y, NPN	2208606104	2	
Q341	KTC3198Y, NPN	2208606104	1	
(Q341)	Not Used ! (AX-747)			
Q342	KTC2240/BKTC3200, NPN	2208606108	1	
(Q342)	Not Used ! (AX-747)			
Q343	KTC3206, NPN	2208606118	1	
Q344	KTA1024, PNP	2208206115	1	
Q345	KTC2240/BKTC3200, NPN	2208606108	1	
(Q345)	Not Used ! (AX-747)			
Q346/Q347	KTC3198Y, NPN	2208606104	2	
Q348	KTD1302, NPN	2208606112	1	
(Q348)	Not Used ! (AX-747)			
Q349	DTA114YS/KRM107M	2238006103	1	
(Q349)	Not Used ! (AX-747)			
Q350/Q351	KTC2240/BKTC3200, NPN	2208606108	2	
Q352-Q355	KTC2240/BKTC3200, NPN	2208606108	4	
(Q352-Q355)	Not Used ! (AX-747)			
Q356	DTC114YS	2208622106	1	
(Q356)	Not Used ! (AX-747)			
Q357/Q358	KTD1302, NPN	2208606112	2	
Q359	DTC114YS	2208622106	1	
Q360/Q361	DTA114YS/KRM107M	2238006103	2	
Q371	2SD718/KTD718, NPN	2028407109	1	
Q372	2SC4137, Bias	2008622110	1	
Q373	2SB688/KTB688, PNP	2028107106	1	
Q374	2SD718/KTD718, NPN	2028407109	1	
Q375	2SC4137, Bias	2008622110	1	
Q376	2SB688/KTB688, PNP	2028107106	1	
Q377	2SD2059/KTD2059, NPN	2028406123	1	
Q378	2SC4137, Bias	2008622110	1	
Q379	KTB1367Y/2SB1367Y, NPN	2028106109	1	

Ref. No.	Description	Part No.	Q'ty	Version
Q380	2SD718/KTD718, NPN	2028407109	1	
Q381	2SC4137, Bias	2008622110	1	
Q382	2SB688/KTB688, PNP	2028107106	1	
	RESISTORS			
R301	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R302	Metal Film 10 ohm 1 W J	3029100470	1	
R303	Metal Film 100 ohm 1/5 W J	3029101970	1	
R304	Mylar 0.047 uF 100 V J	3679473120	1	
(R304)	Not Used ! (AX-747)			
R305-R308	Metal Film 22 ohm 1/5 W J	3029220970	4	
(R305-R308)	Not Used ! (AX-747)			
R309	Carbon Film 20 kohm 1/5 W J	3069203970	1	
R310	Metal Film 10 ohm 1 W J	3029100470	1	
R311-R314	Metal Film 22 ohm 1/5 W J	3029220970	14	
R315	Metal Film 10 ohm 1 W J	3029100470	1	
(R315)	Not Used ! (AX-747)			
R316	Metal Film 180 ohm 1/5 W J	3029181970	1	
R317	Carbon Film 100 kohm 1/5 W J	3069104970	1	
R318	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R319	Cement 0.39 ohm 5 W J	3059039776	1	
(R319)	Not Used ! (AX-747)			
R320	Cement 0.39 ohm 5 W J	3059039776	1	
R321	Metal Film 1 kohm 1/5 W J	3029102970	1	
R322	Metal Film 2.7 kohm 1/5 W J	3029272970	1	
(R322)	Not Used ! (AX-747)			
R323	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
(R323)	Not Used ! (AX-747)			
R324	Metal Film 330 ohm 1/5 W J	3029331970	1	
R325	Metal Film 2.7 kohm 1/5 W J	3029272970	1	
R326	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R326)	Not Used ! (AX-747)			
R327	Metal Film 220 ohm 1/5 W J	3029221970	1	
R328	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R329	Metal Film 470 ohm 1/5 W J	3029471970	1	
R330	Metal Film 47 ohm 1/5 W J	3029470970	1	
R331	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R332	Metal Film 470 ohm 1/5 W J	3029471970	1	
R333	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R334	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R335	Metal Film 220 ohm 1/5 W J	3029221970	1	
(R335)	Not Used ! (AX-747)			
R336	Carbon Film 15 kohm 1/5 W J	3069153970	1	
(R336)	Not Used ! (AX-747)			
R337	Metal Film 220 ohm 1/5 W J	3029221970	1	
R338	Metal Film 470 ohm 1/5 W J	3029471970	1	
R339	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R340	Metal Film 220 ohm 1/5 W J	3029221970	1	
R341	Carbon Film 15 kohm 1/5 W J	3069153970	1	
(R341)	Not Used ! (AX-747)			
R342	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
(R342)	Not Used ! (AX-747)			
R343	Metal Film 33 ohm 1 W J	3029330570	1	
R344	Cement 0.39 ohm 5 W J	3059039776	1	
(R344)	Not Used ! (AX-747)			
R345	Cement 0.39 ohm 5 W J	3059039776	1	
R346	Metal Film 22 ohm 1/5 W J	3029220970	1	
R347	Metal Film 1 kohm 1/5 W J	3029102970	1	
R348	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R348)	Not Used ! (AX-747)			
R349	Metal Film 100 ohm 1/5 W J	3029101970	1	
R350	Metal Film 2.7 kohm 1/5 W J	3029272970	1	
(R350)	Not Used ! (AX-747)			
R351	Metal Film 2.7 kohm 1/5 W J	3029272970	1	
R352	Metal Film 330 ohm 1/5 W J	3029331970	1	
(R352)	Not Used ! (AX-747)			
R353	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R354	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R355	Metal Film 1.5 kohm 1/5 W J	3029152970	1	
R356	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R358	Carbon Film 33 kohm 1/5 W J	3069333970	1	
(R358)	Not Used ! (AX-747)			
R359	Carbon Film 12 kohm 1/5 W J	3069123970	1	
(R359)	Not Used ! (AX-747)			
R360	Carbon Film 33 kohm 1/5 W J	3069333970	1	
(R360)	Not Used ! (AX-747)			
R361/R362	Carbon Film 12 kohm 1/5 W J	3069123970	2	

Ref. No.	Description	Part No.	Q'ty	Version
(R361/R362)	Not Used ! (AX-747)			
R363	Metal Film 330 ohm 1/5 W J	3029331970	1	
R364	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R365	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R366	Metal Film 330 ohm 1/5 W J	3029331970	1	
R367	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R368	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R369	Carbon Film 6.8 kohm 1/5 W J	3069682970	1	
R370	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R371	Metal Film 220 ohm 1/5 W J	3029221970	1	
(R371)	Not Used ! (AX-747)			
R372	Carbon Film 6.8 kohm 1/5 W J	3069682970	1	
R374	Carbon Film 15 kohm 1/5 W J	3069153970	1	
R375	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R376/R377	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R378	Metal Film 120 ohm 1/5 W J	3029121970	1	
(R378)	Not Used ! (AX-747)			
R379	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R379)	Not Used ! (AX-747)			
R380	Metal Film 2.2 kohm 1 W J	3029222470	1	
(R380)	Not Used ! (AX-747)			
R381	Carbon Film 15 kohm 1/5 W J	3069153970	1	
R382	Metal Film 120 ohm 1/5 W J	3029121970	1	
(R382)	Not Used ! (AX-747)			
R383	Metal Film 120 ohm 1/5 W J	3029121970	1	
R384	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R385/R386	Metal Film 120 ohm 1/5 W J	3029121970	2	
(R385/R386)	Not Used ! (AX-747)			
R387	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R387)	Not Used ! (AX-747)			
R388	Metal Film 1 kohm 1/5 W J	3029102970	1	
R389/R390	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
(R389/R390)	Not Used ! (AX-747)			
R391	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R391)	Not Used ! (AX-747)			
R392	Carbon Film 10 kohm 1/5 W J	3069103970	1	
(R392)	Not Used ! (AX-747)			
R393	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R394	Carbon Film 2 kohm 1/5 W J	3069202970	1	
(R394)	Not Used ! (AX-747)			
R395	Carbon Film 10 kohm 1/5 W J	3069103970	1	
(R395)	Not Used ! (AX-747)			
R396	Carbon Film 2 kohm 1/5 W J	3069202970	1	
(R396)	Not Used ! (AX-747)			
R397	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R397)	Not Used ! (AX-747)			
R398	Carbon Film 33 kohm 1/5 W J	3069333970	1	
(R398)	Not Used ! (AX-747)			
R399	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R400	Metal Film 1 kohm 1/5 W J	3029102970	1	
R401	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R401)	Not Used ! (AX-747)			
R402	Carbon Film 2 kohm 1/5 W J	3069202970	1	
R403	Metal Film 390 ohm 1/5 W J	3029391970	1	
(R403)	Not Used ! (AX-747)			
R404	Metal Film 1 kohm 1/5 W J	3029102970	1	
(R404)	Not Used ! (AX-747)			
R405	Metal Film 120 ohm 1/5 W J	3029121970	1	
R406	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R407	Carbon Film 2 kohm 1/5 W J	3069202970	1	
R408	Carbon Film 33 kohm 1/5 W J	3069333970	1	
(R408)	Not Used ! (AX-747)			
R409	Metal Film 390 ohm 1/5 W J	3029391970	1	
(R409)	Not Used ! (AX-747)			
R410	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R411	Metal Film 2.2 kohm 1 W J	3029222470	1	
R412	Metal Film 1 kohm 1/5 W J	3029102970	1	
R413	Metal Film 120 ohm 1/5 W J	3029121970	1	
R414/R415	Metal Film 1.2 kohm 1/5 W J	3029122970	2	
(R414/R415)	Not Used ! (AX-747)			
R416	Carbon Film 2 kohm 1/5 W J	3069202970	1	
(R416)	Not Used ! (AX-747)			
R417	Metal Film 1 kohm 1/5 W J	3029102970	1	
R418	Carbon Film 2 kohm 1/5 W J	3069202970	1	
(R418)	Not Used ! (AX-747)			
R419	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R420	Metal Film 3.3 kohm 1/5 W J	3029332970	1	

Ref. No.	Description	Part No.	Q'ty	Version
(R420)	Not Used ! (AX-747)			
R421	Metal Film 120 ohm 1/5 W J	3029121970	1	
R422	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R423	Carbon Film 33 kohm 1/5 W J	3069333970	1	
(R423)	Not Used ! (AX-747)			
R424	Metal Film 390 ohm 1/5 W J	3029391970	1	
R425	Carbon Film 2 kohm 1/5 W J	3069202970	1	
R426/R427	Carbon Film 33 kohm 1/5 W J	3069333970	2	
R428	Carbon Film 33 kohm 1/5 W J	3069333970	1	
(R428)	Not Used ! (AX-747)			
R429	Metal Film 1.8 kohm 1/5 W J	3029182970	1	
R430	Metal Film 390 ohm 1/5 W J	3029391970	1	
R431	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R432	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
(R432)	Not Used ! (AX-747)			
R433	Metal Film 1 kohm 1/5 W J	3029102970	1	
R434	Carbon Film 2 kohm 1/5 W J	3069202970	1	
R435/R436	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R437	Metal Film 1.8 kohm 1/5 W J	3029182970	1	
R438	Metal Film 1 kohm 1/5 W J	3029102970	1	
R439	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R440	Metal Film 1 kohm 1/5 W J	3029102970	1	
	FUSES			
F301/302	⚠T 1.6 A, 250 V	5508302335	2	A,D,PT INDO
(F301/302)	⚠NB 1.5 A, 250 V	5508202230	2	KS
F303/304	⚠T 1 A, 250 V	5508302035	2	A,D,PT INDO
(F303/304)	⚠NB 1 A, 250 V	5508100851	2	KS
	MISCELLANEOUS			
RLY301	⚠Relay, OSA-SS-212DM3	5528001750	1	
GND301	Terminal Ground	4235007310	1	
24	Terminal, Speaker, 4P	4408105410	2	
25	Terminal, Speaker, 2P	4408107010	1	
34	Heatsink, Regulator	7505206230	3	
PCB4	**ASSEMBLY P.C.BOARD VOLUME**			
	CAPACITORS			
C501	Electrolytic SG 100 uF 16 V M	3479310131	1	
C502	Electrolytic SG 47 uF 16 V M	3479347031	1	
C503	Ceramic Tubular 0.01 uF 16 V M	3519103915	1	
C504	Electrolytic SG 47 uF 16 V M	3479347031	1	
	CONNECTORS			
CNT501	Wafer, 2P	4428508210	1	
CNT202	Wafer, 10P	4428810995	1	
CNT101	Wafer, 21P	4428526750	1	
	TRANSISTORS			
Q501	DTC114YS	2208622106	1	
Q502/Q503	KTA1015Y/BKTA1266, PNP	2208206105	2	
Q504/Q505	KTC3198Y, NPN	2208606104	2	
	RESISTORS			
R501/R502	Metal Film 1 kohm 1/5 W J	3029102970	2	
R503	Metal Film 220 ohm 1/5 W J	3029221970	1	
R505/R506	Metal Film 1 kohm 1/5 W J	3029102970	2	
R507	Metal Film 1.5 kohm 1/5 W J	3029152970	1	
R508/R509	Metal Film 1 kohm 1/5 W J	3029102970	2	
R510/R511	Metal Film 4.7 kohm 1/5 W J	3029472970	2	
	MISCELLANEOUS			
VR501	Semi Fixed Resistor, 50 k(B)	3248050353	1	
1	Volume, Motor	3228020010	1	
PCB5	**ASSEMBLY P.C.BOARD HEADPHONE**			
C601-C603	CAP, Ceramic Tu 0.022 pF 25 V J	3519223520	3	
CNT105	Connector, Lead Ass'y, 4P, 300mm	436204303332	1	
D601	Diode, 1N4148, Switching	2058322101	1	
5	Jack, Phone	4438005510	1	
PCB6	**ASSEMBLY P.C.BOARD VOLUME LED**			
CNT701	Connector, Lead Ass'y, 2P, 140mm	435102143481	1	
LED701	LED, SLH-34K-3	2308220142	1	

Ref. No.	Description	Part No.	Q'ty	Version
PCB7	**ASSEMBLY P.C.BOARD VOLTAGE**			
C801	Not Used !			
CNT801	Connector, Wafer LV, 4P	4428525780	1	A,D,PT INDO
(CNT801)	Connector, Wafer LV, 2P	4428525800	1	PT INDO
CNT802	Connector, Wafer LV, 2P	4428100291	1	
F801	⚠Fuse, T 2A, 250V	5508302435	1	PT INDO
(F801)	Not Used !			A,D,KS
F802	⚠Fuse, T 3.15A, 250V	5508302735	1	A,D,KS
(F802)	⚠Fuse, NB 3.5A, 250V	5508202830	1	PT INDO
32	Plate, Ground	6165143510	1	A,D,KS
(32)	Switch, Slide	4618006510	1	PT INDO

IC FUNCTIONAL BLOCK DIAGRAM

IC101 : LC7522



IC102/IC103 : KA324



IC102, IC103, IC104, IC105, IC106 : KIA4559S/KIA75559S



IC302 : KA7912



IC303 :KA7805



SCHEMATIC DIAGRAM I

Model No. : AX-747/AV-757

FRONT(PCB2)

EQ(PCB1)

NOTES

1. Resistor values are indicated in ohms unless otherwise specified (K=1,000 M=1,000,000)
2. Capacitor values are indicated in microfarades unless otherwise specified. (p=micro-microfarades)

CAUTION

Safety precaution to be followed during servicing

1) Since those parts marked with ⚠ are critical parts for safety, use only the one described in the parts list.
2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

FRONT "R"ch SIGNAL

REAR SIGNAL

CENTER SIGNAL

SCHEMATIC DIAGRAM II



PIN CONNECTION OF TRANSISTORS, DIODES AND ICS.

KTD1302 KTC2240/KTC3200 KTC3198/KTC1815 KTA1266/KTA1015Y	MPSA56Y	DTA114YS DTC114YS	KTA949/KTA1024	2SC4137 KSC2690A KSA1220A	KTB688 KTD718	2SB1367 2SD2059	ZENER IN5402 IN4003 IN4148
							

G	H	I	J	K	L	M

	F301/F302	F303/F304	F801	F802
KOR	NB1.5A/250V	NB1A/250V	-	NB3.5A/250V
EUROPE	T1.6A/250V	T1A/250V	-	T3.15A/250V
USA	T1.6A/250V	T1A/250V	-	T3.15A/250V
PT-INDO	T1.6A/250V	T1A/250V	T2A/250V	T3.15A/250V

SURROUND SIGNAL

CENTER SIGNAL

CENTER AMP

REAR SPEAKER 303

CENTER SPEAKER 302

FRONT SPEAKER 301

FAN

VOLTAGE SEL. (PCB7)

ONLY VERSION

CNT201 TO FRONT B'D

CNT309 TO TUNER SYSTEM CNT

DIGI-LINK

FROM TRANS

FRONT "R"ch SIGNAL

SURROUND SIGNAL

CENTER SIGNAL

ER 402 003 48 Anode Cathode	SLR-34GCF25 SLR-34URCF25 SLM-34K-3 Cathode Anode	KIA7805 IN GND OUT	KIA7912 GND IN OUT	KIA4559S/KIA75559S 1 9	KA324 14 1 7	LC7522 28 1 14	MPD78042

WIRING DIAGRAM



G	H	I	J	K	L


PCB3
MAIN B'D
4001002800B
BAR CODE
CNT103
B'D TO B'D
CONNECTOR
PCB1
EQ B'D 4005012710B
BAR CODE
CNT102
CNT101
CNT104
FROM TX-747/TX-757
SYSTEM CONNECTOR, 9P
WHITE
AX747
PCB2
CNT202
B'D TO B'D
CONNECTOR
PCB4
CNT501
CNT202
VOLUME B'D
40010028408
WHITE
AX747
CNT101
CARD CABLE, 21P(AV-757)
CARD CABLE, 14P(AX-747)
PCB6
4001002830B
WHITE

■ TX-757/747 ■

SPECIFICATIONS

*** Preparation :** Output voltage setting at speaker terminal for measrement is 2 V (Input : VIDEO, 1kHZ. 250MV)

FM SECTION

* Measurement Condition

- Antenna input impedance: 75 ohms

Version	USA/Canada ("A")	Europe ("D")	Korea ("KS")	Multi ("PT INDO")
RF Signal	98.1 MHz	98.0 MHz	98.1 MHz	98.0 MHz

No.	Description		Unit	Nominal	Limit
1	Tuning Frequency Range	KS, A D, PT INDO	MHz	87.5 - 107.9 87.5 - 108.0	
2	Scaning Frequency Interval	KS, A D, PT INDO	kHz	200 50	
3	FM De-emphasis	KS, A D, PT INDO	uS	75 50	
4	Usable Sensitivity 90.1/106.1 MHz, Stereo Mode, S/N=30 dB		uV	≤1.5	≤3
5	50 dB Quieting Sensitivity S/N=50 dB (IHF BPF)		uV	≤50	
6	Signal to Noise Ratio, 75 kHz Dev.	MONO STEREO (BPF)	dB	≥73 ≥70	≥67 ≥64
7	Total Harmonic Distortion at 1 kHz, 75 kHz Dev.	MONO STEREO (BPF)	%	≤0.2 ≤0.4	≤0.4 ≤0.8
8	Stereo Threshold		uV	10±2	10±4
9	Muting Threshold		uV	10±2	10±4
10	Output Voltage with 1 kHz, DOLBY Tape (TCC-130) (Referance voltage setting: speaker output 2 V)		mV	4000±400	4000±600
11	Memory Holding Time		week	≥4	
12	Stereo Separation at 1 kHz, 98 MHz (IHF BPF)		dB	≥45	≥40

AM SECTION

* Measurement Condition

- RF Signal: 999 kHz, 5 mV/m or 207 kHz, 5 mV/m
- MOD.: 400 Hz, 30%

No.	Description		Unit	Nominal	Limit
1	Tuning Frequency Range	KS A PT INDO D	kHz	522~1611 520~1710 520/522~1710/1611 522~1611, 153~279	
2	Scaning Frequency Interval	KS, D A PT INDO	kHz	9 10 9/10	
3	Usable Sensitivity, S/N=20 dB, 30% Mod.	600/1400 kHz 162/252 kHz	uV/m	≤600 ≤1000	≤1000 ≤1300
4	Signal to Noise Ratio, 30% Mod.	999 kHz, 400 Hz 207 kHz, 400 Hz	dB	≥40 ≥35	≥36 ≥30
5	Output Voltage, 400 Hz, 30% Mod., 5mV/m (Referance voltage setting: speaker output 2 V)	DOLBY Tape TCC-130	mV	1500±400	1500±600
6	Search Level		uV/m	600±100	600±200

VIDEO SECTION (TX-757 ONLY)

No.	Description	Unit	Nominal	Limit
1	Input Sensitivity/Impedance (75 Ω)	dB	1Vp-p ± 0.5	1Vp-p ± 1
2	Output Voltage/Impedance (75 Ω)	dB	1Vp-p ± 0.5	1Vp-p ± 1
3	Frequency Response at ∓3 dB	Hz	10~6M	20~5M
4	Crosstalk at 1.0 MHz	dB	≥50	≥45
5	Signal to Noise Ratio at 1 MHz, Input shorted	dB	≥50	≥45

INPUT SECTION

No.	Description	Unit	Nominal	Limit
1	Input Sensitivity			
	TV/AUX etc. (Impedance : 47 kohms) **TX-757**	mV	250±20	250±40
	AUX (Inpedance : 49 kohms) **TX-747**			
	MIC (Impedance: 600 ohms)		2.5±0.2	2.5±0.5
2	Output Voltage at TAPE REC	mV	250±20	250±40

BLOCK DIAGRAM I

Model No : TX-747



BLOCK DIAGRAM II

Model No : TX-757



DISASSEMBLY PROCEDURES

REFER TO PAGES 39 AND 52.

[1] COVER TOP REMOVAL.
Remove 5 screws (S2) (05 to 09) and then remove the Cover Top (30).

[2] FRONT PANEL ASSEMBLY REMOVAL
1. Remove the Cover Top (30), referring to then previous step [1].
2. Remove the Card Cable from wafer (CNT701) on the Main P.C.Board (PCB1)
3. Disconnect (CNT401) from the Main P.C.Board (PCB5).
4. Remove 7 screws (S2) (01 to 04), (S1) (01 to 03) and then remove the Front Panel Assembly (AA).

[3] MIC P.C.BOARD (PCB3) REMOVAL
1. Remove the Cover Top (30), referring to the previous step [1].
2. Remove the Front Panel Assembly (AA), referring to the previous step [2].
3. Remove 2 screw (S3) (01, 02) and then remove the Mic PC.Board (PCB3)

[4] FRONT P.C.BOARD (PCB2) REMOVAL
1. Remove the Cover Top (30), referring to the prvious step[1].
2. Remove the Front Panel Assembly (AA), reffering to the previous step [2].
3. Remove 9 screws (S2) (23 to 31) and then remove the Front P.CB.oard (PCB2).

[5] RMC P.C.BOARD (PCB5) REMOVAL
1. Remove the Cover Top (30), referring to the prvious step[1].
2. Remove the Front Panel Assembly (AA), reffering to the previous step [2].
3. Remove screw (S2) (22) and then remove (PCB5) by pressing the hooks arround it outward.

[6] MAIN P.C.BOARD (PCB1) REMOVAL
1. Remove the Cover Top (30), referring to the previous step [1].
2. Remove the Card Cable from wafer(CNT701) on the Main P.C.Board(PCB1).
3. Disconnect (CNT401, CNT102, CNT105) from the Main P.C.Board(PCB1).
4. Disconnect (CP501) from the Voltage P.C.Board (PCB4).
5. Remove 2 screw (S4) (03), (S5) (01) on the Main P.C.Board(PCB1).
6. Remove 9 screws (S2) (14 to 20, 11, 21) from the Chassis Back (25) (TX-757).
   Remove 6 screw (S2) (14, 15, 19, 20, 21,11) from the Chassis Back (25) (TX-747).

[7] VOLTAGE P.C.BOARD(PCB4) REMOVAL
1. Remove the Cover Top (30), referring to the previous step [1].
2. Disconnect (CP501) from the Voltage P.C.Board(PCB4).
3. Remove 2 screws (S4) (01, 02).
4. Remove the Fastener (13) and then remove the Voltage P.C.Board(PCB4).

CIRCUIT DESCRIPTION

IC701 : CXP82324 (CMOS 8bit 1-Chip Microcomputer)

1. Pin Connection Diagram



2. Block Diagram



3. Input and Output Terminal Functions

<table>
<tr><th>Pin No.</th><th>Symbol</th><th>Description</th></tr>
<tr><td>79, 80, 1</td><td>STEP SEL</td><td>Input to select frequency band and step according to regions.
<table>
<tr><th>Region</th><th>Frequency</th><th>Step</th><th>79</th><th>80</th><th>1</th></tr>
<tr><td>Korea</td><td>FM: 87.5~107.9 MHz
AM: 522~1611 kHz</td><td>200 kHz
9 kHz</td><td>L</td><td>H</td><td>H</td></tr>
<tr><td>PT INDO</td><td>FM: 87.5~108 MHz
AM: 522~1611 kHz
520~1710 kHz</td><td>50 kHz
9 kHz
10 kHz</td><td>L</td><td>L</td><td>H</td></tr>
<tr><td>Europe</td><td>FM: 87.5~108 MHz
AM: 522~1611 kHz
153~279 kHz</td><td>50 kHz
9 kHz
9 kHz</td><td>L</td><td>L</td><td>L</td></tr>
<tr><td>USA/Canada</td><td>FM: 87.5~107.9 MHz
AM: 520~1710 kHz</td><td>200 kHz
10 kHz</td><td>L</td><td>H</td><td>L</td></tr>
</table></td></tr>
<tr><td>2</td><td>RMC IN</td><td>Input for remote control signal.(At "L", it is active)</td></tr>
<tr><td>3</td><td>MODEL</td><td>Input to segment, and data output for key scan.</td></tr>
<tr><td>4</td><td>ST-NJU9701</td><td>Chip enable output for NJM9701.</td></tr>
<tr><td>5</td><td>ST-TC9176</td><td>Chip enable output for TC9176.</td></tr>
<tr><td>6</td><td>DIGI-LINK</td><td>Output/Input for communication with other sets.</td></tr>
<tr><td>7, 8</td><td>MODE CONTROL</td><td>Output to select prologic mode.
<table>
<tr><th>Pin No.</th><th>Normal</th><th>Wide</th><th>Phantom</th></tr>
<tr><td>7</td><td>H</td><td>L</td><td>L</td></tr>
<tr><td>8</td><td>L</td><td>H</td><td>L</td></tr>
</table></td></tr>
<tr><td>9</td><td>TEST TONE MUTE</td><td>Output is "H" when the test tone mode is being activated.</td></tr>
<tr><td>10~12</td><td>NOISE SEQUENCER</td><td>Output to select noise sequence in prologig mode.</td></tr>
<tr><td>13</td><td>NC</td><td>Not Used !</td></tr>
<tr><td>14</td><td>CH. CONTROL</td><td>Output to select the channel mode in NJM2177.</td></tr>
<tr><td>15, 16</td><td>VIDEO CONTROL</td><td>Output to select the video signal in LA7952.
<table>
<tr><th>Pin No.</th><th>VCR1</th><th>VCR2</th><th>VCD</th></tr>
<tr><td>15</td><td>H</td><td>L</td><td>L</td></tr>
<tr><td>16</td><td>L</td><td>H</td><td>H</td></tr>
</table></td></tr>
<tr><td>17</td><td>BY-PASS CONTROL</td><td>Output to allow the audio signal to by-pass dolby decoder IC NJM2177.
At "L" the signal is by-passed.</td></tr>
<tr><td>18</td><td>ST-LC7821</td><td>Chip enable output for LC7821.</td></tr>
<tr><td>19~21</td><td>KEY INPUT</td><td>Data input for key scan.</td></tr>
<tr><td>22</td><td>ST-BY</td><td>When power is on, control data output is "H".
When power is off, control data output is "L".</td></tr>
<tr><td>23/24</td><td>DA/CK</td><td>Data/Clock output for LC7821, NJM9701 and TC9176.</td></tr>
<tr><td>25</td><td>STEREO</td><td>Input to light "STEREO" indicator.(At "L", it is active)</td></tr>
<tr><td>26</td><td>S/M</td><td>Input to detect RF level of station during tuning.</td></tr>
<tr><td>27</td><td>VCD CHECK</td><td>Input to detect CDC ("H") or VCDC ("L").</td></tr>
<tr><td>28</td><td>FM MODE</td><td>Output to select FM MONO or STEREO.
At "H", FM MONO is selected and at "L", FM STEREO is selected.</td></tr>
<tr><td>29</td><td>T-MUTE</td><td>Output for tuner mute.(At "H", it is active)</td></tr>
<tr><td>30</td><td>RST</td><td>Input to reset CPU.</td></tr>
<tr><td>31</td><td>EXTAL</td><td>Input for crystal oscillator.</td></tr>
</table>

Pin No.	Symbol	Description
32	XTAL	Output for crystal oscillator.
33	Vss	Ground
34	ST-LM7001	Chip enable output for LM7001.
35/36	DA/CK	Data/Clock output for LM7001.
37～41	NC	Not Used !
42～49	SEGMENT	Segment signal output for FIP.
50～54	SEGMENT/ KEY SCAN	Segment signal output for FIP and Data output for key scan.
55～57	SEGMENT	Segment signal output for FIP.
58	NC	Not Used !
59～70	GRID	Grid signal output for FIP.
71	Vfdp	Power supply for FIP controller.
72	Vdd	+5V Power supply.
73	NC	Not Used ! (Connected to Vdd)
74～77	NC	Not Used !
78	P/D	Input to detect power down.(At "H", it is active)

ALIGNMENT PROCEDURES

1. Equipment Required

- AM Standard Signal Generator (AM SSG)
- Oscilloscope
- AC Voltmeter
- FM Standard Signal Generator (FM SSG)
- Stereo Modulator
- Audio Generator
- Distortion Meter
- DC Voltmeter
- Frequency Counter

Note: Disconnect external FM antenna prior to alignment.

2. Alignment and Test Points (PCB1)



3. AM IF and RF Alignment

Preparation

1. Output of Signal Generator should not be higher than necessary to obtain an optimum output reading.

Step	Signal Generator Frequency	Receiver Frequency on the Display	Equipment Connection	Adjustment point	Adjust for
1	999 kHz (400 Hz, Mod.)	522 kHz	DC Voltmeter TP1	T802	1.1 V reading
	207 kHz (400 Hz, Mod.)	153 kHz	DC Voltmeter TP1	T809	1.8 V reading
2	594 kHz (400 Hz, Mod.)	594 kHz	AC Voltmeter to speaker terminal	T801 (ANT Coil)	Maximum reading
3	1404 kHz (400 Hz, Mod.)	1404 kHz	AC Voltmeter to speaker terminal	T801 (ANT Trimmer)	Maximum reading
4	450 kHz (400 Hz, Mod.)	999 kHz	AC Voltmeter to speaker terminal	T805 (IFT)	Maximum reading
5	999 kHz (400 Hz, Mod.)	999 kHz	DC Voltmeter TP3	VR801	FL display 'TUNED' Indication on receiver with AM SSG output level of 800μV/m 1.4V reading
6	162 kHz (400 Hz, Mod.)	162 kHz	speaker terminal	T808	Maximum reading
7	252 kHz (400 Hz, Mod.)	252 kHz	speaker terminal	TC803	Maximum reading



AM Alignment Connection

4. FM IF Alignment

Preparation

1. Signal Generator output should be no higher than necessary to obtain an optimum output reading.
2. Switch Press to FM.
3. Signal generator deviation : 40 kHz (D, PT Version) or 75kHz (A, KS Version)

Step	Signal Generator Frequency	Receiver Frequency on the Display	Equipment Connection	Adjustment point	Adjust for
1	98.0 MHz (1 kHz, Mod.)	98.0 MHz	Distortion meter to speaker terminal	T804	Maximum distortion
2	98.0 MHz (1 kHz, Mod.)	98.0 MHz	DC Voltmeter to TP3	VR802	FL display 'TUNED' Indication on receiver with FM SSG output level of 10μV 1.3V reading
3	98.0 MHz (1 kHz, Mod.)	98.0 MHz	DC Voltmeter to TP2 & TP5	T803	Zero reading on DC voltmeter.



FM RF/IF and MPX Alignment Connection

5. MPX Alignment

Preparation

1. Switch:Press to FM.
2. Tuner for 98 MHz on band.
3. Signal Generator output level:1000μV.
4. Deviation:40 kHz (D, PT Version) or 75kHz (A, KS Version) at 100% modulation of composite signal.
5. Connect Signal Generator to FM antenna terminal through FM dummy antenna (75Ω).

Step	19 kHz Modulation Level	Signal Generator Frequency Setting	Equipment Connection	Adjustment point	Adjust for
1	Pilot off	Carrier only	Frequency counter connect to TP4	VR803	76 kHz ± 50 Hz
2	8% Mod.	Composite to channel 1 kHz R	AC voltmeter to R channel speaker terminal	-	Setting 0dB reference
3	8% Mod.	Composite to channel 1 kHz L	AC voltmeter to R channel speaker terminal	VR804	AC voltmeter reading should be at least 40 dB below.
4	8% Mod.	Composite to channel 1 kHz R	AC voltmeter to R channel speaker terminal	VR804	Same as Step 3.
	If you could not obtain -40 dB readings in Steps 3 and 4 (compared with Step 2), readjust VR804 until you obtain -40 dB readings for both Steps 3 and 4. Nominal is -45dB.				

TROUBLESHOOTING

Symptom	Cause and Remedy
Unit inoperative (FL indicator does not light)	A) Filament resistor R723 or R722 is Blown. Replace the resistor. B) Check the CNT104 (Pin No. 1, 2, 3) and CNT701 (Pin No. 1, 2, 3).
FM inoperative	A) Defective front-end. Replace. B) Defective FM switch. Replace the switch. C) PLL IC(LM7001) Malfunction. Replace the IC(LM7001). D) Defective coil T803 or T804. Replace the coil(s). E) Defective lead-in. Repair or replace the lead-in. F) Ceramic filter CF801, CF802 defective. Replace the defective ceramic filter(s). G) Defective controller circuit component. Replace.
Poor multiplex separation	A) Improper adjustment. Readjust VR803 and VR804. (Refer to MPX Alignment.) B) IC803 defective. Replace. C) Variable resistor VR803 or VR804 defective. Replace the variable resistor(s).
STEREO indicator does not light	A) Defective indicator in FL. Replace. B) Improper adjustment of VR803 of tuner board. Make readjustment. C) Defective IC803 Replace the defective component.
FM volume not sufficient	A) If volume from both L and R channels is not loud enough: Front - end section defective. Faulty C801, Coil T803. Defective C838 of tuner Board. If sound of one channel is not loud enough: Defective T806, T807
FM Mono has no effect	A) Defective FM MODE switch. Replace.

Symptom	Cause and Remedy
AM inoperative	A) Damaged IC801 of tuner board. Replace. B) Defective T801, T802, T805 or CF804 of tuner board. Replace the defective component(s). C) Resistor R829, R822 defective. Replace the defective component(s). D) Capacitor C857, C818, C822 defective. Replace the defective capacitor(s). E) Defective AM switch. Replace. F) Defective varicap diode VD1, VD2. Replace Varicap diode(s). G) Damaged AM loop antenna. Repair or replace. H) Defective controller circuit component. Replace.
Auto tune inoperative (UP/DOWN)	A) Poor contact in Up/Down key. Repair or replace. B) Defective IC701. Replace. C) Defective tuner circuit component. Replace. D) In case of FM only, improper adjustment of FM front-end. Readjust.
Manual tune inoperative(UP/DOWN) (AM or FM)	A) Poor contact in Up/Down key. Replace. B) Defective IC701. Replace.
Memory setting inoperative	A) Poor contact in memory set key. Replace. B) Defective IC701. Replace the defective component.
FL inoperative	A) FL defective. Replace. B) Defective IC701. Replace. C) Defective X701. Replace.
Remote Control Unit inoperative	A) Weak Battery. Replace. B) Defective. Replace. C) Defective IC701(CPU). Replace.

MECHANICAL PARTS LIST

Model No. : TX-757

Ref. No.	Description	Part No.	Q'ty	Version
	PACKAGE			
	Box Carton	049605258301	1	KS
	Box Carton	049605258304	1	D,PT INDO,A
	Poly Bag	9705001550	1	
	Cushion Poly	9722041410	1	
	Film Soft PE	9715000120	1	
	ACCESSORIES			
	Assembly Commander	541810127015	1	KS
	Assembly Commander	541810127025	1	D,PT INDO,A
	Battery 1.5V AA(R6M)	5518001610	1	KS
	FM Antenna Wire Dipole	4348000320	1	KS,PT INDO,A
	FM Antenna Cord	4348001110	1	D
	Cord RCA, 1P	4328206410	1	KS,PT INDO
	Manual Instruction	9007018440	1	KS
	Manual Instruction	9007018441	1	PT INDO
	Manual Instruction	9007018451	1	D
	Manual Instruction	9007018443	1	A
	Antenna AM Loop Stand Strip Wire	2608207361	1	KS,PT INDO,A
	Antenna AM Loop Stand Type	2608207360	1	D
	CABINET & CHASSIS			
1	Badge, INKEL	048535045411	1	KS
(1)	Badge, SHERWOOD	048535045421	1	A,D,PT INDO
2	Panel Front	048602020111	1	KS
(2)	Panel Front	048602020131	1	A,D,PT INDO
3	Window Display	048553023512	1	
4	Body Front	048521009511	1	
5	Button Function	048543070012	1	
6	Button Input, 1 key	048545131311	2	
7	Button Mode, 2 key	048545131411	1	
8	Jack Phone	4438005510	1	KS,PT INDO
(8)	Not Used !			A,D
9	Shield Fence	6165146110	1	KS,PT INDO
(9)	Not Used !			A,D
10(VR401)	Volume Mic	3208052410	1	KS,PT INDO
(10)	Not Used !			A,D
11	Foot & Rubber	6035104310	2	
12	Fastener, 12H	6528301710	2	KS,PT INDO
(12)	Fastener, 12H	6528301710	1	A,D
13	Fastener, 19H	6528300210	2	
14	Spacer PCB	6705004220	1	
15	Cushion Foot	6715021230	2	
16	Chassis Main	6121614930	1	
17	Heatsink Regulator TR.	7505206210	1	
18	Jack RCA, 2P	4438103020	1	
19	Jack RCA, 9P	4438114510	1	
20	Jack RCA, 2P	4438103010	1	
21	Terminal Antenna, 4P	4408107120	1	A,KS,PT INDO
(21)	Terminal Antenna, 4P	4408108220	1	D
22	Shield Plate	6165151910	1	A,KS,PT INDO
(22)	Not Used !			D
23	Stopper Connector	6518002210	1	
24	Stopper Connector	6518002110	1	
25	Chassis Back	046102045411	1	KS
(25)	Chassis Back	046102045491	1	PT INDO
(25)	Chassis Back	046102045421	1	A
(25)	Chassis Back	046102045451	1	D
26	Cover Top	046123018011	1	
27	Shield Fence, Front-end	6163115510	1	A,KS,PT INDO
(27)	Not Used !			D
28	Switch Tact	4658003710	14	
29	Switch Tact	4658004010	1	
30	Sponge Rubber	6715012010	1	
31	Knob Rotary	048545131511	1	KS,PT INDO
(31)	Not Used !			A,D
	HARDWARE KIT			
S1	Screw, #2FTC 3x8B	8129230083	5	
S2	Screw, #BBTT 3x8B	8179130083	32	KS,PT INDO
(S2)	Screw, #BBTT 3x8B	8179130083	31	A,D
S3	Screw, Mecha	8155001210	2	KS,PT INDO
(S3)	Not Used !			A,D
S4	Screw, #BWPTT 3x6Y	8179230061	3	
S5	Screw, #2WPTC 3x14Y	8159230141	1	
	MISCELLANEOUS			
	Card Cable, 13P, 140mm	4118613145	1	
	Card Cable, 20P, 200mm	4118620205	1	
	Connector, System, 13P, 500mm	4358613501	1	
	Connector, System, 9P, 500mm	4358609501	1	
PCB1	P.C.Board Main	4004001500	1	
PCB2	P.C.Board Mic (KS, PT INDO AREA ONLY)	4004001530	1	
PCB3	P.C.Board Power	4005512700	1	
PCB4	P.C.Board Front	4004001510	1	
PCB5	P.C.Board RMC	4004001520	1	

Model No. : TX-747

Ref. No.	Description	Part No.	Q'ty	Version
	PACKAGE			
	Box Carton	04960525830	1	KS
	Box Carton	04960525830	1	D,PT INDO
	Poly Bag	9705001550	1	
	Cushion Poly	9722041410	1	
	Film Soft PE	9715000120	1	
	ACCESSORIES			
	Assembly Commander	41810126015	1	KS
	Assembly Commander	41810126025	1	D,PT INDO
	Battery 1.5V AA(R6M)	5518001610	1	KS
	FM Antenna Wire Dipole	4348000320	1	KS,PT INDO
	FM Antenna Cord	4348001110	1	D
	Cord RCA, 1P	4328206410	1	KS,PT INDO
	Manual Instruction	9007018450	1	KS
	Manual Instruction	9007018452	1	PT INDO
	Manual Instruction	9007018451	1	D
	Antenna AM Loop Stand Strip Wire	2608207361	1	KS,PT INDO
	Antenna AM Loop Stand Type	2608207360	1	D
	CABINET & CHASSIS			
1	Badge, INKEL	04853504541	1	KS
(1)	Badge, SHERWOOD	04853504542	1	A,D,PT INDO
2	Panel Front	04860202012	1	A,KS,PT INDO
(2)	Panel Front	04860202014	1	D
3	Window Display	04855302351	1	
4	Body Front	04852100951	1	
5	Button Function	04854307001	1	
6	Button Input, 1 key	04854513131	2	
7	Not Used !			
8	Jack Phone	4438005510	1	
9	Shield Fence	6165146110	1	
10	Volume Mic	3208052410	1	
11	Foot & Rubber	6035104310	2	
12	Fastener, 12H	6528301710	2	
13	Fastener, 19H	6528300210	2	
14	Spacer PCB	6705004220	1	
15	Cushion Foot	6715021230	2	
16	Chassis Main	6121614930	1	
17	Heatsink Regulator TR	7505206210	1	A,KS,PT INDO
(17)	Not Used !			D
18	Not Used !			
19	Not Used !			
20	Jack RCA, 2P	4438103010	1	
21	Terminal Antenna, 4P	4408107120	1	A,KS,PT INDO
(21)	Terminal Antenna, 4P	4408108220	1	D
22	Shield Plate	6165151910	1	A,KS,PT INDO
(22)	Not Used !			D
23	Stopper Connector	6518002210	1	
24	Stopper Connector	6518002110	1	
25	Chassis Back	046102045311	1	KS,PT INDO
(25)	Chassis Back	046102045391	1	A
(25)	Chassis Back	046102045351	1	D
26	Cover Top	046123018011	1	
27	Shield Fence, Front-end	6163115510	1	A,KS,PT INDO
(27)	Not Used !			D
28	Switch Tact	4658003710	11	
29	Switch Tact	4658004010	1	
30	Sponge Rubber	6715012010	1	
31	Knob Rotary	048545131511	1	A,KS,PT INDO
(31)	Not Used !			D
	HARDWARE KIT			
S1	Screw, #2FTC 3x8B	8129230083	5	
S2	Screw, #BBTT 3x8B	8179130083	29	KS,PT INDO
(S2)	Screw, #BBTT 3x8B	8179130083	28	A,D
S3	Screw, Mecha	8155001210	2	A,KS,PT INDO
(S3)	Not Used !			D
S4	Screw, #BWPTT 3x6Y	8179230061	3	
S5	Screw, #2WPTC 3x14Y	8159230141	1	
	MISCELLANEOUS			
	Card Cable, 20P, 200mm	4118620205		
	Connector, System, 13P, 500mm	4358613501		
	Connector, System, 9P, 500mm	4358609501		
PCB1	P.C.Board Main	4004001500		
PCB2	P.C.Board Mic (KS, PT INDO AREA ONLY)	4004001530		
PCB3	P.C.Board Power	4005512700		
PCB4	P.C.Board Front	4004001510		
PCB5	P.C.Board RMC	4004001520		

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol ⚠ in the parts list are of special significance to safety. When replacing a component identified with ⚠ , use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.

EXPLODED VIEW

Model No : TX-757/747



***REMARK**

The marks (▭) is applied for only TX-757.

PRINTED CIRCUIT BOARDS

Model No : TX-757/747

MAIN (PCB1)



MIC (PCB3)



POWER (PCB4)



FRONT (PCB2)



RMC (PCB5)



ELECTRICAL PARTS LIST

PRODUCT SAFETY NOTICE : Products marked with ⚠ have special characteristics important to safety.
If you replace any of these components, read carefully the product safety notice in this manual.
Don't degrade the safety of the product through improper servicing.
Resistor/Capacitor tolerance – D : (±0.5%), J : (±5%), K : (±10%), M : (±20%), Z : +80, – 20%)

Model No. : TX-757

Ref. No.	Description				Part No.	Q'ty	Version
PCB1	ASSEMBLY P.C.BOARD MAIN						
	CAPACITORS						
C100/C101	Chip	0.1	uF	50 V Z	3539104060	2	
C102	Chip, CH	100	pF	50 V J	3539101210	1	
C103	Chip	0.047	uF	50 V Z	3539473060	1	
C104	Electrolytic SG	1	uF	50 V M	3479310971	1	
C105	Chip	0.047	uF	50 V Z	3539473060	1	
C107	Chip, CH	220	pF	50 V J	3539221210	1	KS,PT INDO D,A
(C107)	Not Used !						
C108	Electrolytic SG	10	uF	35 V M	3479310061	1	
C110	Chip, CH	220	pF	50 V J	3539221210	1	KS,PT INDO D,A
(C110)	Not Used !						
C111/C112	Electrolytic SG	47	uF	16 V M	3479347031	2	
C113	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C114	Electrolytic SG	10	uF	35 V M	3479310061	1	
C115-C128	Chip CH	100	pF	50 V J	3539101210	14	D KS,PT INDO,A
(C115-C128	Not Used !						
C201-C203	Electrolytic SG	10	uF	35 V M	3479310061	3	
C204/C205	Electrolytic SG	470	uF	10 V M	3479347121	2	
C206	Electrolytic SG	100	uF	16 V M	3479310131	1	
C207	Chip	0.047	uF	50 V Z	3539473060	1	
C301	Mylar	0.047	uF	100 V J	3679473120	1	
C302/C303	Mylar	0.1	uF	63 V K	3679104297	2	
C304	Chip, CH	680	pF	50 V J	3539681210	1	
C305	Mylar	0.047	uF	100 V J	3679473120	1	
C306	Electrolytic SG	22	uF	16 V M	3479322031	1	
C307-C309	Electrolytic SG	10	uF	35 V M	3479310061	3	
C310	Electrolytic SG	22	uF	16 V M	3479322031	1	
C311	Chip	0.005	uF	50 V K	3539472820	1	
C312	Electrolytic SG	0.47	uF	50 V M	3479347871	1	
C313/C314	Electrolytic SG	4.7	uF	50 V M	3479347971	2	
C315	Electrolytic SG	0.22	uF	50 V M	3479322871	1	
C316	Electrolytic SG	10	uF	35 V M	3479310061	1	
C317	Electrolytic SG	220	uF	16 V M	3479322131	1	
C318	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C319	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C320	Chip	0.006	uF	50 V K	3539562820	1	
C321	Electrolytic SG	220	uF	10 V M	3479322121	1	
C322	Mylar	0.047	uF	100 V J	3679473120	1	
C323	Chip, CH	470	pF	50 V J	3539471210	1	
C324	Chip	0.005	uF	50 V J	3539472820	1	
C325	Chip	0.006	uF	50 V K	3539562820	1	
C326	Mylar	0.68	uF	63 V K	3679684297	1	
C327-C329	Mylar	0.22	uF	63 V K	3679224297	3	
C330/C331	Electrolytic SG	4.7	uF	50 V M	3479347971	2	
C332	Mylar	0.22	uF	63 V K	3679224297	1	
C333-C336	Chip	0.1	uF	50 V Z	3539104060	4	
C337/C338	Chip	0.022	uF	50 V K	3539223820	2	
C339/C340	Mylar	0.1	uF	63 V K	3679104297	2	
C341	Chip, CH	680	pF	50 V J	3539681210	1	
C342	Chip	0.006	uF	50 V K	3539562820	1	
C343	Electrolytic SG	1	uF	50 V M	3479310971	1	
C344	Chip	0.006	uF	50 V K	3539562820	1	
C345	Chip, CH	470	pF	50 V J	3539471210	1	
C346	Chip	0.1	uF	50 V Z	3539104060	1	
C347	Electrolytic SG	47	uF	16 V M	3479347031	1	
C348/C349	Mylar	0.047	uF	100 V J	3679473120	2	
C350	Chip	0.1	uF	50 V Z	3539104060	1	
C351	Chip	0.003	uF	50 V K	3539332820	1	
C352	Chip, CH	470	pF	50 V J	3539471210	1	
C353	Electrolytic SG	220	uF	10 V M	3479322121	1	
C354	Chip	0.1	uF	50 V Z	3539104060	1	
C355/C356	Chip, CH	270	pF	50 V J	3539271210	2	
C357/C358	Chip, CH	100	pF	50 V J	3539101210	2	
C359	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C360	Chip	0.1	uF	50 V Z	3539104060	1	
C361	Electrolytic SG	47	uF	16 V M	3479347031	1	
C362	Chip, CH	100	pF	50 V J	3539101210	1	
C363	Chip, CH	680	pF	50 V J	3539681210	1	
C364	Electrolytic SG	0.47	uF	50 V M	3479347871	1	
C365	Chip	0.1	uF	50 V Z	3539104060	1	
C366	Electrolytic SG	47	uF	16 V M	3479347031	1	
C367	Chip, CH	100	pF	50 V J	3539101210	1	
C368	Chip, CH	680	pF	50 V J	3539681210	1	
C369	Electrolytic SG	47	uF	16 V M	3479347031	1	
C370	Chip, CH	100	pF	50 V J	3539101210	1	
C371	Electrolytic SG	1	uF	50 V M	3479310971	1	
C372	Electrolytic SG	47	uF	16 V M	3479347031	1	
C373	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C374	Electrolytic SG	0.47	uF	50 V M	3479347871	1	
C711	Chip, CH	470	pF	50 V J	3539471210	1	
C712	Electrolytic SG	1	uF	50 V M	3479310971	1	
C801	Electrolytic SG	100	uF	16 V M	3479310131	1	
C802	Chip	0.047	uF	50 V Z	3539473060	1	
C803	Chip, CH	33	pF	50 V J	3539330210	1	
C804	Chip	0.01	uF	50 V K	3539103820	1	
C805	Chip, CH	33	pF	50 V J	3539330210	1	
C806-C809	Chip	0.047	uF	50 V Z	3539473060	4	
C810	Electrolytic SG	47	uF	16 V M	3479347031	1	
C811-C813	Chip, CH	100	pF	50 V J	3539101210	3	
C814	Chip, CH	330	pF	50 V J	3539331210	1	
C815	Electrolytic SG	1	uF	50 V M	3479310971	1	
C816	Chip	0.047	uF	50 V Z	3539473060	1	
C817	Electrolytic SG	10	uF	35 V M	3479310061	1	
C818	Electrolytic SG	3.3	uF	50 V M	3479333971	1	
C819	Electrolytic SG	2.2	uF	50 V M	3479322971	1	
C820	Chip	0.022	uF	50 V K	3539223820	1	
C821	Chip	0.047	uF	50 V Z	3539473060	1	
C822	Mylar	0.047	uF	100 V J	3679473120	1	
C823	Chip, CH	470	pF	50 V J	3539471210	1	
C824	Electrolytic SG	3.3	uF	50 V M	3479333971	1	
C825	Electrolytic SG	1	uF	50 V M	3479310971	1	
C826	Chip	0.047	uF	50 V Z	3539473060	1	
C827	Electrolytic SG	0.22	uF	50 V M	3479322871	1	
C828/C829	Chip	0.01	uF	50 V K	3539103820	2	
C830	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C831	Electrolytic SG	47	uF	16 V M	3479347031	1	
C832	Chip	0.047	uF	50 V Z	3539473060	1	
C833	Electrolytic SG	47	uF	16 V M	3479347031	1	
C834/C835	Chip	0.047	uF	50 V Z	3539473060	2	
C837	Electrolytic SG	10	uF	35 V M	3479310061	1	
C838	Chip	0.047	uF	50 V Z	3539473060	1	
C839	CeramicTubular	0.001	uF	50 V K	3519102935	1	
C840	Chip	0.047	uF	50 V Z	3539473060	1	
C841	Chip, CH	470	pF	50 V J	3539471210	1	
C842	Electrolytic SG	4.7	uF	50 V M	3479347971	1	
C843	Electrolytic SG	100	uF	16 V M	3479310131	1	
C844	Electrolytic SG	100	uF	10 V M	3479310121	1	
C845	Chip	120	pF	50 V J	3539121210	1	
C846	Chip	0.002	uF	50 V K	3539152820	1	KS,A
(C846)	Chip	0.001	uF	50 V K	3539102820	1	D,PT INDO
C847	Chip	0.002	uF	50 V K	3539152820	1	KS,A
(C847)	Chip	0.001	uF	50 V K	3539102820	1	D,PT INDO
C848	Electrolytic SG	2.2	uF	50 V M	3479322971	1	
C849	Chip	0.002	uF	50 V K	3539222820	1	
C850	Electroiytic SG	2.2	uF	50 V M	3479322971	1	
C851	Chip	0.002	uF	50 V K	3539222820	1	
C852	Chip, CH	15	pF	50 V J	3539150210	1	
C853	Chip	0.047	uF	50 V Z	3539473060	1	D KS,PT INDO,A
(C853)	Not Used !						
C854	Chip	0.047	uF	50 V Z	3539473060	1	D KS,PT INDO,A
(C854)	Not Used !						
C855	Chip, CH	180	pF	50 V J	3539181210	1	D KS,PT INDO,A
(C855)	Not Used !						
C856	Chip, CH	33	pF	50 V J	3539330210	1	D KS,PT INDO,A
(C856)	Not Used !						
C857	Chip, CH	470	pF	50 V J	3539471210	1	
C858/C859	Chip, CH	100	pF	50 V J	3539101210	2	D KS,PT INDO,A
(C858/C859	Not Used !						
	FILTERS						
CF801/802	SFE 10.7MA8-A				3978011001	2	KS,A
(CF801/802	SFE 10.7MS3G				3978011011	2	D,PT INDO
CF804	CFM2-450BL				3908001080	1	
	CONNECTORS						
CNT101	Lead Ass'y, 6P, 160mm				436106163761	1	
CNT102	Wafer, 13P				4428525340	1	
CNT103	Wafer, 13P				4428513820	1	
CNT104	Wafer, 15P				4428515820	1	
CNT105	Wafer, 9P				4428525300	1	
CNT401	Wire Trap, 5P				4428531105	1	KS,PT INDO D,A
(CNT401)	Not Used !						
CNT701	Wafer, FPC, 20P				4426001020	1	
CNT702	Wafer, FPC, 13P				4426001013	1	
	DIODES						
D101	1N4148, Switching				2058322101	1	
D102	Zener, UZ 5.1 BSB				2258599103	1	
D201	1N4148, Switching				2058322101	1	
D301/D302	1N4148, Switching				2058322101	2	
D708	1N4148, Switching				2058322101	1	
D709/D710	Zener, UZ 5.1 BSB				2258599103	2	
D801	Zener, UZ 5.1 BSB				2258599103	1	
D802-D805	1N4148, Switching				2058322101	4	
D806/D807	1N4148, Switching				2058322101	2	D KS,PT INDO,A
(D806/D807	Not Used !						
VD1/VD2	Varactor, SVC321SPA-C				2258817104	2	
VD3	Varactor, SVC321SPA-C				2258817104	1	D KS,PT INDO,A
(VD3)	Not Used !						
	INTEGRATED CIRCUITS						
IC101	LC7821				2168017132	1	
IC102	KIA4559S/KIA75559S				2168206103	1	
IC103	KIA7806PI, Regulator				2168606110	1	
IC201	LA7952, Video Switch				2168317136	1	
IC301	NJM2177AFB3				2169020000	1	
IC302	NJU9701				2168020117	1	
IC303	GD4053B				2138001117	1	
IC304	KIA4559P/KIA75559P				2168206104	1	
IC305	TC9176P				2138007124	1	
IC306	KIA4559S/KIA75559S				2168206103	1	
IC801	LA1266				2168017128	1	
IC802	LM7001M				2138017136	1	
IC803	AN7470				2168410101	1	
	TRANSISTORS						
Q101	DTC114YS				2208622106	1	
Q102	KRA107M/DTA114YS				2238006103	1	
Q103	KTA1273/KTA966A, PNP				2228106104	1	
Q104	BKTC3199Y, NPN				2208610109	1	
Q201/Q202	BKTC3199Y, NPN				2208610109	2	
Q203	DTC114TS				2208622108	1	
Q301/Q302	DTC323TS, NPN				2238422100	2	
Q303-Q305	KRA107M/DTA114YS				2238006103	3	
Q306/Q307	DTC114TS				2208622108	2	
Q702/Q703	DTC114TS				2208622108	2	
Q801	Chip, KTC3880				2207606002	1	
Q802/Q803	BKTC3199Y, NPN				2208610109	2	
Q804	KRA107M/DTA114YS				2238006103	1	
Q805/Q806	BKTC3199Y, NPN				2208610109	2	
Q807/Q808	KRA107M/DTA114YS				2238006103	2	
Q809-Q814	BKTC3199Y, NPN				2208610109	6	D KS,PT INDO,A
(Q809-Q81	Not Used !						
Q815	KRA107M/DTA114YS				2238006103	1	D KS,PT INDO,A
(Q815)	Not Used !						
	RESISTORS						
R101-R106	Chip	1	kohm	1/10 W J	3099102870	6	
R107	Chip	5.6	kohm	1/10 W J	3099562870	1	KS,PT INDO
(R107)	Chip	3.3	kohm	1/10 W J	3099332870	1	D,A
R108	Chip	5.6	kohm	1/10 W J	3099562870	1	KS,PT INDO D,A
(R108)	Not Used !						
R109	Chip	5.6	kohm	1/10 W J	3099562870	1	KS,PT INDO
(R109)	Chip	3.3	kohm	1/10 W J	3099332870	1	D,A
R110	Chip	5.6	kohm	1/10 W J	3099562870	1	KS,PT INDO D,A
(R110)	Not Used !						
R111-R113	Metal Film	1	kohm	1/5 W J	3029102970	3	
R114	Carbon Film	100	kohm	1/5 W J	3069104970	1	
R115	Chip	51	kohm	1/10 W J	3099513870	1	
R116	Metal Film	4.7	kohm	1/5 W J	3029472970	1	KS,PT INDO D,A
(R116)	Not Used !						
R117	Chip	4.7	kohm	1/10 W J	3099472870	1	KS,PT INDO
(R117)	Chip	0	ohm	1/10 W J	3099000870	1	D,A
R118	Chip	2.2	kohm	1/10 W J	3099222870	1	KS,PT INDO
(R118)	Chip	1	kohm	1/10 W J	3099102870	1	D,A
R119	Chip	2.4	kohm	1/10 W J	3099242870	1	KS,PT INDO D,A
(R119)	Not Used !						
R120	Chip	51	kohm	1/10 W J	3099513870	1	
R121	Metal Film	4.7	kohm	1/5 W J	3029472970	1	KS,PT INDO D,A
(R121)	Not Used !						
R122	Chip	4.7	kohm	1/10 W J	3099472870	1	KS,PT INDO
(R122)	Chip	0	ohm	1/10 W J	3099000870	1	D,A
R123	Chip	2.2	kohm	1/10 W J	3099222870	1	KS,PT INDO
(R123)	Chip	1	kohm	1/10 W J	3099102870	1	D,A
R124	Chip	2.4	kohm	1/10 W J	3099242870	1	KS,PT INDO D,A
(R124)	Not Used !						
R125/R126	Metal Film	100	ohm	1/5 W J	3029101970	2	
R127	Chip	47	kohm	1/10 W J	3099473870	1	
R128	Chip	3.3	kohm	1/10 W J	3099332870	1	
R129	Metal Film	22	ohm	1 W J	3029220470	1	
R130	Carbon Film	10	kohm	1/5 W J	3069103970	1	
R201	Chip	22	ohm	1/10 W J	3099220870	1	
R202-R204	Chip	68	ohm	1/10 W J	3099680870	3	
R205	Metal Film	68	ohm	1/5 W J	3029680970	1	
R206	Chip	47	kohm	1/10 W J	3099473870	1	
R207	Chip	68	ohm	1/10 W J	3099680870	1	
R208	Chip	47	kohm	1/10 W J	3099473870	1	
R209/R210	Chip	390	ohm	1/10 W J	3099391870	2	
R211	Chip	3.3	kohm	1/10 W J	3099332870	1	
R212/R213	Metal Film	1	kohm	1/5 W J	3029102970	2	
R301	Chip	6.8	kohm	1/10 W J	3099682870	1	
R302	Chip	47	kohm	1/10 W J	3099473870	1	
R303	Chip	15	kohm	1/10 W J	3099153870	1	
R304	Chip	2.2	Mohm	1/10 W J	3099225870	1	
R305	Chip	47	kohm	1/10 W J	3099473870	1	
R306	Carbon Film	47	kohm	1/5 W J	3069473970	1	
R307-R309	Chip	100	kohm	1/10 W J	3099104870	3	
R311	Chip	27	ohm	1/10 W J	3099270870	1	
R314	Chip	100	kohm	1/10 W J	3099104870	1	
R315	Chip	15	kohm	1/10 W J	3099153870	1	
R316/R317	Chip	8.2	kohm	1/10 W J	3099822870	2	
R318	Chip	6.8	kohm	1/10 W J	3099682870	1	
R319	Chip	330	kohm	1/10 W J	3099334870	1	
R320	Chip	6.8	kohm	1/10 W J	3099682870	1	
R321	Chip	47	kohm	1/10 W J	3099473870	1	
R322	Chip	15	kohm	1/10 W J	3099153870	1	
R323/R324	Metal Film	1	kohm	1/5 W J	3029102970	2	
R325	Metal Film	1.5	kohm	1/5 W J	3029152970	1	
R326	Chip	1.5	kohm	1/10 W J	3099152870	1	
R327/R328	Carbon Film	33	kohm	1/5 W J	3069333970	2	
R329	Carbon Film	180	kohm	1/5 W J	3069184970	1	
R330	Chip	15	kohm	1/10 W J	3099153870	1	
R331	Metal Film	1	kohm	1/5 W J	3029102970	1	
R332	Chip	8.2	kohm	1/10 W J	3099822870	1	
R333	Chip	6.8	kohm	1/10 W J	3099682870	1	
R334	Chip	18	kohm	1/10 W J	3099183870	1	
R335	Chip	5.6	kohm	1/10 W J	3099562870	1	
R336/R337	Chip	22	ohm	1/10 W J	3099220870	2	
R338	Chip	15	kohm	1/10 W J	3099153870	1	
R339	Chip	18	kohm	1/10 W J	3099183870	1	
R340	Chip	15	kohm	1/10 W J	3099153870	1	
R341	Chip	22	ohm	1/10 W J	3099220870	1	
R342	Chip	1	Mohm	1/10 W J	3099105870	1	
R343/R344	Chip	1	kohm	1/10 W J	3099102870	2	
R345	Chip	4.7	kohm	1/10 W J	3099472870	1	
R346/R347	Metal Film	1	kohm	1/5 W J	3029102970	2	
R348	Metal Film	4.7	kohm	1/5 W J	3029472970	1	
R349	Chip	100	kohm	1/10 W J	3099104870	1	
R350	Chip	1.8	kohm	1/10 W J	3099182870	1	
R351	Chip	8.2	kohm	1/10 W J	3099822870	1	
R352	Chip	100	kohm	1/10 W J	3099104870	1	
R353	Chip	1.8	kohm	1/10 W J	3099182870	1	
R354	Chip	8.2	kohm	1/10 W J	3099822870	1	
R355/R356	Chip	330	ohm	1/10 W J	3099331870	2	
R358	Chip	100	kohm	1/10 W J	3099104870	1	
R359	Chip	10	kohm	1/10 W J	3099103870	1	
R712	Chip	22	kohm	1/10 W J	3099223870	1	
R713	Carbon Film	220	kohm	1/5 W J	3069224970	1	
R714	Carbon Film	100	kohm	1/5 W J	3069104970	1	
R715	Chip	4.7	kohm	1/10 W J	3099472870	1	
R716	Carbon Film	5.6	kohm	1/5 W J	3069562970	1	
R717/R718	Chip	5.6	kohm	1/10 W J	3099562870	2	
R719-R721	Chip	1	kohm	1/10 W J	3099102870	3	
R722/R723	Metal Film	3.3	ohm	1/5 W J	3029339970	2	
R801	Chip	100	ohm	1/10 W J	3099101870	1	
R802	Chip	1	kohm	1/10 W J	3099102870	1	
R803	Chip	560	ohm	1/10 W J	3099561870	1	
R804	Chip	3.3	kohm	1/10 W J	3099332870	1	
R805	Chip	330	ohm	1/10 W J	3099331870	1	
R806	Chip	470	ohm	1/10 W J	3099471870	1	KS,D,A
(R806)	Chip	330	ohm	1/10 W J	3099331870	1	PT INDO
R807	Chip	10	kohm	1/10 W J	3099103870	1	
R808	Chip	3.3	kohm	1/10 W J	3099332870	1	

Model No. : TX-757

Ref. No.	Description							Part No.	Q'ty	Version
R809	Carbon Film	18	kohm	1/5	W	J		3069183970	1	KS,A
(R809)	Carbon Film	47	kohm	1/5	W	J		3069473970	1	D,PT INDO
R810	Chip	22	ohm	1/10	W	J		3099220870	1	
R811	Chip	2.4	kohm	1/10	W	J		3099243870	1	
R812	Chip	10	kohm	1/10	W	J		3099103870	1	
R813	Chip	68	kohm	1/10	W	J		3099683870	1	
R814	Chip	4.7	kohm	1/10	W	J		3099472870	1	
R815	Chip	33	ohm	1/10	W	J		3099330870	1	
R816	Metal Film	240	ohm	1/5	W	J		3029241970	1	
R817	Metal Film	330	ohm	1/5	W	J		3029331970	1	
R818	Chip	2	kohm	1/10	W	J		3099202870	1	KS,A
(R818)	Chip	3.9	kohm	1/10	W	J		3099392870	1	D,PT INDO
R819	Chip	2.2	kohm	1/10	W	J		3099222870	1	
R820	Chip	22	kohm	1/10	W	J		3099223870	1	KS,PT INDO,A
(R820)	Chip	12	kohm	1/10	W	J		3099123870	1	D
R821	Chip	68	ohm	1/10	W	J		3099680870	1	
R822	Chip	100	kohm	1/10	W	J		3099104870	1	
R823	Chip	47	kohm	1/10	W	J		3099473870	1	
R824	Chip	1	kohm	1/10	W	J		3099102870	1	
R825	Chip	560	ohm	1/10	W	J		3099561870	1	
R826	Chip	10	kohm	1/10	W	J		3099103870	1	
R827	Carbon Film	5.6	kohm	1/5	W	J		3069562970	1	
R828/R829	Chip	100	ohm	1/10	W	J		3099101870	2	
R831	Chip	47	kohm	1/10	W	J		3099473870	1	KS,A
(R831)	Chip	33	kohm	1/10	W	J		3099333870	1	D,PT INDO
R832	Chip	22	kohm	1/10	W	J		3099223870	1	KS,A
(R832)	Chip	27	kohm	1/10	W	J		3099273870	1	D,PT INDO
R833	Chip	22	kohm	1/10	W	J		3099223870	1	KS,A
(R833)	Chip	27	kohm	1/10	W	J		3099273870	1	D,PT INDO
R834	Chip	8.2	kohm	1/10	W	J		3099822870	1	KS,A
(R834)	Chip	5.6	kohm	1/10	W	J		3099562870	1	D,PT INDO
R835	Chip	10	kohm	1/10	W	J		3099103870	1	
R836	Chip	8.2	kohm	1/10	W	J		3099822870	1	KS,A
(R836)	Chip	5.6	kohm	1/10	W	J		3099562870	1	D,PT INDO
R837	Chip	1	kohm	1/10	W	J		3099102870	1	
R838/R839	Chip	56	kohm	1/10	W	J		3099563870	2	
R840-R842	Chip	3.3	kohm	1/10	W	J		3099332870	3	
R843	Chip	10	kohm	1/10	W	J		3099103870	1	KS,A
(R843)	Chip	3.3	kohm	1/10	W	J		3099332870	1	D,PT INDO
R844	Chip	3.3	kohm	1/10	W	J		3099332870	1	
R845	Chip	10	kohm	1/10	W	J		3099103870	1	KS,A
(R845)	Chip	3.3	kohm	1/10	W	J		3099332870	1	D,PT INDO
R846/R847	Metal Film	3.9	kohm	1/5	W	J		3029392970	2	
R848	Chip	15	kohm	1/10	W	J		3099153870	1	
R849	Chip	1	kohm	1/10	W	J		3099102870	1	
R850	Chip	6.8	kohm	1/10	W	J		3099682870	1	
R851	Chip	100	kohm	1/10	W	J		3099104870	1	
R852	Chip	3.3	kohm	1/10	W	J		3099332870	1	KS,A
(R852)	Chip	1.8	kohm	1/10	W	J		3099182870	1	D,PT INDO
R853	Carbon Film	100	kohm	1/5	W	J		3069104970	1	D
(R853)	Not Used !									A,KS,PT INDO
R854	Chip	56	kohm	1/10	W	J		3099563870	1	D
(R854)	Not Used !									KS,PT INDO,A
R855	Chip	100	kohm	1/10	W	J		3099104870	1	D
(R855)	Not Used !									KS,PT INDO,A
R856/R857	Chip	47	kohm	1/10	W	J		3099473870	1	D
(R856/R857	Not Used !									KS,PT INDO,A
R858	Chip	1	Mohm	1/10	W	J		3099105870	1	D
(R858)	Not Used !									KS,PT INDO,A
R859	Chip	100	kohm	1/10	W	J		3099104870	1	
R860/R861	Chip	47	kohm	1/10	W	J		3099473870	2	D
R862/R863	Carbon Film	47	kohm	1/5	W	J		3069473970	2	D
R860-R863	Chip	47	kohm	1/10	W	J		3099473870	4	D
(R860-R863	Not Used !									KS,PT INDO,A
	COILS									
L701	Inductor, 1 mH 03							2648610283	1	
L801	Inductor, 20.8mH							2648601430	1	D
(L801)	Not Used !									KS,PT INDO,A
T801	AM-ANT							2608201120	1	
T802	AM-OSC							2638201150	1	
T803	FM-DET-A							2838501110	1	
T804	FM-DET-B							2838501210	1	
T805	AM-IFT							2848001250	1	
T806/T807	MPX, 19 kHz, FB-7SG							2658301100	2	
T808	LW ANT							2608201130	1	D
(T808)	Not Used !									KS,PT INDO,A
T809	LW OSC							2638401060	1	D
(T809)	Not Used !									KS,PT INDO,A
	SEMI FIXED RESISTORS									
VR801	2 kohm (B)							3248020243	1	
VR802	50 kohm							3248050343	1	KS,PT INDO,A
(VR802)	20 kohm							3248020343	1	D
VR803	5 kohm (B)							3248050243	1	
VR804	200 kohm							3248020443	1	
	MISCELLANEOUS									
X301	Resonator, CSA2.00MG-TF21							3938124001	1	
X801	Crystal, 7.2MHz							3978101031	1	
TC801	Trimmer, 10P							3838001140	1	
TC803	Trimmer, 10P							3838001140	1	D
(TC803)	Not Used !									KS,PT INDO,A
17	Heatsink Regulator TR.							7505206210	1	
18	Jack RCA, 2P							4438103020	1	
19	Jack RCA, 9P							4438114510	1	
20	Jack RCA, 2P							4438103010	1	
21	Terminal Antenna, 4P							4408107120	1	A,KS,PT INDO
(21)	Terminal Antenna, 4P							4408108220	1	D
22	Shield Plate							6165151910	1	A,KS,PT INDO
(22)	Not Used !									D
27	Shield Fence, Front-end							6163115510	1	A,KS,PT INDO
(27)	Not Used !									D
FRONT-EN	Front -End, FTH4-460V							3928101850	1	D
FRONT-EN	**ASSEMBLY P.C.BOARD FRONT END**							**054002009835**	**1**	**KS,PT INDO,A**
C81	CAP, CeramicTubular,	8.2	pF	50	V	K		3511825235	1	
C83	CAP, CeramicTubular	100	pF	50	V	J		3519101935	1	
C84	CAP, CeramicTubular	0.001	uF	50	V	Z		3519102935	1	
C85	CAP, CeramicTubular,	3.9	pF	50	V	K		3511395235	1	
C86	CAP, CeramicTubular,	5.6	pF	50	V	K		3511565235	1	
C87	CAP, CeramicTubular,	2.2	pF	50	V	K		3511225235	1	
C88	CAP, CeramicTubular,	18	pF	50	V	J		3511186135	1	
C89	CAP, CeramicTubular	0.001	uF	50	V	Z		3519102935	1	
C90	CAP, CeramicTubular,	8.2	pF	50	V	K		3511825235	1	
C91	CAP, CeramicTubular,	3.3	pF	50	V	K		3511335235	1	
C92	CAP, CeramicTubular	15	pF	50	V	J		3519150935	1	
L81	Coil, Inductor, 0.47 uH							2648647882	1	
L82	Coil, Inductor, 2.2 uH							2648622982	1	
Q81	TR, KSC2786R							2208406128	1	
Q82/Q83	TR, KTC3193-0, NPN							2208406125	2	
Q84	FET, 2SK544							2218217000	1	
R81	RES, Carbon Film	100	kohm	1/5	W	J		3069104970	1	
R82/R83	RES, Carbon Film	33	kohm	1/5	W	J		3069333970	2	
R84	RES, Metal Film	220	ohm	1/5	W	J		3029221970	1	
R85	RES, Carbon Film	330	kohm	1/5	W	J		3069334970	1	
R86/R87	RES, Metal Film	390	ohm	1/5	W	J		3029391970	2	
R88	RES, Carbon Film	560	kohm	1/5	W	J		3069564970	1	
R89	RES, Carbon Film	33	kohm	1/5	W	J		3069333970	1	
R90	RES, Metal Film	390	ohm	1/5	W	J		3029391970	1	
R91	RES, Carbon Film	680	kohm	1/5	W	J		3069684970	1	
VD81-VD83	Vractor, SVC211SPA-C							2258817103	3	
PCB2	**ASSEMBLY P.C.BOARD MIC (KS, PT INDO AREA ONLY)**									
	CAPACITORS									
C401	Electrolytic SG	4.7	uF	50	V	M		3479347971	1	
C402	Chip, CH	220	pF	50	V	J		3539221210	1	
C403	Electrolytic SG	10	uF	35	V	M		3479310061	1	
C404	Electrolytic SG	4.7	uF	50	V	M		3479347971	1	
C405	Electrolytic SSE	4.7	uF	16	V	M		3479147935	1	
C406	Chip	0.006	uF	50	V	K		3539562820	1	
C407	Electrolytic SG	4.7	uF	50	V	M		3479347971	1	
C408	Chip, CH	560	pF	50	V	J		3539561210	1	
C409	Electrolytic SG	4.7	uF	50	V	M		3479347971	1	
C410	Chip	0.033	uF	50	V	K		3539333820	1	
C411	Chip	0.006	uF	50	V	K		3539562820	1	
C412	Chip, CH	560	pF	50	V	J		3539561210	1	
C413/C414	Chip	0.047	uF	50	V	Z		3539473060	2	
C415	Chip	0.01	uF	50	V	K		3539103820	1	
C416/C417	Electrolytic SG	0.33	uF	50	V	M		3479333871	2	
C418	Chip	0.01	uF	50	V	K		3539103820	1	
C419	Electrolytic SG	10	uF	35	V	M		3479310061	1	
C420	Chip, CH	220	pF	50	V	J		3539221210	1	
C421	Electrolytic SSE	4.7	uF	16	V	M		3479147935	1	
C422/C423	Electrolytic SG	47	uF	16	V	M		3479347031	2	
C424	Chip	0.047	uF	50	V	Z		3539473060	1	
C425	Electrolytic SG	47	uF	16	V	M		3479347031	1	
C426	Electrolytic SG	4.7	uF	50	V	M		3479347971	1	
C427	Electrolytic SG	100	uF	10	V	M		3479310121	1	
	CONNECTOR									
CNT401	Lead Ass'y, 5P, 180mm							436405180732	1	
	INTEGRATED CIRCUITS									
IC401	KIA4559S/KIA75559S							2168206103	1	
IC402	ES56028E, Digital Echo							2138633001	1	

Ref. No.	Description							Part No.	Q'ty	Version
	RESISTORS									
R401	Chip	0	ohm	1/10	W	J		3099000870	1	
R402	Chip	4.7	kohm	1/10	W	J		3099472870	1	
R403	Chip	1	kohm	1/10	W	J		3099102870	1	
R404	Chip	100	kohm	1/10	W	J		3099104870	1	
R405	Chip	10	kohm	1/10	W	J		3099103870	1	
R406	Chip	15	kohm	1/10	W	J		3099153870	1	
R407	Chip	8.2	kohm	1/10	W	J		3099822870	1	
R408	Chip	12	kohm	1/10	W	J		3099123870	1	
R409	Chip	3.3	kohm	1/10	W	J		3099332870	1	
R410	Chip	12	kohm	1/10	W	J		3099123870	1	
R411	Chip	15	kohm	1/10	W	J		3099153870	1	
R412	Chip	10	kohm	1/10	W	J		3099103870	1	
R413	Chip	15	kohm	1/10	W	J		3099153870	1	
R414	Chip	6.8	kohm	1/10	W	J		3099682870	1	
R415	Chip	68	kohm	1/10	W	J		3099683870	1	
R416	Chip	6.8	kohm	1/10	W	J		3099682870	1	
R417	Chip	68	kohm	1/10	W	J		3099683870	1	
R418	Chip	27	kohm	1/10	W	J		3099273870	1	
R419	Chip	560	ohm	1/10	W	J		3099561870	1	
R420	Chip	15	kohm	1/10	W	J		3099153870	1	
R421/R422	Chip	330	ohm	1/10	W	J		3099331870	2	
R423	Chip	1	kohm	1/10	W	J		3099102870	1	
R424	Chip	100	kohm	1/10	W	J		3099104870	1	
R425	Chip	47	kohm	1/10	W	J		3099473870	1	
R426	Metal Film	10	ohm	1/5	W	J		3029100970	1	
R427	Carbon Film	15	kohm	1/5	W	J		3069153970	1	
	MISCELLANEOUS									
8	Jack Phone							4438005510	1	
9	Shield Fence							6165146110	1	
10(VR401)	Volume Mic, 10 kohm							3208052410	1	
PCB3	**ASSEMBLY P.C.BOARD POWER**									
C501-C503	Mylar	0.047	uF	100	V	J		3679473120	3	
C504	Electroiytic SD	4700	uF	25	V	M		3409347248	1	
C505	Electrolytic SG	1	uF	50	V	M		3479310971	1	
C506	Ceramic Tubular	0.022	uF	25	V	Z		3579223530	1	KS,PT INDO
(C506)	Not Used !									D,A
C507	Electrolytic SG	1	uF	50	V	M		3479310971	1	KS,PT INDO
(C507)	Not Used !									D,A
D501/D502	1N4003, Rectifier							2058512108	2	
D503	1N4148, Switching							2058322101	1	KS,PT INDO
(D503)	Not Used !									D,A
IC501	KIA7808PI, Regulator							2168606116	1	
IC502	KIA7805PI, Regulator							2108499104	1	KS,PT INDO
(IC502)	Not Used !									D,A
R501	Metal Film	3.3	ohm	2	W	J		3029339570	1	KS,PT INDO
(R501)	Not Used !									D,A
PCB4	**ASSEMBLY P.C.BOARD FRONT**									
	CAPACITORS									
C702/C703	Chip	0.047	uF	50	V	Z		3539473060	2	
C704	Electrolyte SSE	47	uF	10	V	M		3479147025	1	
C705	Electric Back-up	0.047	F	5.5	V			3438247315	1	
C706	Chip	0.1	uF	50	V	Z		3539104060	1	
C707	Chip	22	pF	50	V	Z		3539220210	1	
C708	Trimmer, CH	10	pF					3838001140	1	
C709	Chip, CH	33	pF	50	V	J		3539330210	1	
C710	Electrolytic SSE	10	uF	16	V	M		3479110035	1	
C713/C714	Chip	0.1	uF	50	V	Z		3539104060	2	
	CONNECTORS									
CNT701	Wafer, FPC, 20P							4426001120	1	
CNT702	Wafer, 13P							4428513826	1	
CNT703	Lead Ass'y, 4P, 80mm							436404080732	1	
	DIODES									
D701-D707	1N4148, Switching							2058322101	7	
	INTEGRATED CIRCUIT									
IC701	CXP82324-331Q, CPU, DEP-449							2139322704	1	
	COIL									
L702	Inductor, 1 mH 03							2648610283	1	
	TRANSISTOR									
Q701	BKTC3199Y, NPN							2208610109	1	
	RESISTORS									
R701	Chip	100	kohm	1/10	W	J		3099104870	1	
R702-R706	Carbon Film	100	kohm	1/5	W	J		3069104970	5	

Ref. No.	Description							Part No.	Q'ty	Version
R707	Carbon Film	10	kohm	1/5	W	J		3069103970	1	
R708	Chip	10	kohm	1/10	W	J		3099103870	1	
R709-R711	Carbon Film	100	kohm	1/5	W	J		3069104970	3	
	MISCELLANEOUS									
X701	Crystal, 10MHz							3978011001	1	
FL701	FL Display, CM1361C							2328002306	1	
28	Switch Tact							4658003710	14	
PCB5	**ASSEMBLY P.C.BOARD RMC**									
29	Switch Tact							4658004010	1	
C701	CAP, Electrolytic SG	10	uF	35	V			3479310061	1	
CNT703	Connector, Wire Trap, 5P							4428531104	1	
IC702	TFMT4380, Remote Sensor							2408005001	1	

Model No. : TX-747

Ref. No.	Description					Part No.	Q'ty	Version
PCB1	ASSEMBLY P.C.BOARD MAIN							
	CAPACITORS							
C101	Chip	0.1	uF	50 V	Z	3539104060	1	
C102	Chip, CH	100	pF	50 V	J	3539101210	1	
C103	Chip	0.047	uF	50 V	Z	3539473060	1	
C104	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C105	Chip	0.047	uF	50 V	Z	3539473060	1	
C107	Chip, CH	220	pF	50 V	J	3539221210	1	KS,PT INDO
(C107)	Not Used !							D,A
C108	Electrolytic SG	10	uF	35 V	M	3479310061	1	
C110	Chip, CH	220	pF	50 V	J	3539221210	1	KS,PT INDO
(C110)	Not Used !							D,A
C111/C112	Electrolytic SG	47	uF	16 V	M	3479347031	2	
C113	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	KS,PT INDO
(C113)	Not Used !							D,A
C114	Electrolytic SG	10	uF	35 V	M	3479310061	1	
C115-C118	Chip, CH	100	pF	50 V	J	3539101210	4	D
(C115-C118)	Not Used !							KS,PT INDO,A
C711	Chip, CH	470	pF	50 V	J	3539471210	1	
C712	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C801	Electrolytic SG	100	uF	16 V	M	3479310131	1	
C802	Chip	0.047	uF	50 V	Z	3539473060	1	
C803	Chip, CH	33	pF	50 V	J	3539330210	1	
C804	Chip	0.01	uF	50 V	K	3539103820	1	
C805	Chip, CH	33	pF	50 V	J	3539330210	1	
C806-C809	Chip	0.047	uF	50 V	Z	3539473060	4	
C810	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C811-C813	Chip, CH	100	pF	50 V	J	3539101210	3	
C814	Chip, CH	330	pF	50 V	J	3539331210	1	
C815	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C816	Chip	0.047	uF	50 V	Z	3539473060	1	
C817	Electrolytic SG	10	uF	35 V	M	3479310061	1	
C818	Electrolytic SG	3.3	uF	50 V	M	3479333971	1	
C819	Electrolytic SG	2.2	uF	50 V	M	3479322971	1	
C820	Chip	0.022	uF	50 V	K	3539223820	1	
C821	Chip	0.047	uF	50 V	Z	3539473060	1	
C822	Mylar	0.047	uF	100 V	J	3679473120	1	
C823	Chip, CH	470	pF	50 V	J	3539471210	1	
C824	Electrolytic SG	3.3	uF	50 V	M	3479333971	1	
C825	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C826	Chip	0.047	uF	50 V	Z	3539473060	1	
C827	Electrolytic SG	0.22	uF	50 V	M	3479322871	1	
C828/C829	Chip	0.01	uF	50 V	K	3539103820	2	
C830	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C831	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C832	Chip	0.047	uF	50 V	Z	3539473060	1	
C833	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C834/C835	Chip	0.047	uF	50 V	Z	3539473060	2	
C837	Electrolytic SG	10	uF	35 V	M	3479310061	1	
C838	Chip	0.047	uF	50 V	Z	3539473060	1	
C839	CeramicTubular	0.001	uF	50 V	K	3519102935	1	
C840	Chip	0.047	uF	50 V	Z	3539473060	1	
C841	Chip, CH	470	pF	50 V	J	3539471210	1	
C842	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C843	Electrolytic SG	100	uF	16 V	M	3479310131	1	
C844	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C845	Chip	120	pF	50 V	J	3539121210	1	
C846	Chip	0.002	uF	50 V	K	3539152820	1	KS,A
(C846)	Chip	0.001	uF	50 V	K	3539102820	1	D,PT INDO
C847	Chip	0.002	uF	50 V	K	3539152820	1	KS,A
(C847)	Chip	0.001	uF	50 V	K	3539102820	1	D,PT INDO
C848	Electrolytic SG	2.2	uF	50 V	M	3479322971	1	
C849	Chip	0.002	uF	50 V	K	3539222820	1	
C850	Electrolytic SG	2.2	uF	50 V	M	3479322971	1	
C851	Chip	0.002	uF	50 V	K	3539222820	1	
C852	Chip, CH	15	pF	50 V	J	3539150210	1	
C853	Chip	0.047	uF	50 V	Z	3539473060	1	D
(C853)	Not Used !							KS,PT INDO,A
C854	Chip	0.047	uF	50 V	Z	3539473060	1	D
(C854)	Not Used !							KS,PT INDO,A
C855	Chip, CH	180	pF	50 V	J	3539181210	1	D
(C855)	Not Used !							KS,PT INDO,A
C856	Chip, CH	33	pF	50 V	J	3539330210	1	D
(C856)	Not Used !							KS,PT INDO,A
C857	Chip, CH	470	pF	50 V	J	3539471210	1	
C858/C859	Chip, CH	100	pF	50 V	J	3539101210	2	D
(C858/C859	Not Used !							KS,PT INDO,A
	FILTERS							
CF801/802	SFE 10.7MA8-A					3978011001	2	KS,A
(CF801/802)	SFE 10.7MS3G					3978011011	2	D,PT INDO
CF804	CFM2-450BL					3908001080	1	

Ref. No.	Description	Part No.	Q'ty	Version
	CONNECTORS			
CNT101	Lead Ass'y, 6P, 160mm	36106163761	1	
CNT102	Wafer, 13P	4428525340	1	
CNT103	Wafer, 13P	4428513820	1	
CNT104	Wafer, 15P	4428515820	1	
CNT105	Wafer, 9P	4428525300	1	
CNT401	Wire Trap, 5P	4428531105	1	KS,PT INDO
(CNT401)	Not Used !			D,A
CNT701	Wafer, FPC, 20P	4426001020	1	
	DIODES			
D101	1N4148, Switching	2058322101	1	
D102	Zener, UZ 5.1 BSB	2258599103	1	
D708	1N4148, Switching	2058322101	1	
D709/D710	Zener, UZ 5.1 BSB	2258599103	2	
D801	Zener, UZ 5.1 BSB	2258599103	1	
D802-D805	1N4148, Switching	2058322101	4	
D806/D807	1N4148, Switching	2058322101	2	D
(D806/D807)	Not Used !			KS,PT INDO,A
VD1/VD2	Varactor, SVC321SPA-C	2258817104	2	
VD3	Varactor, SVC321SPA-C	2258817104	1	D
(VD3)	Not Used !			KS,PT INDO,A
	INTEGRATED CIRCUITS			
IC101	LC7821	2168017132	1	
IC102	KIA4559S/KIA75559S	2168206103	1	
IC103	KIA7806PI, Regulator	2168606110	1	KS,PT INDO
(IC103)	Not Used !			D,A
IC801	LA1266	2168017128	1	
IC802	LM7001M	2138017136	1	
IC803	AN7470	2168410101	1	
	TRANSISTORS			
Q101	DTC114YS	2208622106	1	
Q102	KRA107M/DTA114YS	2238006103	1	
Q103	2SA1515	2208722102	1	
Q104	BKTC3199Y, NPN	2208610109	1	
Q702/Q703	DTC114TS	2208622108	2	
Q801	Chip, KTC3880	2207606002	1	
Q802/Q803	BKTC3199Y, NPN	2208610109	2	
Q804	KRA107M/DTA114YS	2238006103	1	
Q805/Q806	BKTC3199Y, NPN	2208610109	2	
Q807/Q808	KRA107M/DTA114YS	2238006103	2	
Q809-Q814	BKTC3199Y, NPN	2208610109	6	D
(Q809-Q814)	Not Used !			KS,PT INDO,A
Q815	KRA107M/DTA114YS	2238006103	1	D
(Q815)	Not Used !			KS,PT INDO,A
	RESISTORS			
R101/R102	Chip	1 kohm 1/10 W J	3099102870	2
R111-R113	Metal Film	1 kohm 1/5 W J	3029102970	3
R114	Carbon Film	100 kohm 1/5 W J	3069104970	1
R115	Chip	51 kohm 1/10 W J	3099513870	1
R116	Metal Film	4.7 kohm 1/5 W J	3029472970	1 KS,PT INDO
(R116)	Not Used !			D,A
R117	Chip	4.7 kohm 1/10 W J	3099472870	1 KS,PT INDO
(R117)	Chip	0 ohm 1/10 W J	3099000870	1 D,A
R118	Chip	2.2 kohm 1/10 W J	3099222870	1 KS,PT INDO
(R118)	Chip	1 kohm 1/10 W J	3099102870	1 D,A
R119	Chip	2.2 kohm 1/10 W J	3099222870	1 KS,PT INDO
(R119)	Not Used !			D,A
R120	Chip	51 kohm 1/10 W J	3099513870	1
R121	Metal Film	4.7 kohm 1/5 W J	3029472970	1 KS,PT INDO
(R121)	Not Used !			D,A
R122	Chip	4.7 kohm 1/10 W J	3099472870	1 KS,PT INDO
(R122)	Chip	0 ohm 1/10 W J	3099000870	1 D,A
R123	Chip	2.2 kohm 1/10 W J	3099222870	1 KS,PT INDO
(R123)	Chip	1 kohm 1/10 W J	3099102870	1 D,A
R124	Chip	2.2 kohm 1/10 W J	3099222870	1 KS,PT INDO
(R124)	Not Used !			D,A
R125/R126	Metal Film	100 ohm 1/5 W J	3029101970	2
R127	Chip	47 kohm 1/10 W J	3099473870	1
R128	Chip	3.3 kohm 1/10 W J	3099332870	1
R129	Metal Film	22 ohm 1 W J	3029220470	1 KS,PT INDO
(R129)	Not Used !			D,A
R130	Carbon Film	10 kohm 1/5 W J	3069103970	1
R712	Chip	22 kohm 1/10 W J	3099223870	1
R713	Carbon Film	220 kohm 1/5 W J	3069224970	1
R714	Carbon Film	100 kohm 1/5 W J	3069104970	1
R715	Chip	4.7 kohm 1/10 W J	3099472870	1
R716	Carbon Film	5.6 kohm 1/5 W J	3069562970	1

Ref. No.	Description	Part No.	Q'ty	Version
R717/R718	Chip	5.6 kohm 1/10 W J	3099562870	2
R719-R721	Chip	1 kohm 1/10 W J	3099102870	3
R722/R723	Metal Film	3.3 ohm 1/5 W J	3029339970	2
R801	Chip	100 ohm 1/10 W J	3099101870	1
R802	Chip	1 kohm 1/10 W J	3099102870	1
R803	Chip	560 ohm 1/10 W J	3099561870	1
R804	Chip	3.3 kohm 1/10 W J	3099332870	1
R805	Chip	330 ohm 1/10 W J	3099331870	1
R806	Chip	470 ohm 1/10 W J	3099471870	1 KS,D,A
(R806)	Chip	330 ohm 1/10 W J	3099331870	1 PT INDO
R807	Chip	10 kohm 1/10 W J	3099103870	1
R808	Chip	3.3 kohm 1/10 W J	3099332870	1
R809	Carbon Film	18 kohm 1/5 W J	3069183970	1 KS,A
(R809)	Carbon Film	47 kohm 1/5 W J	3069473970	1 D,PT INDO
R810	Chip	22 ohm 1/10 W J	3099220870	1
R811	Chip	2.4 kohm 1/10 W J	3099243870	1
R812	Chip	10 kohm 1/10 W J	3099103870	1
R813	Chip	68 kohm 1/10 W J	3099683870	1
R814	Chip	4.7 kohm 1/10 W J	3099472870	1
R815	Chip	33 ohm 1/10 W J	3099330870	1
R816	Metal Film	240 ohm 1/5 W J	3029241970	1
R817	Metal Film	330 ohm 1/5 W J	3029331970	1
R818	Chip	2 kohm 1/10 W J	3099202870	1 KS,A
(R818)	Chip	3.9 kohm 1/10 W J	3099392870	1 D,PT INDO
R819	Chip	2.2 kohm 1/10 W J	3099222870	1
R820	Chip	22 kohm 1/10 W J	3099223870	1 KS,PT INDO,A
(R820)	Chip	12 kohm 1/10 W J	3099123870	1 D
R821	Chip	68 ohm 1/10 W J	3099680870	1
R822	Chip	100 kohm 1/10 W J	3099104870	1
R823	Chip	47 kohm 1/10 W J	3099473870	1
R824	Chip	1 kohm 1/10 W J	3099102870	1
R825	Chip	560 ohm 1/10 W J	3099561870	1
R826	Chip	10 kohm 1/10 W J	3099103870	1
R827	Carbon Film	5.6 kohm 1/5 W J	3069562970	1
R828/R829	Chip	100 ohm 1/10 W J	3099101870	2
R831	Chip	47 kohm 1/10 W J	3099473870	1 KS,A
(R831)	Chip	33 kohm 1/10 W J	3099333870	1 D,PT INDO
R832	Chip	22 kohm 1/10 W J	3099223870	1 KS,A
(R832)	Chip	27 kohm 1/10 W J	3099273870	1 D,PT INDO
R833	Chip	22 kohm 1/10 W J	3099223870	1 KS,A
(R833)	Chip	27 kohm 1/10 W J	3099273870	1 D,PT INDO
R834	Chip	8.2 kohm 1/10 W J	3099822870	1 KS,A
(R834)	Chip	5.6 kohm 1/10 W J	3099562870	1 D,PT INDO
R835	Chip	10 kohm 1/10 W J	3099103870	1
R836	Chip	8.2 kohm 1/10 W J	3099822870	1 KS,A
(R836)	Chip	5.6 kohm 1/10 W J	3099562870	1 D,PT INDO
R837	Chip	1 kohm 1/10 W J	3099102870	1
R838/R839	Chip	56 kohm 1/10 W J	3099563870	2
R840-R842	Chip	3.3 kohm 1/10 W J	3099332870	3
R843	Chip	10 kohm 1/10 W J	3099103870	1 KS,A
(R843)	Chip	3.3 kohm 1/10 W J	3099332870	1 D,PT INDO
R844	Chip	3.3 kohm 1/10 W J	3099332870	1
R845	Chip	10 kohm 1/10 W J	3099103870	1 KS,A
(R845)	Chip	3.3 kohm 1/10 W J	3099332870	1 D,PT INDO
R846/R847	Metal Film	3.9 kohm 1/5 W J	3029392970	2
R848	Chip	15 kohm 1/10 W J	3099153870	1
R849	Chip	1 kohm 1/10 W J	3099102870	1
R850	Chip	6.8 kohm 1/10 W J	3099682870	1
R851	Chip	100 kohm 1/10 W J	3099104870	1
R852	Chip	3.3 kohm 1/10 W J	3099332870	1 KS,A
(R852)	Chip	1.8 kohm 1/10 W J	3099182870	1 D,PT INDO
R853	Carbon Film	100 kohm 1/5 W J	3069104970	1 D
(R853)	Not Used !			KS,PT INDO,A
R854	Chip	56 kohm 1/10 W J	3099563870	1 D
(R854)	Not Used !			KS,PT INDO,A
R855	Chip	100 kohm 1/10 W J	3099104870	1 D
(R855)	Not Used !			KS,PT INDO,A
R856/R857	Chip	47 kohm 1/10 W J	3099473870	1 D
(R856/R857	Not Used !			KS,PT INDO,A
R858	Chip	1 Mohm 1/10 W J	3099105870	1 D
(R858)	Not Used !			KS,PT INDO,A
R859	Chip	100 kohm 1/10 W J	3099104870	1
R860/R861	Chip	47 kohm 1/10 W J	3099473870	1 D
R862/863	Carbon Film	47 kohm 1/5 W J	3069473970	1 D
(R860-R863)	Not Used !			KS,PT INDO,A
	COILS			
L701	Inductor, 1 mH 04		2648610284	1
L801	Iductor, 20.8mH		2648601430	1 D
(L801)	Not Used !			KS,PT INDO,A
T801	AM-ANT		2608201120	1
T802	AM-OSC		2638201150	1
T803	FM-DET-A		2838501110	1
T804	FM-DET-B		2838501210	1
T805	AM-IFT		2848001250	1

Ref. No.	Description	Part No.	Q'ty	Version
T806/T807	MPX, 19 kHz, FB-7SG	2658301100	2	
T808	LW ANT	2608201130	1	D
(T808)	Not Used !			KS,PT INDO,A
T809	LW OSC	2638401060	1	D
(T809)	Not Used !			KS,PT INDO,A
	SEMI FIXED RESISTORS			
VR801	2 kohm (B)	3248020243	1	
VR802	50 kohm	3248050343	1	KS,PT INDO,A
(VR802)	20 kohm	3248020343	1	D
VR803	5 kohm (B)	3248050243	1	
VR804	200 kohm	3248020443	1	
	MISCELLANEOUS			
X801	Crystal, 7.2MHz	3978101031	1	
TC801	Trimmer, 10P	3838001140	1	
TC803	Trimmer, 10P	3838001140	1	D
(TC803)	Not Used !			KS,PT INDO,A
17	Heatsink Regulator TR.	7505206210	1	KS,PT INDO
(17)	Not Used !			D,A
20	Jack RCA, 2P	4438103010	1	
21	Terminal Antenna, 4P	4408107120	1	A,KS,PT INDO
(21)	Terminal Antenna, 4P	4408108220	1	D
22	Shield Plate	6165151910	1	A,KS,PT INDO
(22)	Not Used !			D
27	Shield Fence, Front-end	6163115510	1	A,KS,PT INDO
(27)	Not Used !			D
FRONT-EN	Front -End, FTH4-460V	3928101850	1	D
FRONT-EN	**ASSEMBLY PCB FRONT END**	**54002009835**	**1**	**KS,PT INDO,A**
C81	CAP, CeramicTubular, 8.2 pF 50 V K	3511825235	1	
C83	CAP, CeramicTubular 100 pF 50 V J	3519101935	1	
C84	CAP, CeramicTubular 0.001 uF 50 V Z	3519102935	1	
C85	CAP, CeramicTubular, 3.9 pF 50 V K	3511395235	1	
C86	CAP, CeramicTubular, 5.6 pF 50 V K	3511565235	1	
C87	CAP, CeramicTubular, 2.2 pF 50 V K	3511225235	1	
C88	CAP, CeramicTubular, 18 pF 50 V J	3511186135	1	
C89	CAP, CeramicTubular 0.001 uF 50 V Z	3519102935	1	
C90	CAP, CeramicTubular, 8.2 pF 50 V K	3511825235	1	
C91	CAP, CeramicTubular, 3.3 pF 50 V K	3511335235	1	
C92	CAP, CeramicTubular 15 pF 50 V J	3519150935	1	
L81	Coil, Inductor, 0.47 uH	2648647882	1	
L82	Coil, Inductor, 2.2 uH	2648622982	1	
Q81	TR, KSC2786R	2208406128	1	
Q82/Q83	TR, KTC3193-0, NPN	2208406125	2	
Q84	FET, 2SK544	2218217000	1	
R81	RES, Carbon Film 100 kohm 1/5 W J	3069104970	1	
R82/R83	RES, Carbon Film 33 kohm 1/5 W J	3069333970	2	
R84	RES, Metal Film 220 ohm 1/5 W J	3029221970	1	
R85	RES, Carbon Film- 330 kohm 1/5 W J	3069334970	1	
R86/R87	RES, Metal Film 390 ohm 1/5 W J	3029391970	2	
R88	RES, Carbon Film 560 kohm 1/5 W J	3069564970	1	
R89	RES, Carbon Film 33 kohm 1/5 W J	3069333970	1	
R90	RES, Metal Film 390 ohm 1/5 W J	3029391970	1	
R91	RES, Carbon Film 680 kohm 1/5 W J	3069684970	1	
VD81-VD83	Vractor, SVC211SPA-C	2258817103	3	

PCB2	ASSEMBLY P.C.BOARD MIC (KS, PT INDO AREA ONLY)							
	CAPACITORS							
C401	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C402	Chip, CH	220	pF	50 V	J	3539221210	1	
C403	Electrolytic SG	10	uF	35 V	M	3479310061	1	
C404	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C405	Electrolytic SSE	4.7	uF	16 V	M	3479147935	1	
C406	Chip	0.006	uF	50 V	K	3539562820	1	
C407	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C408	Chip, CH	560	pF	50 V	J	3539561210	1	
C409	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C410	Chip	0.033	uF	50 V	K	3539333820	1	
C411	Chip	0.006	uF	50 V	K	3539562820	1	
C412	Chip, CH	560	pF	50 V	J	3539561210	1	
C413/C414	Chip	0.047	uF	50 V	Z	3539473060	2	
C415	Chip	0.01	uF	50 V	K	3539103820	1	
C416/C417	Electrolytic SG	0.33	uF	50 V	M	3479333871	2	
C418	Chip	0.01	uF	50 V	K	3539103820	1	
C419	Electrolytic SG	10	uF	35 V	M	3479310061	1	
C420	Chip, CH	220	pF	50 V	J	3539221210	1	
C421	Electrolytic SSE	4.7	uF	16 V	M	3479147935	1	
C422/C423	Electrolytic SG	47	uF	16 V	M	3479347031	2	
C424	Chip	0.047	uF	50 V	Z	3539473060	1	
C425	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C426	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C427	Electrolytic SG	100	uF	10 V	M	3479310121	1	

Model No. : TX-747

Ref. No.	Description					Part No.	Q'ty	Version
	CONNECTOR							
CNT401	Lead Ass'y, 5P, 180mm					36405180732	1	
	INTEGRATED CIRCUITS							
IC401	KIA4559S/KIA75559S					2168206103	1	
IC402	ES56028E, Digital Echo					2138633001	1	
	RESISTORS							
R401	Chip	0	ohm	1/10 W	J	3099000870	1	
R402	Chip	4.7	kohm	1/10 W	J	3099472870	1	
R403	Chip	1	kohm	1/10 W	J	3099102870	1	
R404	Chip	100	kohm	1/10 W	J	3099104870	1	
R405	Chip	10	kohm	1/10 W	J	3099103870	1	
R406	Chip	15	kohm	1/10 W	J	3099153870	1	
R407	Chip	8.2	kohm	1/10 W	J	3099822870	1	
R408	Chip	12	kohm	1/10 W	J	3099123870	1	
R409	Chip	3.3	kohm	1/10 W	J	3099332870	1	
R410	Chip	12	kohm	1/10 W	J	3099123870	1	
R411	Chip	15	kohm	1/10 W	J	3099153870	1	
R412	Chip	10	kohm	1/10 W	J	3099103870	1	
R413	Chip	15	kohm	1/10 W	J	3099153870	1	
R414	Chip	6.8	kohm	1/10 W	J	3099682870	1	
R415	Chip	68	kohm	1/10 W	J	3099683870	1	
R416	Chip	6.8	kohm	1/10 W	J	3099682870	1	
R417	Chip	68	kohm	1/10 W	J	3099683870	1	
R418	Chip	27	kohm	1/10 W	J	3099273870	1	
R419	Chip	560	ohm	1/10 W	J	3099561870	1	
R420	Chip	15	kohm	1/10 W	J	3099153870	1	
R421/R422	Chip	330	ohm	1/10 W	J	3099331870	2	
R423	Chip	1	kohm	1/10 W	J	3099102870	1	
R424	Chip	100	kohm	1/10 W	J	3099104870	1	
R425	Chip	47	kohm	1/10 W	J	3099473870	1	
R426	Metal Film	10	ohm	1/5 W	J	3029100970	1	
R427	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
	MISCELLANEOUS							
8	Jack Phone					4438005510	1	
9	Shield Fence					6165146110	1	
10	Volume Mic, 10 kohm					3208052410	1	

PCB3	ASSEMBLY P.C.BOARD POWER							
C501-C503	Mylar	0.047	uF	100 V	J	3679473120	3	
C504	Electrolytic SD	4700	uF	25 V	M	3409347248	1	
C505	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C506	Ceramic Tubular	0.022	uF	25 V	Z	3579223530	1	KS,PT INDO D,A
(C506)	Not Used !							
C507	Electrolytic SG	1	uF	50 V	M	3479310971	1	KS,PT INDO D,A
(C507)	Not Used !							
D501/D502	1N4003, Rectifier					2058512108	2	
D503	1N4148, Switching					2058322101	1	KS,PT INDO D,A
(D503)	Not Used !							
IC501	KIA7808PI, Regulator					2168606116	1	
IC502	KIA7805PI, Regulator					2108499104	1	KS,PT INDO D,A
(IC502)	Not Used !							
R501	Metal Film	3.3	ohm	2 W	J	3029339570	1	KS,PT INDO D,A
(R501)	Not Used !							
CP501	Wafer, 6P					4428505810	1	

PCB4	ASSEMBLY P.C.BOARD FRONT							
	CAPACITORS							
C702/C703	Chip	0.047	uF	50 V	Z	3539473060	2	
C704	Electrolytic SSE	47	uF	10 V	M	3479147025	1	
C705	Electric Back-up	0.047	F	5.5 V		3438247315	1	
C706	Chip	0.1	uF	50 V	Z	3539104060	1	
C707	Chip, CH	22	pF	50 V	J	3539220210	1	
C708	Trimmer, CH	10	pF			3838001140	1	
C709	Chip, CH	33	pF	50 V	J	3539330210	1	
C710	Electrolytic SSE	10	uF	16 V	M	3479110035	1	
C713/C714	Chip	0.1	uF	50 V	Z	3539104060	2	
	CONNECTORS							
CNT701	Wafer, FPC, 20P					4426001120	1	
CNT703	Lead Ass'y, 4P, 80mm					36404080732	1	
	DIODES							
D701-D707	1N4148, Switching					2058322101	7	
	INTEGRATED CIRCUIT							
IC701	CXP82324-331Q, CPU, DWP449					2139322704	1	
	COIL							
L702	Inductor, 1 mH 03					2648610283	1	

Ref. No.	Description					Part No.	Q'ty	Version
	TRANSISTOR							
Q701	BKTC3199Y, NPN					2208610109	1	
	RESISTORS							
R701	Chip	100	kohm	1/10 W	J	3099104870	1	
R702-R706	Carbon Film	100	kohm	1/5 W	J	3069104970	5	
R707	Carbon Film	10	kohm	1/5 W	J	3069103970	1	
R708	Chip	10	kohm	1/10 W	J	3099103870	1	
R709-R711	Carbon Film	100	kohm	1/5 W	J	3069104970	3	
	MISCELLANEOUS							
X701	Crystal, 10MHz					3978011001	1	
FL701	FL Display, CM1361C					2328002306	1	
28	Switch Tact					4658003710	11	

PCB5	ASSEMBLY P.C.BOARD RMC							
C701	CAP, Electrolytic SG	10	uF	35 V		3479310061	1	
CNT703	Connector, Wire Trap, 5P					4428531104	1	
IC702	TFMT4380, Remote Sensor					2408005001	1	
29	Switch Tact					4658004010	1	

IC FUNCTIONAL BLOCK DIAGRAM

IC803 : AN7470



IC801 : LA1266



IC102, IC306, IC401 : KIA4559S/KIA75559S



IC304 : KIA4559S/KIA75559P



IC101 : LC7821



IC305 : TC9176P



IC301 : NJM2177FB3



IC502 : KIA7805PI
IC103 : KIA7806PI
IC501 : KIA7808PI



IC303 : GD4053B



IC802 : LM7001M



Pin Name

No	LM 7001	LM7001M
1	XOUT	XOUT
2	XIN	XIN
3	CE	NC
4	CL	CE
5	DATA	CL
6	$\overline{SYC}$	DATA
7	$\overline{BO1}$	$\overline{SYC}$
8	$\overline{BO2}$	$\overline{BO1}$
9	$\overline{BO3}$	$\overline{BO2}$
10	AMIN	$\overline{BO3}$
11	FMIN	NC
12	VDD1	AMIN
13	VDD2	NC
14	PD1	FMIN
15	PD2	NC
16	VSS	VDD1
17		VDD2
18		PD1
19		PD2
20		VSS

IC302 : NJU9701



FM FRONT - END (A, PT INDO, KS VERSION)



FM FRONT - END
FTA4 - 460V (D Version)



Ref. No.	Content	Ref. No.	Content	Ref. No.	Content	Ref. No.	Content	Ref. No.	Content	Ref. No.	Content	Ref. No.	Content
IFT	10.7 MHz	C1	22 pF	C11	1 pF	C21	8 pF	R1	33 KΩ	R11	33 KΩ	Q1	3SK 180
		C2	15 pF	C12	22 pF	C22	27 pF	R2	100 KΩ	R12	10 KΩ	Q2	2SC3142
L6	2.2 or 1 MHz	C3	0~5 pF	C13	22 pF	C23	20 pF	R3	100 KΩ	R13	10 KΩ	Q3	2SK 543
		C4	18 pF	C14	22 nF	C24	2 pF	R4	22~330 Ω	R14	1~1.8 KΩ	Q4	2SC2814
L1~L5, L7	AIR WIL	C5	7 pF	C15	0~22 nF	C25	15 pF	R5	33 KΩ	R15	10 KΩ	Q5	2SC2814
		C6	7 pF	C16	22 nF			R6	33 KΩ	R16	330 Ω	D1	KV1440
		C7	4~10 pF	C17	22 nF			R7	1~3.3 MΩ	R17	100 Ω	D2	KV1440
		C8	0~7 pF	C18	33~68 pF			R8	-	R18	470 Ω	D3	KV1440
		C9	5 pF	C19	0~5 pF			R9	10 KΩ	R19	330 KΩ	D4	KV1440
		C10	100 or 220 pF	C20	2 pF			R10	100~1 KΩ	R20	330 Ω		

NOTE

SCHEMATIC DIAGRAM I



	G	H	I	J	K	L

MAIN(PCB1) (※KS, PT INDO VERSION)



MAIN "L"ch. SIGNAL

CONNECTION DIAGRAM DIODES, TRANSISTORS AND ICS

Anode	SVC321 SPA-C SVC211 SPA-C	DTC114YS DTC114TS DTC323TS KSC2786R KTC3193 KTC3199	KTA1273	KTC3880	KIA7805PZ KI7806PI KIA7808PI	KIA4559P/KIA7555P
		B C E	E C B	B C E	IN GND OUT	8 1 4
KIA75559S	LA1266 NJU9701	NJM2177AFB3	LC7821	LM7001M	ES56028	
9	24 1 12	49 48 64 33 1 32 16 17	30 1 15	20 1 11 10	28 1 14	

SCHEMATIC DIAGRAM II



G	H	I	J	K	L

A, D VERSION)



NOTES
1. Resistor values are indicated in ohms unless otherwise specified
(K=1.000 M=1.000.000)
2. Capacitor values are indicated in microfarades unless otherwise specified.
(p=micro-microfarades)

CAUTION
Safety precaution to be followed during servicing
1) Since those parts marked with ⚠ are critical parts for safety. use only the one described in the parts list
2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

MAIN "L"ch. SIGNAL

CENTER SIGNAL

SURROUND SIGNAL

NOTES
1. Resistor values are indicated in ohms unless otherwise specified
(K=1.000 M=1.000.000)
2. Capacitor values are indicated in microfarades unless otherwise specified.
(p=micro-microfarades)

CAUTION
Safety precaution to be followed during servicing
1) Since those parts marked with ⚠ are critical parts for safety. use only the one described in the parts list
2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

SCHEMATIC DIAGRAM III

A	B	C	D	E	F	G

1
2
3
4
5
6
7
8
9

MAIN(PCB1) TUNER PART



MAIN(PCB1) (※A, KS, PT INDO VERSION)



FM SIGNAL

AM SIGNAL

TUNER "L"ch. SIGNAL

*REMARK

	R818	R852	R809	R84
KS, A	2K	3K3	18K	10K
PT	3K9	1K8	47K	3K3

G	H	I	J	K	L

) TUNER PART D VERSION



NOTES

1. Resistor values are indicated in ohms unless otherwise specified (K=1,000 M=1,000,000)
2. Capacitor values are indicated in microfarades unless otherwise specified. (p=micro-microfarades)

CAUTION

Safety precaution to be followed during servicing

1) Since those parts marked with ⚠ are critical parts for safety, use only the one described in the parts list

2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

RMC(PCB5)



POWER(PCB3) (※KS, PT INDO VERSION)



POWER(PCB3) (※ A/D VERSION)





MIC(PCB2) (※KS, PT INDO VERSION ONLY)



R852	R809	R843 R845	R832 R833	R834 R836	R831	C846 C847
3K3	18K	10K	22K	5K2	47K	1N5
1K8	47K	3K3	27K	5K6	33K	1N

WIRING DIAGRAM



Model No. : TX-747/757

L K J I H G

SYSTEM CONNECTOR, 15P
FROM AX-747 or AV-757

SYSTEM CONNECTOR, 13P
FROM DD-757

PCB1

CNT104

CNT103

CNT101

RED

CNT102

CNT105

SYSTEM CONNECTOR, 13P
TO CDC-757 or VCDC-757

SYSTEM CONNECTOR, 8P
TO AX-747 or AV-757

CNT401

CNT701

WHITE

MAIN B'D
400400150OB

CNT702

FM FRONT END

BAR CODE

IN | ICT | OP | ADJ | F1

PCB4

RED

CP501

CP502

POWER B'D
400551270OB

F1 | ADJ | OP | ICT | IN

TO POWER CABLE, 19P

▪ VCDC-757/CDC-757 ▪

SPECIFICATIONS

GENERAL

Transmission bit ratio	4.3218 Mbit/sec
Transmission on clock	16.9344 MHz
Error correction	CIRC C1: Double correction C2: Quadruple correction

PICK-UP

System object lens type	Optical pick-up
Object lens drive system	2 Dimensional parallel drive type
Optical source	Semiconductor laser
Wave length	780 nm
Tracking system	3 Beam tracking servo type

OTHER

D/A Converter	1 bit twin with digital filter

ELECTRICAL

- Measuring methods in confirmity with EIAJ CP-307, CCIR 468-3
- Reference level: 0 dB
- Test disc: SONY CD-3 YEDS-7, A,BEX TCD725
- Filter: 30 kHz, 18 dB/oct low pass filter

Description		Track	Nominal	Limit
Frequency Response at 20 Hz - 20 kHz		2 - 13	±1.0 dB	±2.0 dB
Signal to Noise Ratio at 1 kHz (Weighted A)		23	75 dB	70 dB
Dynamic Range at 1 kHz, 60 dB (Weighted A)		20	75 dB	70 dB
Total Harmonic Distortion at 0 dB				
	100 Hz	4	0.06%	0.1%
	1 kHz	7	0.06%	0.1%
	20 kHz	13	0.08%	0.1%
Channel Separation at 1 kHz (Selective)		30, 34	55 dB	50 dB
Channel Unbalance at 1 kHz		7	±1.0 dB	±2.0 dB
Access Time (Track to next track)			7 sec	9 sec
Disc Defects				
	Black dot	10 - 15	700 uM	700 uM
	Interrupt	3 - 9	800 uM	800 uM
	Fingerprint	17 - 19	ALL	ALL
De-emphasis		39	±0.2 dB	±0.3 dB
		40	±0.3 dB	±0.5 dB
		41	±0.5 dB	±1.0 dB

ENVIRONMETAL

Test to specification

Temperature between 59°F (15℃) and 95°F (35℃) and relative humidity between 45% and 75%, with power supply voltage of 10% the normal supply voltage.
Test disc: SONY,YEDS-7 or ABEX TCD784, TCD725.

Operation

Unit must work properly and correctly at the temperature range from 32°F (0℃)to 113°F (45℃) and the relative humidity from 40% to 80%, and with the supply voltage.

Storage

Temperature test: 48 hours each at -40°F (-40℃) and 149°F (65℃).
Humidity test: 40℃ 95% relative humidity.

BLOCK DIAGRAM I

Model No : CDC-757/VCDC-757



BLOCK DIAGRAM II

Model No. : VCDC-757



LASER BEAM SATETY PTECATIONS

CLASS 1 LASER PRODUCT

CLASS 1
LASER PRODUCT

CAUTION
Invisible laser radiation when the unit is open. DO not stare into beam.

CAUTION: USE OF ANY CONTROLS, ADJUSTMENT, OR PROCEDURES OTHER THAN THOSE SPECIFIED HEREIN MAY RESULT IN HAZARDOUS RADIATION EXPOSURE.

Do not look directly at the laser beam coming from the pickup or allow it to strike against your skin.



This compact disc player uses a pickup that emits a laser beam. The laser beam is emitted from the location shown in the figure. When checking the laser diode, be sure to keep your eyes at least 1 foot away from the pickup lens when the diode is turned on. Do not look directly at the laser beam.



CAUTION:
Using controls and adjustment, or doing procedures other than those specified herein, may result in hazardous radiation exposure.

SAFETY PRECAUTIONS

CAUTION

RISK OF ELECTRIC SHOCK.
DO NOT OPEN.

CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK, DO NOT REMOVE COVER (OR BACK). NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.

This symbol is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.

This symbol is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

Caution: To prevent electric shock do not use this (polarized) plug with an extension cord, receptacle or other outlet unless the blades can be fully inserted to prevent blade exposure.

Attention: Pour prévenir les chocs électriques ne pas utiliser cetre fiche polarisée avec un prolongateur, une prise de courant ou une autre sortie de courant, sauf si les lames prévent étre insérées à fond sans en laisser aucune partie à découvert.

WARNING

To prevent fire or shock hazard, do not expose the unit to rain or moisture.

HANDLING LASER PICKUP

The laser diode in the optical system of this player can be damaged by electrostatic discharge from your clothes or your body. Proper electrostatic grounding for service personal is required during servicing.

BEFORE REPAIRING THE COMPACT DISC PLAYER

Preparation

- Human Body Grounding:
  Many of the components used in this compact disc player, including the laser pickup, are sensitive to electrostatic discharge. Service personal should be grounded with an electrostatic armband (1 Mohm).

- Caution:
  Static charge on clothing does not escape through a body grounding wrist band.
  Be careful not to contact the pickup or electrical components with your clothing.

- Workbench and Tool Grounding:
  A properly-grounded electroconductive plate (1 Mohm) or metal sheet should be fitted to the workbench surface. Tools and instruments (such as soldering irons and scopes) should be grounded to prevent AC leakage.

Fig. 1



Fig. 2

Note: Laser diodes are so susceptible to damage from static electricity that, even if a static discharge does not ruin a diode, it can shorten its life or cause it to work improperly.

PICKUP REPLACEMENT

Caution:
Laser diodes are extremely susceptible to damage from static electricity. Even if a static discharge does not ruin the diode, it can shorten its life or cause it to work improperly. When replacing the pickup, take appropriate measures, such as using a conductive mat and a grounded soldering iron, to protect the laser diode from static damage.

1. Remove the CD mechanism assembly by referring to the "EXPLODED VIEW II" on page 72 (See Fig. 3).



Fig. 3

2. Remove four screws S12 (See Fig. 4).



Fig. 4

3. Remove the gear A (See Fig. 5).
4. Pull out the slide shaft.



Fig. 5

5. Remove the pickup (See Fig. 6).



Fig. 6

6. Refer to the EXPLODED VIEW II of the compact disc mechanism on page 72 for detailed illustrations.

OPERATION CHECK

When the power switch is turned on after the chucking arm is removed, observe the objective lens and check the following. (The optical system block should be at the lead-in position when it is checked.)

1. The disc table should be at the innermost position after the chucking arm is removed.
2. The diffused light of the laser beam can be seen when the power switch is turned on.
3. Vertical (up and down) movement of the objective lens takes place (2 or 3 times).

DISASSEMBLY PROCEDURES

REFER TO PAGES 71 AND 82.

1 COVER TOP REMOVAL
Remove 5 screws ⓐ and then remove the Cover Top ❼.

2 FRONT PANEL ASSEMBLY REMOVAL
1. Remove the Cover Top ❼, referring to the previous step 1
2. Remove 8 screws ⓑ.
3. Disconnect (CP401) from Front1 P.C.Board (PCB4) and then remove the Front Panel Assembly ⒶⒶ.

3 FRONT1, 2 P.C.BOARD (PCB4, PCB5) REMOVAL
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Remove the Front Panel Assembly ⒶⒶ, referring to the previous step 2.
3. Remove 6 screws ⓒ and then remove the Front1, 2 P.C.Board (PCB4, PCB5).

4 ASSEMBLY MECHANISM REMOVAL
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Remove the Front Panel Assembly ⒶⒶ, referring to the previous step 2.
3. Remove 4 screws ⓓ.
4. Disconnect (CP301) from CNT P.C.Board (PCB3) and then remove the Assembly Mechanism ⓫.

5 DSP P.C.BOARD (PCB2) REMOVAL
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Do steps 2 and 4.
3. Remove the card cable from wafer (CP203 and CP202) on the DSP P.C.Board (PCB2)
4. Disconnect (CP201) from the DSP P.C.Board (PCB2).
5. Remove 3 screws ⓔ and then remove the DSP P.C.Board (PCB2).

6 MAIN P.C.BOARD (PCB1) REMOVAL
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Do steps 2 and 4.
3. Remove 3 screws ⓕ and then remove the 2 taps (attached to the Main P.C.Board) from the body mechanism.
4. Remove the card cable from wafer (CP109) on the Main P.C.Board (PCB1).
5. Disconnect (CP102, CP101, CN106 and CP103) from the Main P.C.Board (PCB1).
6. Disconnect (CP901, CP902, CP903 and CP904) from the MPEG P.C.Board (PCB7). (This step is applicable for only VCDC757)

7 MPEG P.C.BOARD (PCB7) REMOVAL
(This step is applicable for only VCDC757)
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Do steps 2 and 4.
3. Disconnect (CP901, CP902, CP903 and CP904) from the MPEG P.C.Board (PCB7)
4. Remove 3 screws ⓖ and then remove the MPEG P.C.Board (PCB7).

8 VIDEO JACK P.C.BOARD (PCB6) REMOVAL
(This step is applicable for only VCDC757)
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Disconnect (CP601) from the MPEG P.C.Board (PCB7).
3. Remove a screw ⓗ and then remove the Video Jack P.C.Board (PCB6).

9 CNT P.C.BOARD (PCB3) REMOVAL
1. Remove the Cover Top ❼, referring to the previous step 1.
2. Disconnect (CP301) from the CNT P.C.Board (PCB3).
3. Remove 2 screws ⓘ and then remove the CNT P.C.Board (PCB3).

CIRCUIT DESCRIPTION

1. IC201 : CXP82324 (CMOS 8bit 1-Chip Microcomputer)

1-1. Pin Connection Diagram



1-2. Block Diagram



1-3. Input and Output Terminal Functions

Pin No.	Symbol	Description
1	GFS	GFS signal input from CXD2515Q.
2	NC	Not used !
3	SENS	Sense signal output to pick-up unit (M-101).
4	LD-ON	LD-on signal output to pick-up unit (M-101).
5	XLAT	Serial latch data output to CXD2515Q.
6	VIDEO SEL	Output for controlling audio signal to 74HC157. If video CD, then "H" and if normal CD, then "L".
7	COMEN (MPEG)	Input for checking data transmission to MPEG CPU.
8	SCK (MPEG)	Clock data output to MPEG CPU.
9	SO (MPEG)	Serial data output to MPEG CPU.
10	SI (MPEG)	Serial data input from MPEG CPU.
11	SQCK	Clock data input for subcode-Q readout to CXD2515Q.
12	SQSO	Subcode-Q signal input from CXD2515Q.
13	DATA	Serial data output to CXD2515Q.
14 ~ 17	KEY INPUT	Data input for key scan.
18	NC	Not used !
19	ONE MODE	Input for test mode for production.
20	NC	Not used !
21	XRST	Output for resetting CXD2515Q. (At "L", it is active)
22	DIGI-LINK	Input for remocon data.
23	NC	Not used !
24	DISC NO SENS	Roulette sensor data input from mecha.
25	SPDCON	Output for roulette motor to stop the disc roulette.
26, 27	MPX SEL	According to settings, each MPX mode operates as follows.
28, 29	NC	Not used !
30	RST	Input for resetting CPU. (At "L", it is active)
31	EXTAL	Input of 10.0 MHz oscillator crystal.
32	XTAL	Output of 10.0 MHz oscillator crystal.
33	Vss	Ground
34	NC	Not used !
35	LINE MUTE	Output for audio mute. (At "H", it is active)
36	ROULETTE BWD(-)	Output for driving motor to rotate counter clockwise the roulette.
37	ROULETTE FWD(+)	Output for driving motor to rotate counter clockwise the roulette.
38	PICK-UP DOWN	Output for chucking motor to draw down the pick-up.
39	PICK-UP UP	Output for chucking motor to draw up the pick-up.
40	TRAY OPEN	Output for driving motor to open the tray. (At "H", it is active)
41	TRAY CLOSE	Output for driving motor to close the tray. (At "H", it is active)
42 ~ 57	SEGMENT	Segment signal output for FIP.
58 ~ 61	NC	Not used !
62 ~ 70	GRID	Grid signal output of for FIP.
71	V_{FDP}	-30 V power supply for FIP controller.
72, 73	Vdd	+5 V power supply for CPU.
74	NC	Not used !
75	SELF WAKE-UP	Input for waking up CPU.
76	VCDC/CDC SEL	Input for selecting VCDC-757 or CDC-757. If "H", then VCDC-757 and if "L", then CDC-757.
77	PWR ON/OFF	Output for power off when function changed. (At "L", it is active)
78	POWER DOWN	Input for detecting power-down. (At "L", it is active)
79	FOK	FOK signal input from CXD2515Q.
80	SCOR	GFS signal input from CXD2515Q.

According to settings, each MPX mode operates as follows.

Pin No.		Signal Output	
26	27	L-CH.	R-CH.
"L"	"H"	L-CH.	L-CH.
"H"	"L"	R-CH.	R-CH.
"H"	"H"	L+R-CH.	L+R-CH.
"L"	"L"	L-CH.	L-CH.

2. APC CIRCUIT

A semiconductor laser is used as the light source for the optical pickup. As the laser diode has large negative temperature characteristics in its optical output when driven with a constant current, a circuit must be provided to stabilize this output. For this purpose, a monitor diode which detects the optical output of the laser diode is used in the semiconductor laser.
As the laser diode emits light from its bonded surface, light is emitted both in front and behind. The light emitted behind is monitored with the monitor diode installed on its rear surface, and the optical output is thus controlled. The light emitted in front becomes the light source for the pickup.

Fig. 7 shows the APC circuit.
When the temperature rises and the optical output decreases, the monitor diode current (Is) decreases, the electric potential of OE-IC pin 24 rises, the base current of the driving transistor increases, and the laser diode current increases. This causes the reduced optical output to return to its former level.



Fig. 7

3. FOCUS SERVO

3-1. Optical pickup

This set employs a three-beam optical pickup comprised of six division photodiodes, A through F as shown in Fig. 8. The four photo diodes (A through D) at the center provide focus error detection by using their property to allow the beam to focus into a round image only at a certain point.
The sums of outputs from diagonal two elements of four division photo diodes (A+C and B+D) are compared by the differential amplifier in OE-IC to detect the shape of the beam image.
The remaining two diodes (E and F) provide tracking error detection by means of sub-beam spots.



Three spotted (six-division) photo diodes

Fig. 8

3-2. Focus error detecting operation

Fig. 9 shows the reflected laser beam from a disc is polarized 90° with the beam-splitter and sent to the cylindrical lens. The beam passed through this cylindrical lens is then sent to the four division photo diodes and focuses into an image whose shape varies with the distance between the disc and the objective lens. Such change in the beam shape causes the current flowing from the photo diodes to vary.



Fig. 9

3-3. Tracking error detection system

Fig. 10 shows the principle of the tracking error detection system which employs the three beam system.

The laser beam is divided into the main beam and two sub-beams by diffraction grating and they are arranged on one line. The center line connecting these three beams has a slight offset angle against the main beam. The main beam is received by photo diodes A, B, C and D and two sub-beams by E and F respectively.

Fig. 10-A shows the on-track state. As both auxiliary beams 1 and 2 are slightly on the track in this state, the outputs of photo diodes E and F are equal and the tracking signal is 0(zero). When the track is shifted to the left (Fig. 10-B), the auxiliary beam 1 is off the pit. This allows more light to be received by the photo diode E, resulting in positive (+) tracking signal output. On the other hand, when the track is shifted to the right (Fig. 10-C), the amount of light received by the photo diode F increases, resulting in negative (-) tracking signal output. And these extreme signals are detected as tracking error signals.



Fig. 10

TROBLESHOOTING

[Repair item 1] At power on, "0" and some parts are not displayed.





Fig. 11

[repair item 2] Tray cannot be opened and closed by pressing "OPEN/CLOSE" button.



[Repair item 3] "0" is displayed instead of total playing time and track number.



[Repair item 3-A] Sled motor dose not move.



[Repair item 3-B] Laser does not emit.



Fig. 12

[Repair item 3-C] Object lens of pickup unit does not move up and down.



Fig. 13

[Repair item 3-D] Spindle motor does not rotate.





Fig. 14



Fig. 15

[Repair item 4] No sound signal.



MECHANICAL PARTS LIST

Ref. No.	Description	Parts No.	Q'ty	Version
	PACKAGE			
	Carton Box	049605258410	1	KS
	Carton Box	049605258403	1	A,D,PT INDO
	Cushion Poly	9722041310	1	
	Film Soft PE	9715000120	1	
	ACCESSORIES			
	Cord Patch, 1P	4328201910	1	KS
	Demo Disc, Video CD	5058001210	1	KS
	CABINET & CHASSIS			
1	Door (CDC757)	048663001412	1	
(1)	Door (VCDC757)	048663001411	1	KS
2	Base Door	6043010510	1	
3	Badge, INKEL	048535045411	1	KS
(3)	Badge, SHERWOOD	048535045421	1	A,D,PT INDO
4	Panel Front (CDC757)	048602019912	1	
(4)	Panel Front (VCDC757)	048602019911	1	KS
5	Window	8553023510	1	
6	Body Front	048521009811	1	
7	Cover Top	046123017911	1	
8	FIP, 9CEM6	2328130322	1	
9	Shield Fence	6163115610	1	
10	Heatsink	7505202410	1	
11	Assembly Mechanism	5728000840	1	
12	Button Function	048543070211	1	
13	Button Skip	048543070311	1	
14	Switch Tact	4658004410	2	
15	Switch Tact	4658003710	10	
16	Foot	6035104310	2	
17	Rubber Foot	6715021230	2	
18	Chassis Main	6121615010	1	
19	Plate Ground	6165143510	1	
20(CP302)	Connector, System	4428513820	1	
21	Jack RCA	4438113810	1	
22	Chassis Back (VCDC757)	'046102045111	1	KS
(22)	Chassis Back (CDC757)	'046102045211	1	KS
(22)	Chassis Back	'046102045221	1	A
(22)	Chassis Back	'046102045251	1	D
(22)	Chassis Back	'046102045291	1	PT INDO
	HARDWARE KIT			
S1	Screw, #B BTT 3x8B (VCDC757)	8179130083	27	KS
(S1)	Screw, #B BTT 3x8B (CDC757)	8179130083	24	
S2	Screw, #2 FTC 3x10B	8129230083	9	
S3	Screw, #B WTT 3x6Y	8179230061	2	
S4	Screw Gurond, 3x10B (VCDC757)	8155000710	2	KS
(S4)	Screw Gurond, 3x10B (CDC757)	8155000710	1	
S5	Screw, #2 BTC 2.6x8B	8109260083	3	
	MISCELLANEOUS			
	Connector, Lead Ass'y, 6P, 80mm	435206082042	1	
	Connector, Lead Ass'y, 14P, 420mm	435214422022	1	
	Card Cable, 12P	4118512100	1	
	Card Cable, 19P	4118619085	1	
PCB1	P.C.Board Main	4004000700	1	
PCB2	P.C.Board DSP	4004000710	1	
PCB3	P.C.Board CNT	4004000730	1	
PCB4	P.C.Board Front 1	4004000720	1	
PCB5	P.C.Board Front 2	4004000750	1	
PCB6	P.C.Board Video Jack (VCDC757)	4004000740	1	KS
(PCB6)	Not Used ! (CDC757)			A,D,PT INDO
PCB7	P.C.Board MPEG (VCDC757)	4009000100	1	KS
(PCB7)	Not Used ! (CDC757)			A,D,PT INDO
11	**ASSEMBLY MECHANISM (ICM02D)**	**5728000840**		
1	Gear Center	7105000410	2	
2	Gear Pulley	7105000510	1	
3	Gear Roulette	7105000610	1	
4	Gear Motor	7105000710	1	
5	Gear Worm	7105000810	1	
6	Bracket Side	6505133510	4	
7	Chuck Chassis	6023408710	1	
8	Bracket Motor	6023801010	1	
9	Frame Front	6023601320	1	
10	Guide Chuck	6063103110	1	
11	Gear Loading	7103001910	1	
12	Base D.U	6062101520	1	
13	Cam Gear	7142000510	1	
14	Cover Cam	7142000610	1	
15	Roultte	7121400320	1	
16	Tray Roulette	6021800410	1	
17	Body Mecha	6021601310	1	
18	Rubber Limit	6715022810	2	
19	Rubber Bracket	6715023310	3	
20	Shaft Gear Roulette	7005007910	1	
21	Cover Roulette	6735011410	1	
22	Sheet Tray	6705022510	1	

Ref. No.	Description	Parts No.	Q'ty	Version
23	Sheet Tapping	6725003610	1	
24	Belt Loading	7165002510	1	
25	P.C.Board Sensor	4009500500	1	
26	Base Magnet	6063103010	1	
27	Cover Magnet	6023408610	1	
28	Magnet	5125000910	1	
29	Pulley Motor	7113001310	1	
30	Rubber Damping	6715024510	4	
31	Spring Damping	6555014010	4	
32	Poly Washer (Ø2.1)	8338300710	1	
33	Poly Washer (Ø4.1)	8338301310	1	
34	Poly Washer (Ø5.2)	8338301410	1	
35	Poly Washer (Ø3.1)	8338301210	1	
36	Screw Mecha	8155001210	3	
37	Screw Damping	8155001610	4	
38	Screw BM 2x3Y	8009120031	2	
39	Screw BM 2.6x4Y	8009126041	4	
40	Screw #1 WPT 2.6x8Y	8159126081	2	
41	Screw #1 BT 2.6x8Y	8109126080	2	
42	Screw #1 BT 3x8Y	8109130081	3	
43	Screw #1 BT 3x10B	8109130101	6	
44	Screw #1 WPT 3x15Y	8159130151	1	
45	Screw BTTS 3x4Y	8109430051	1	
46	Connector, Lead Ass'y, 5P	436105080121	1	
47	Connector, Lead Ass'y, 5P	436105080121	1	
48	Connector, Wafer, 5P	5798100307	1	
49	Connector, Lead Ass'y, 2P	436202070132	1	
50	Connector, Wafer, 2P		1	
51	Resistor, 150 ohm, 1/5 W, J	3069151970	1	
52	Resistor, 10 kohm, 1/5 W, J	3069103970	1	
53	Drive Unit, KSM-2401ABM)	5728001110	1	
54	Motor, RF-500TB-12560	5558001810	1	
55	Motor, FF-130SH-14230	5558200410	1	
56	Switch Lever, SSCF-21004A	4638003410	2	
57	Photo Sensor, SG-23F1	78001111	1	

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol ⚠ in the parts list are of special significance to safety. When replacing a component identified with ⚠, use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.

EXPLODED VIEW I

Model No : CDC-757/VCDC-757

CABINET & CHASSIS



*** REMARK**
This marks (▭) is applied for only VCDC-757.

EXPLODED VIEW II

Model No : CDC-757/VCDC-757

MECHANISM



PRINTED CIRCUIT BOARDS

MAIN(PCB1)



DSP(PCB2)



FRONT 1(PCB4)



FRONT 2(PCB5)



CNT(PCB3)



VIDEO JACK(PCB6) : VCDC757ONLY



MPEG(PCB7) : VCDC757 ONLY

- Top View -



-Bottom View -



ELECTRICAL PARTS LIST

PRODUCT SAFETY NOTICE : Products marked with ⚠ have special characteristics important to safety.
If you replace any of these components, read carefully the product safety notice in this manual.
Don't degrade the safety of the product through improper servicing.
Resistor/Capacitor tolerance – D : (±0.5%), J : (±5%), K : (±10%), M : (±20%), Z : +80, – 20%)

Ref. No.	Description					Parts No.	Q'ty	Version
PCB1	**ASSEMBLY P.C.BOARD MAIN**							
	CAPACITORS							
C101	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C102	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C103	Ceramic Tubular	1000	pF	50 V	J	3519102935	1	
C105	Ceramic Tubular	220	pF	50 V	J	3519221935	1	
C106/C107	Electrolytic SG	100	uF	10 V	M	3479310121	2	
C108/C109	Ceramic Tubular	0.1	uF	50 V	J	3519104935	2	
C110	Electrolytic SG	3.3	uF	50 V	M	3479333971	1	
C111	Electrolytic SG	2.2	uF	50 V	M	3479322971	1	
C113/C114	Electrolytic SG	100	uF	10 V	M	3479310121	2	
C115	Ceramic Tubular	0.022	pF	50 V	J	3519223935	1	
C116	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C117	Ceramic Tubular	220	pF	50 V	J	3519221935	1	
C118	Ceramic Disc, CH	33	pF	50 V	J	3528330210	1	
C119	Ceramic Tubular	0.022	pF	50 V	J	3519223935	1	
C120	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C121	Ceramic Tubular	0.022	pF	50 V	J	3519223935	1	
C122/C123	Electrolytic SG	100	uF	10 V	M	3479310121	2	
C124-C128	Ceramic Tubular	120	pF	50 V	J	3519121935	5	
C129	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C130	Ceramic Tubular	100	pF	50 V	J	3519101935	1	
C131	Mylar	0.001	uF	100 V	J	3679102120	1	
C132	Ceramic Tubular	120	pF	50 V	J	3519121935	1	
C133	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C134	Ceramic Tubular	120	pF	50 V	J	3519121935	1	
C135	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C136	Ceramic Tubular	120	pF	50 V	J	3519121935	1	
C137	Ceramic Tubular	100	pF	50 V	J	3519101935	1	
C138	Ceramic Tubular	100	pF	50 V	J	3519101935	1	
C139	Mylar	0.001	uF	100 V	J	3679102120	1	
C140	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C141	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C142	Ceramic Tubular	0.1	uF	50 V	J	3519104935	1	
C143	Electrolytic SG	100	uF	10 V	M	3479310121	1	
C144	Ceramic Tubular	120	pF	50 V	J	3519121935	1	
C701	Electrolytic SG	470	uF	10 V	M	3479347121	1	
C702	Electrolytic SG	470	uF	10 V	M	3479347121	1	
C704	Ceramic Tubular	1000	pF	50 V	J	3519102935	1	
	CONNECTORS							
CN104	Lead Ass'y, 5P, 220mm					436205223782	1	
CN105	Lead Ass'y, 2P, 80mm					436101083167	1	
CN106	Lead Ass'y, 14P, 420mm					435214423822	1	
CN107	Lead Ass'y, 7P, 180mm					436207183332	1	
CN108	Lead Ass'y, 6P, 80mm					436206083132	1	
CN110	Lead Ass'y, 5P, 100mm					436205103132	1	
CP101	Wafer, 5P					4428513450	1	
CP102	Wafer, 5P					4428525550	1	
CP103	Wafer, 5P					4428506910	1	
CP109	Wafer, FPC, 19P					4428526316	1	
	DIODES							
D101	Zener, UZ 5.1 BSB					2258599103	1	
D102-D111	1N4148, Switching					2058322101	10	
D112	Zener, UZ 5.1 BSB					2258599103	1	
D113-D119	1N4148, Switching					2058322101	7	
	INTEGRATED CIRCUITS							
IC101	CXP82324-330Q					2139322703	1	
IC102	GD74HC157					2139036002	1	
IC103	SM5874AM, DA Converter					2139937001	1	
IC104/105	KIA4559S/KIA75559S					2168206103	2	
IC106	NJM4052BCF					2168027107	1	
IC107	TA7291S					2168007204	1	
IC108	KA7805, Regulator					2168602105	1	
	COILS							
L101-L104	Inductor, 10 uH					2648610082	4	
	TRANSISTORS							
Q101/Q102	DTC114YS					2208622106	2	
Q103-Q105	KTC3198Y, NPN					2208606105	3	
Q106/Q107	KTA1015/BKTA1266Y, PNP					2208206105	2	
Q108/Q109	KTC3198Y, NPN					2208606105	2	
Q110	DTC114YS					2208622106	1	
Q111/Q112	KTA1015/BKTA1266Y, PNP					2208206105	2	
Q113	DTC114YS					2208622106	1	
Q114	KTA966A/KTA1273, PNP					2228106104	1	
Q115	DTC114YS					2208622106	1	
Q116	KTA966A/KTA1273, PNP					2228106104	1	
	RESISTORS							
R100/R101	Carbon Film	2.2	ohm	1/5 W	J	3069229970	2	
R102	Carbon Film	3.3	kohm	1/5 W	J	3069332970	1	
R103	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R104	Carbon Film	10	kohm	1/5 W	J	3069103970	1	
R105	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R106	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R107	Carbon Film	1.2	kohm	1/5 W	J	3069122970	1	
R108	Carbon Film	47	kohm	1/5 W	J	3069473970	1	
R109	Carbon Film	10	kohm	1/5 W	J	3069103970	1	
R110	Carbon Film	2.2	ohm	1/5 W	J	3069229970	1	
R111-R113	Carbon Film	68	kohm	1/5 W	J	3069683970	3	
R114	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R115	Carbon Film	68	kohm	1/5 W	J	3069683970	1	
R116	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R117	Metal Film	1	ohm	1/5 W	J	3029109970	1	
R118	Carbon Film	4.7	kohm	1/5 W	J	3069472970	1	
R119	Carbon Film	3.3	kohm	1/5 W	J	3069332970	1	
R120	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R121	Metal Film	33	ohm	1/5 W	J	3029330970	1	
R122/R123	Metal Film	560	ohm	1/5 W	J	3029561970	2	
R124	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R125	Metal Film	56	ohm	1/5 W	J	3029560970	1	
R126/R127	Metal Film	2.2	kohm	1/5 W	J	3029222970	2	
R128	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R129	Metal Film	270	ohm	1/5 W	J	3029271970	1	
R130	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R131-R134	Carbon Film	47	kohm	1/5 W	J	3069473970	4	
R135	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R136	Metal Film	680	ohm	1/5 W	J	3029681970	1	
R137	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R138	Carbon Film	120	kohm	1/5 W	J	3069124970	1	
R139	Carbon Film	68	kohm	1/5 W	J	3069683970	1	
R140/R141	Carbon Film	120	kohm	1/5 W	J	3069124970	2	
R142	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R143	Metal Film	330	ohm	1/5 W	J	3029331970	1	
R144	Metal Film	220	ohm	1/5 W	J	3029221970	1	
R145	Metal Film	330	ohm	1/5 W	J	3029331970	1	
R146	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R147/R148	Metal Film	33	ohm	1/5 W	J	3029330970	2	
R149-R151	Metal Film	100	ohm	1/5 W	J	3029101970	3	
R152	Carbon Film	750	ohm	1/5 W	J	3069751970	1	
R153	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R154/R155	Metal Film	2.2	kohm	1/5 W	J	3029222970	2	
R156	Carbon Film	47	kohm	1/5 W	J	3069473970	1	
R157	Carbon Film	10	kohm	1/5 W	J	3069103970	1	
R158	Metal Film	330	ohm	1/5 W	J	3029331970	1	
R159	Carbon Film	220	kohm	1/5 W	J	3069224970	1	
R160-R163	Carbon Film	10	kohm	1/5 W	J	3069103970	4	
R164	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R165/R166	Carbon Film	33	kohm	1/5 W	J	3069333970	2	
R167	Carbon Film	47	kohm	1/5 W	J	3069473970	1	
R168	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R169	Carbon Film	33	kohm	1/5 W	J	3069333970	1	
R170	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R171	Carbon Film	68	kohm	1/5 W	J	3069683970	1	
R172/R173	Carbon Film	120	kohm	1/5 W	J	3069124970	2	
R174	Carbon Film	33	kohm	1/5 W	J	3069333970	1	
R175	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R176	Carbon Film	33	kohm	1/5 W	J	3069333970	1	
R177	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R178	Carbon Film	20	kohm	1/5 W	J	3069203970	1	
R180	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R181	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R182	Carbon Film	33	kohm	1/5 W	J	3069333970	1	
R183	Carbon Film	47	kohm	1/5 W	J	3069473970	1	
R184	Carbon Film	750	ohm	1/5 W	J	3069751970	1	
R185/R186	Carbon Film	33	kohm	1/5 W	J	3069333970	2	
R187	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R188	Metal Film	220	ohm	1/5 W	J	3029221970	1	
R189	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R190-R192	Carbon Film	47	kohm	1/5 W	J	3069473970	3	
R193	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R194	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R195	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R196	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R197	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R198	Carbon Film	20	kohm	1/5 W	J	3069203970	1	
R701-R706	Carbon Film	47	kohm	1/5 W	J	3069473970	6	
R707	Carbon Film	1	Mohm	1/5 W	J	3069105970	1	
R800	Carbon Film	68	kohm	1/5 W	J	3069683970	1	
	MISCELLANEOUS							
X101	Resonator, CST10.00MTW					3938131750	1	
X102	Crystal, 16.9344 MHz					3938101500	1	
8	FIP, 9CEM6					2328130322	1	
9	Shield Fence					6163115610	1	
10	Heatsink					7505202410	1	
PCB2	**ASSEMBLY P.C.BOARD DSP**							
	CAPACITORS							
C201	CeramicTubular	680	pF	50 V	J	3519681935	1	
C202	CeramicTubular	0.002	uF	50 V	Z	3519223935	1	
C203	Electrolytic SG	470	uF	10 V	M	3479347121	1	
C204	CeramicTubular	680	pF	50 V	J	3519681935	1	
C205/C206	CeramicTubular	0.022	uF	50 V	Z	3519223935	2	
C207	CeramicTubular	0.1	uF	50 V	Z	3519104935	1	
C208	CeramicTubular	0.0022	uF	50 V	Z	3519222935	1	
C210/C211	CeramicTubular	0.1	uF	50 V	Z	3519104935	2	
C212	CeramicTubular	680	pF	50 V	J	3519681935	1	
C214	Mylar	0.0015	uF	100 V	J	3679152120	1	
C216	CeramicTubular	0.01	uF	50 V	J	3519103935	1	
C217	CeramicTubular	470	pF	50 V	J	3519471935	1	
C219	CeramicTubular	0.1	uF	50 V	Z	3519104935	1	
C220	CeramicTubular	100	pF	50 V	J	3519101935	1	
C221	CeramicTubular	0.01	uF	50 V	J	3519103935	1	
C222	CeramicTubular	0.1	uF	50 V	Z	3519104935	1	
C223	CeramicTubular	470	pF	50 V	J	3519471935	1	
C224	CeramicTubular	0.022	uF	50 V	J	3519223935	1	
C225	CeramicTubular	0.047	uF	50 V	Z	3519473935	1	
C226/C229	CeramicTubular	0.022	uF	50 V	J	3519223935	2	
C230	Electrolytic SG	100	pF	10 V	M	3479310121	1	
C231	Electrolytic SG	3.3	uF	50 V	M	3479333971	1	
C232	CeramicTubular	0.1	uF	50 V	Z	3519104935	1	
	CONNECTORS							
CN109	Wafer, FPC, 19P					4428519826	1	
CP201	Wafer, 6P					4428525560	1	
CP202	Wafer, FPC, 12P					4428527170	1	
CN201	Lead Ass'y, 6P					4358102184	1	
	INTEGRATED CIRCUITS							
IC201	CXD2515Q					2138022116	1	
IC202	BA6297					2168027202	1	
	TRANSISTOR							
Q201	2SD1302					2008610102	1	
	RESISTORS							
R200	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R201	Carbon Film	68	kohm	1/5 W	J	3069683970	1	
R202	Metal Film	100	ohm	1/5 W	J	3029101970	1	
R203	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R204-R206	Carbon Film	15	kohm	1/5 W	J	3069153970	3	
R207/R208	Carbon Film	7.5	kohm	1/5 W	J	3069752970	2	
R209	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R210	Carbon Film	7.5	kohm	1/5 W	J	3069752970	1	
R211	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R213/R214	Carbon Film	68	kohm	1/5 W	J	3069683970	2	
R215	Carbon Film	7.5	kohm	1/5 W	J	3069752970	1	
R219	Metal Film	4.7	ohm	1/5 W	J	3029479970	1	
R220	Carbon Film	22	kohm	1/5 W	J	3069223970	1	
R221	Carbon Film	68	kohm	1/5 W	J	3069683970	1	
R222	Carbon Film	12	kohm	1/5 W	J	3069123970	1	
R223	Carbon Film	33	kohm	1/5 W	J	3069333970	1	
R224	Carbon Film	1	Mohm	1/5 W	J	3069105970	1	
R226	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R227	Carbon Film	10	kohm	1/5 W	J	3069103970	1	
R228/R230	Carbon Film	100	kohm	1/5 W	J	3069104970	2	
R231	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R232	Carbon Film	100	kohm	1/5 W	J	3069104970	1	
R233-R225	Metal Film	330	ohm	1/5 W	J	3029331970	3	
R236	Metal Film	1	kohm	1/5 W	J	3029102970	1	
R237	Carbon Film	7.5	kohm	1/5 W	J	3069752970	1	
R238	Carbon Film	15	kohm	1/5 W	J	3069153970	1	
R239	Carbon Film	7.5	kohm	1/5 W	J	3069752970	1	
R240	Carbon Film	4.7	kohm	1/5 W	J	3069472970	1	
PCB3	**ASSEMBLY PCB CNT**							
C301/C302	Capacitor, Mylar	0.0022	uF	100 V	J	3679222120	2	
C303	Capacitor, Electrolytic SG	47	uF	16 V	M	3479347031	1	
C304	Capacitor, Ceramic Tubular	0.047	uF	50 V	J	3519473935	1	
CP301	Connector, Wafer, 14P					4428517310	1	
20(CP302)	Connector, Wafer, 13P					4428513820	1	
D301/D302	Diode, 1N4148, Switching					2058322101	2	
Q301	Transistor, DTA114YS					2208222105	1	
Q302/Q303	Transistor, DTC323TS					2238422100	2	
Q304	Transistor, DTC114YS					2208622106	1	
R302/R303	Resistor, Metal Film	100	ohm	1/5 W	J	3029101970	2	
PCB4	**ASSEMBLY PCB FRONT 1**							
CN402	Connector, Lead Ass'y, 3P, 110mm					436103112632	1	
CP401	Connector, Wafer, 7P					4428525570	1	
15	Switch Tact					4658003710	10	
PCB5	**ASSEMBLY PCB FRONT 2**							
CN501	Connector, Lead Ass'y, 3P, 120mm					436103112632	1	
14	Switch Tact					4658004410	2	
PCB6	**ASSEMBLY PCB VIDEO JACK (VCDC757 ONLY)**							
C601	Capacitor, CeramicTubular	0.1	uF	50 V	Z	3519104935	1	
C602	Capacitor, Electrolytic SG	22	uF	16 V	M	3479322031	1	
CN601	Connector, Wafer, 2P					4428525520	1	
R601	Resistor, Metal Film	10	ohm	1/5 W	J	3029100970	1	
21	Jack RCA					4438113810	1	
PCB7	**ASSEMBLY PCB MPEG (VCDC757 ONLY)**							
	CAPACITORS							
C901/C902	Electrolytic SG	100	uF	10 V	M	3479310121	2	
C903-C905	Ceramic Chip	0.1	uF	50 V	J	3589104539	3	
C906	Not Used !							
C907-C909	Ceramic Chip	0.1	uF	50 V	J	3589104539	3	
C910	Not Used !						1	
C911	Ceramic Chip	0.1	uF	50 V	J	3589104539	1	
C912/C913	Ceramic Chip	15	pF	50 V		3589150139	2	
C914	Ceramic Chip	0.1	uF	50 V	J	3589104539	1	
C915	Not Used !							
C916-C923	Ceramic Chip	0.1	uF	50 V	J	3589104539	8	
C925/C926	Not Used !							
C927-C932	Ceramic Chip	0.1	uF	50 V	J	3589104539	6	
C933-C936	Not Used !							
C937/C938	Ceramic Chip	0.1	uF	50 V	J	3589104539	2	
C939	Electrolytic SG	470	uF	10 V		3479347121	1	
C941-C951	Ceramic Chip	0.1	uF	50 V	J	3589104539	11	
C952	Electrolytic SG	470	uF	10 V		3479347121	1	
C953	Ceramic Chip	0.1	uF	50 V	J	3589104539	1	
C954	Electrolytic Chip	10	uF	16 V		3478010031	1	
C955	Electrolytic SG	470	uF	10 V	M	3479347121	1	
C956	Not Used !							
C957	Ceramic Chip, CH	27	pF	50 V	J	3539270210	1	
C958	Ceramic Chip, CH	39	pF	50 V	J	3539390210	1	
TC901	Ceramic Chip	10	pF	50 V	J	3519100935	1	
V924	Electrolytic SG	100	uF	10 V	M	3479310121	1	
	CONNECTORS							
CP901	Wafer, 5P					4428516410	1	
CP902	Wafer, 5P					4428516410	1	
CP903	Wafer, 2P					4428508210	1	
CP904	Wafer, 6P					4428516510	1	
CN905	Lead Ass'y, 2P, 200mm					436202203782	1	
	RESISTORS							
R901-R906	Chip	10	kohm	1/8 W	J	3099103372	6	
R907	Chip	470	kohm	1/8 W	J	3099474870	1	
R908/R909	Chip	10	kohm	1/8 W	J	3099103372	2	
R910-R913	Chip	33	ohm	1/8 W	J	3099330372	4	
R916-R924	Chip	100	ohm	1/8 W	J	3099101170	9	
R925-R927	Chip	180	ohm	1/8 W	J	3099181870	3	
R928	Chip	47	kohm	1/8 W	J	3099473170	1	
R929	Chip	1	kohm	1/8 W	J	3099102170	1	
R930	Chip	75	ohm	1/8 W	J	3099750372	1	
R931	Chip	470	kohm	1/8 W	J	3099474870	1	
R932	Chip	10	ohm	1/8 W	J	3099100170	1	
R933	Not Used !							
R934	Chip	1	kohm	1/8 W	J	3099102372	1	
R935	Chip	10	kohm	1/8 W	J	3099103372	1	
R936	Chip	1	kohm	1/8 W	J	3099102372	1	
R937-R940	Chip	33	ohm	1/8 W	J	3099330372	4	
R941-R956	Chip	10	kohm	1/8 W	J	3099103372	6	
R957	Chip	33	ohm	1/8 W	J	3099330372	1	
R958	Chip	10	kohm	1/8 W	J	3099103372	1	
R959	Not Used !							
	INTEGRATED CIRCUITS							
U901	CXP82220-127Q					2138322205	1	
U902	KS9241B, CD-ROM Decoder					2139738001	1	
U903	HU62256ALJ					2139433000	1	
U904	STI3400DCV, MPEG V-Ecoder					2138535002	1	
U905	HY514260BJC-70, DRAM					2139433002	1	
U906	STI4510ACV, MPEG A-Ecoder					2138035004	1	
U908	CDVS110-ABYA, DATA-CTRL					2138535001	1	
U909A	GD74HC04D					2139036000	1	
U912	STV8438CV, DA-Converter					2138535003	1	
U913A/B	Not Used !							
U913C	GD74HC04D					2138036000	1	
U913D	GD74HC04D					2138036000	1	
U914	HY534256AJ-70, DRAM					2139433001	1	
U914	CXA1645N-T6, RGB Decoder					2139722001	1	
	MISCELLANEOUS							
U910	Crystal, OSC, 5 0 MHz					3938213002	1	
U911	Crystal, OSC, 13.5 MHz					3938213001	1	
XT901	Resonator, 10 MHz					3938131750	1	
XT902	Crystal, 24 MHz					3908101330	1	
XT903	Crystal, 3.579545 MHz					3938201988	1	

IC FUNCTIONAL BLOCK DIAGRAM

IC102 : GD74HC157



IC108 : KA7805



IC103 : SM5874AM



IC104/IC105
: KIA4559S/KIA75559S



IC107 : TA7291S



IC106 : NJM4052 BCF



TRUTH TABLE

INPUT			CHANNELS			
E	A_1	A_0	Y_0 - Z	Y_1 - Z	Y_2 - Z	Y_3 - Z
L	L	L	ON	OFF	OFF	OFF
L	L	H	OFF	ON	OFF	OFF
L	H	L	ON	OFF	ON	OFF
L	H	H	ON	OFF	OFF	ON
H	X	X	ON	OFF	OFF	OFF

IC202 : BA6297



IC201 : CXD2515Q



MPEG PART

U914 : CXD1645N - T6



U902 : KS9241B



U903 : HY62256ALJ



U912 : STV8438CV



U904 : STI3400DCV



U906 : STI4510ACV



U909A/U913C/U913D : GD74HC04D



U914 : HY534256AJ-07



U905 : HY514260BJC



SCHEMATIC DIAGRAM I

Model No. : VCDC-757

MPEG(PCB7)



NOTES

1. Resistor values are indicated in ohms unless otherwise specified. (K=1,000 M=1,000,000)
2. Capacitor values are indicated in microfarades unless otherwise specified. (pf=micro-microfarades)

CAUTION

Safety precaution to be followed during servicing

1) Since those parts marked with ⚠ are critical parts for safety, use only the one described in the parts list.

2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

SCHEMATIC DIAGRAM II



PIN CONNECTION DIAGRAM OF TRANSISTORS, DIODES AND ICS.

ZENER IN4148	DTA114YS DTC114YS DTC323TS	KA7805	KTD1302/2SD1302 KTC3198/KTC1815 KTA1266/KTA1015Y	KTA966A/KTA1273	TA7291S KIA4559S/KIA75559S	SM5874AM CXA1645N-76 CDVS110	GD74MC157 NJM4052BCF
							

G	H	I	J	K	L	M


IC201
XO25150
81:XRST
82:DIRC
98:LOCK
99:SSTP
100:SFOR
XTSL
VSS
FSTI
FSTO
CAM
C16M
MD2
DOUT
EMPH
WFCK
SCOR
SBSO
EXCK
SQSO
SQCK
MUTE
SENSE
SCLK
DFSW
AISK
DATA
XLAT
CLOCK
COUT
VDD
MIRR
DFCK
FOK
FSW
MON
MOP
MOS
C705 0.1
R240 4.7K
Q201 2SD1302
R236 1K
C224 22N
C226 22N
C229 22N
R230 100K
FROM VIDEO B'D
CN108
BCK
DATA
LRCK
DEMPH
G
5V
FOK
EMPH
XLAT
DATA
SENSE
X-TAL
SQCK
SQSO
SCOR
+5V
GFS
BCLK
DATA
LRCK
LD-ON
G
R136
R109
R106
R144
C704
C109
R142
R104
C103
R188 220
R137 1K
R139 68K
L101 10UH
IC102 74HC157
(EMPH) LRCK
DATA
L104 10UH
C122 100/10
C121 22N
R153 100
R149 100
R151 100
R150 100
C116 100/10
C115 22N
L102 10UH
L103 10UH
C113 100/10
R120 100
IC103
SM5874AM
C118 33P-CH
C114 33P-CH
X102 16.9344
R707 1M
C120 100/10
C119 22N
R158 330
R170 100K
R193 100K
R171 68K
R201 68K
C139 10/50
C141 10/50
IC106
NJM4052
Y0
Y2
L-OUT
Y1
E
VEE
VSS
VDD
X2
X1
X0
CN106
D113 1N4148
MUTE
R-CH
GND
L-CH
GND
+8V
VCDC+5V
-30V
FL
FL
CDID
CPU+5V
D-LINK
D-GND
R110 2.2
R100 2.2
C101 4.7/50
R157 10K
Q102 DTC114Y
R102 3.3K
R198 47K
IC108 7805
Q114 A1273
R156 47K
R152 47K
R115 68K
Q113 DTC114YS
D118 IN4148
C102 470/10
C114/10
Q116 A1273
R183 47K
R184 150
C135 1/50
+5V
G
TO VIDEO B'D
CN105
VCDC
Q115 DTC114YS
C111 2.2/50
R800 68K
CN107
CP401
FRONT 1(PCB4)
4004000720
INTORSCAN
SW402
REPATALL
SW403
SW405
RAMDOMPLAX
SW408
REVERPLAY
/SELSCT
SW409
SW410
/STILL
SW407
PREV
NEXT
SW401
SW404
SW405
CN402
CN501
OPEN/CLOSE
SW411
SW412
DISC SKIP
4004000750
FRONT 2 (PCB5)
V-CD
PBC
REVERT
PROG
AUTO EDIT
GRAPHICS
PEAK
DELETE
A-B
RANDOM
REPEAT
ALLDISCS
MPX
INTRO
SCENE
TRACK
INDEX
STEP
F101
C108 0.1
C142 0.1
C143 0.1
D106 1N4148
R138 120K
R140 120K
R141 120K
R173 120K
R172 120K
120K X 11
CP301
MUTE
RCH
AGND
LCH
GND
+8V
VCDC+5V
-30V
FL
FL
CDID
CPU+5V
DIGI-LINK
D GND
Q303 DTC323TS
Q301 DTA114YS
Q302 DTC114YS
Q304 DTC323TS
R302 100
R303 100
C301 0.0022M
C302 0.0022M
C304 100N
D301
D302
C303 47/16
CP302
CNT(PCB3)
NOTES
1. Resistor values are indicated in ohms unless otherwise specified
[K=1.000 M=1.000.000]
2. Capacitor values are indicated in microfarades unless otherwise specified.
[p=micro-microfarades]
CAUTION
Safety precaution to be followed during servicing
1]Since those parts marked with ⚠ are critical parts for safety. use only the one described in the parts list
2]Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.
R161 10K
R165 33K
C126 120P
C128 100P
R167 47K
R178 20K
R181 15K
R177 22K
C130 100P
R180 100
C125 120P
R166 33K
R160 10K
R169 33K
R174 33K
C144 120P
C124 120P
R190 47K
IC104
KIA4559S
C131 0.001(M)
C133 100/10
R175 22K
R187 22K
IC105
KIA4559S
C137 100P
R191 47K
R163 10K
R186 33K
C132 120P
R192 47K
R162 33K
C127 120P
R185 33K
R182 10K
R176 33K
C134 120P
C135 120P
C136 120P
C142 100/47
R194 22K
R203 22K
R196 15K
C139 0.001(M)
R198 20K
R197 22K
C138 100P
R189 22K
R200 22K
C140 100/10
C123 100/10
R202 100
R168 100
R195 100
C143 100/10
R199 68K
R204 68K
C117 100/10
R154 100K
R155 100K
R159 100K
R160 100K
R161 100K
R162 100K
R163 100K
R164 100K
R165 100K
R166 100K
R167 100K
R168 100K
R169 100K
R170 100K
R171 100K
R172 100K
R173 100K
R174 100K
R175 100K
R176 100K
R177 100K
R178 100K
R179 100K
R180 100K
R181 100K
R182 100K
R183 100K
R184 100K
R185 100K
R186 100K
R187 100K
R188 100K
R189 100K
R190 100K
R191 100K
R192 100K
R193 100K
R194 100K
R195 100K
R196 100K
R197 100K
R198 100K
R199 100K
R200 100K
R201 100K
R202 100K
R203 100K
R204 100K
R205 100K
R206 100K
R207 100K
R208 100K
R209 100K
R210 100K
R211 100K
R212 100K
R213 100K
R214 100K
R215 100K
R216 100K
R217 100K
R218 100K
R219 100K
R220 100K
R221 100K
R222 100K
R223 100K
R224 100K
R225 100K
R226 100K
R227 100K
R228 100K
R229 100K
R230 100K
R231 100K
R232 100K
R233 100K
R234 100K
R235 100K
R236 100K
R237 100K
R238 100K
R239 100K
R240 100K
R241 100K
R242 100K
R243 100K
R244 100K
R245 100K
R246 100K
R247 100K
R248 100K
R249 100K
R250 100K
R251 100K
R252 100K
R253 100K
R254 100K
R255 100K
R256 100K
R257 100K
R258 100K
R259 100K
R260 100K
R261 100K
R262 100K
R263 100K
R264 100K
R265 100K
R266 100K
R267 100K
R268 100K
R269 100K
R270 100K
R271 100K
R272 100K
R273 100K
R274 100K
R275 100K
R276 100K
R277 100K
R278 100K
R279 100K
R280 100K
R281 100K
R282 100K
R283 100K
R284 100K
R285 100K
R286 100K
R287 100K
R288 100K
R289 100K
R290 100K
R291 100K
R292 100K
R293 100K
R294 100K
R295 100K
R296 100K
R297 100K
R298 100K
R299 100K
R300 100K
R301 100K
R302 100K
R303 100K
R304 100K
R305 100K
R306 100K
R307 100K
R308 100K
R309 100K
R310 100K
R311 100K
R312 100K
R313 100K
R314 100K
R315 100K
R316 100K
R317 100K
R318 100K
R319 100K
R320 100K
R321 100K
R322 100K
R323 100K
R324 100K
R325 100K
R326 100K
R327 100K
R328 100K
R329 100K
R330 100K
R331 100K
R332 100K
R333 100K
R334 100K
R335 100K
R336 100K
R337 100K
R338 100K
R339 100K
R340 100K
R341 100K
R342 100K
R343 100K
R344 100K
R345 100K
R346 100K
R347 100K
R348 100K
R349 100K
R350 100K
R351 100K
R352 100K
R353 100K
R354 100K
R355 100K
R356 100K
R357 100K
R358 100K
R359 100K
R360 100K
R361 100K
R362 100K
R363 100K
R364 100K
R365 100K
R366 100K
R367 100K
R368 100K
R369 100K
R370 100K
R371 100K
R372 100K
R373 100K
R374 100K
R375 100K
R376 100K
R377 100K
R378 100K
R379 100K
R380 100K
R381 100K
R382 100K
R383 100K
R384 100K
R385 100K
R386 100K
R387 100K
R388 100K
R389 100K
R390 100K
R391 100K
R392 100K
R393 100K
R394 100K
R395 100K
R396 100K
R397 100K
R398 100K
R399 100K
R400 100K
R401 100K
R402 100K
R403 100K
R404 100K
R405 100K
R406 100K
R407 100K
R408 100K
R409 100K
R410 100K
R411 100K
R412 100K
R413 100K
R414 100K
R415 100K
R416 100K
R417 100K
R418 100K
R419 100K
R420 100K
R421 100K
R422 100K
R423 100K
R424 100K
R425 100K
R426 100K
R427 100K
R428 100K
R429 100K
R430 100K
R431 100K
R432 100K
R433 100K
R434 100K
R435 100K
R436 100K
R437 100K
R438 100K
R439 100K
R440 100K
R441 100K
R442 100K
R443 100K
R444 100K
R445 100K
R446 100K
R447 100K
R448 100K
R449 100K
R450 100K
R451 100K
R452 100K
R453 100K
R454 100K
R455 100K
R456 100K
R457 100K
R458 100K
R459 100K
R460 100K
R461 100K
R462 100K
R463 100K
R464 100K
R465 100K
R466 100K
R467 100K
R468 100K
R469 100K
R470 100K
R471 100K
R472 100K
R473 100K
R474 100K
R475 100K
R476 100K
R477 100K
R478 100K
R479 100K
R480 100K
R481 100K
R482 100K
R483 100K
R484 100K
R485 100K
R486 100K
R487 100K
R488 100K
R489 100K
R490 100K
R491 100K
R492 100K
R493 100K
R494 100K
R495 100K
R496 100K
R497 100K
R498 100K
R499 100K
R500 100K
R501 100K
R502 100K
R503 100K
R504 100K
R505 100K
R506 100K
R507 100K
R508 100K
R509 100K
R510 100K
R511 100K
R512 100K
R513 100K
R514 100K
R515 100K
R516 100K
R517 100K
R518 100K
R519 100K
R520 100K
R521 100K
R522 100K
R523 100K
R524 100K
R525 100K
R526 100K
R527 100K
R528 100K
R529 100K
R530 100K
R531 100K
R532 100K
R533 100K
R534 100K
R535 100K
R536 100K
R537 100K
R538 100K
R539 100K
R540 100K
R541 100K
R542 100K
R543 100K
R544 100K
R545 100K
R546 100K
R547 100K
R548 100K
R549 100K
R550 100K
R551 100K
R552 100K
R553 100K
R554 100K
R555 100K
R556 100K
R557 100K
R558 100K
R559 100K
R560 100K
R561 100K
R562 100K
R563 100K
R564 100K
R565 100K
R566 100K
R567 100K
R568 100K
R569 100K
R570 100K
R571 100K
R572 100K
R573 100K
R574 100K
R575 100K
R576 100K
R577 100K
R578 100K
R579 100K
R580 100K
R581 100K
R582 100K
R583 100K
R584 100K
R585 100K
R586 100K
R587 100K
R588 100K
R589 100K
R590 100K
R591 100K
R592 100K
R593 100K
R594 100K
R595 100K
R596 100K
R597 100K
R598 100K
R599 100K
R600 100K
R601 100K
R602 100K
R603 100K
R604 100K
R605 100K
R606 100K
R607 100K
R608 100K
R609 100K
R610 100K
R611 100K
R612 100K
R613 100K
R614 100K
R615 100K
R616 100K
R617 100K
R618 100K
R619 100K
R620 100K
R621 100K
R622 100K
R623 100K
R624 100K
R625 100K
R626 100K
R627 100K
R628 100K
R629 100K
R630 100K
R631 100K
R632 100K
R633 100K
R634 100K
R635 100K
R636 100K
R637 100K
R638 100K
R639 100K
R640 100K
R641 100K
R642 100K
R643 100K
R644 100K
R645 100K
R646 100K
R647 100K
R648 100K
R649 100K
R650 100K
R651 100K
R652 100K
R653 100K
R654 100K
R655 100K
R656 100K
R657 100K
R658 100K
R659 100K
R660 100K
R661 100K
R662 100K
R663 100K
R664 100K
R665 100K
R666 100K
R667 100K
R668 100K
R669 100K
R670 100K
R671 100K
R672 100K
R673 100K
R674 100K
R675 100K
R676 100K
R677 100K
R678 100K
R679 100K
R680 100K
R681 100K
R682 100K
R683 100K
R684 100K
R685 100K
R686 100K
R687 100K
R688 100K
R689 100K
R690 100K
R691 100K
R692 100K
R693 100K
R694 100K
R695 100K
R696 100K
R697 100K
R698 100K
R699 100K
R700 100K
R701 100K
R702 100K
R703 100K
R704 100K
R705 100K
R706 100K
R707 100K
R708 100K
R709 100K
R710 100K
R711 100K
R712 100K
R713 100K
R714 100K
R715 100K
R716 100K
R717 100K
R718 100K
R719 100K
R720 100K
R721 100K
R722 100K
R723 100K
R724 100K
R725 100K
R726 100K
R727 100K
R728 100K
R729 100K
R730 100K
R731 100K
R732 100K
R733 100K
R734 100K
R735 100K
R736 100K
R737 100K
R738 100K
R739 100K
R740 100K
R741 100K
R742 100K
R743 100K
R744 100K
R745 100K
R746 100K
R747 100K
R748 100K
R749 100K
R750 100K
R751 100K
R752 100K
R753 100K
R754 100K
R755 100K
R756 100K
R757 100K
R758 100K
R759 100K
R760 100K
R761 100K
R762 100K
R763 100K
R764 100K
R765 100K
R766 100K
R767 100K
R768 100K
R769 100K
R770 100K
R771 100K
R772 100K
R773 100K
R774 100K
R775 100K
R776 100K
R777 100K
R778 100K
R779 100K
R780 100K
R781 100K
R782 100K
R783 100K
R784 100K
R785 100K
R786 100K
R787 100K
R788 100K
R789 100K
R790 100K
R791 100K
R792 100K
R793 100K
R794 100K
R795 100K
R796 100K
R797 100K
R798 100K
R799 100K
R800 100K
R801 100K
R802 100K
R803 100K
R804 100K
R805 100K
R806 100K
R807 100K
R808 100K
R809 100K
R810 100K
R811 100K
R812 100K
R813 100K
R814 100K
R815 100K
R816 100K
R817 100K
R818 100K
R819 100K
R820 100K
R821 100K
R822 100K
R823 100K
R824 100K
R825 100K
R826 100K
R827 100K
R828 100K
R829 100K
R830 100K
R831 100K
R832 100K
R833 100K
R834 100K
R835 100K
R836 100K
R837 100K
R838 100K
R839 100K
R840 100K
R841 100K
R842 100K
R843 100K
R844 100K
R845 100K
R846 100K
R847 100K
R848 100K
R849 100K
R850 100K
R851 100K
R852 100K
R853 100K
R854 100K
R855 100K
R856 100K
R857 100K
R858 100K
R859 100K
R860 100K
R861 100K
R862 100K
R863 100K
R864 100K
R865 100K
R866 100K
R867 100K
R868 100K
R869 100K
R870 100K
R871 100K
R872 100K
R873 100K
R874 100K
R875 100K
R876 100K
R877 100K
R878 100K
R879 100K
R880 100K
R881 100K
R882 100K
R883 100K
R884 100K
R885 100K
R886 100K
R887 100K
R888 100K
R889 100K
R890 100K
R891 100K
R892 100K
R893 100K
R894 100K
R895 100K
R896 100K
R897 100K
R898 100K
R899 100K
R900 100K
R901 100K
R902 100K
R903 100K
R904 100K
R905 100K
R906 100K
R907 100K
R908 100K
R909 100K
R910 100K
R911 100K
R912 100K
R913 100K
R914 100K
R915 100K
R916 100K
R917 100K
R918 100K
R919 100K
R920 100K
R921 100K
R922 100K
R923 100K
R924 100K
R925 100K
R926 100K
R927 100K
R928 100K
R929 100K
R930 100K
R931 100K
R932 100K
R933 100K
R934 100K
R935 100K
R936 100K
R937 100K
R938 100K
R939 100K
R940 100K
R941 100K
R942 100K
R943 100K
R944 100K
R945 100K
R946 100K
R947 100K
R948 100K
R949 100K
R950 100K
R951 100K
R952 100K
R953 100K
R954 100K
R955 100K
R956 100K
R957 100K
R958 100K
R959 100K
R960 100K
R961 100K
R962 100K
R963 100K
R964 100K
R965 100K
R966 100K
R967 100K
R968 100K
R969 100K
R970 100K
R971 100K
R972 100K
R973 100K
R974 100K
R975 100K
R976 100K
R977 100K
R978 100K
R979 100K
R980 100K
R981 100K
R982 100K
R983 100K
R984 100K
R985 100K
R986 100K
R987 100K
R988 100K
R989 100K
R990 100K
R991 100K
R992 100K
R993 100K
R994 100K
R995 100K
R996 100K
R997 100K
R998 100K
R999 100K
R1000 100K
CD "L" ch SIGNAL
BA6297
GD74HC04D
74MC157
M4052BCF
HY62256ALJ
HY53425AJ-70
CXD2515Q
CXP8220
STI4510ACV
STV8438CV
HY514260BJC-70
CXP82324
KS9241B

WIRING DIAGRAM

Model No. : CDC-757/VCDC-757

L K J I H G

PCB3

SYS CNT A.ASY

SYSTEM CONNECTOR, 13P
FROM TX-747 or TX-757

EXPLODED VIEW II (Page 72)
ITEM (53)
DRIVE UNIT (KSM-2401ABM)

WHITE
WHITE
WHITE
WHITE
RED

(VCDC757 ONLY)

PCB6

CN601

VIDEO JACK B'D
4007000740C

PCB2

CP201

DSP B'D

WHITE
WHITE
WHITE
WHITE
WHITE
RED

EXPLODED VIEW II (Page 72)
ITEM (54), (56)

RED
BLACK
YELLOW
GREEN
BLUE

CARD CABLE, 19P

EXPLODED VIEW II (Page 72)
ITEM (25), (55)

PCB SENSOR

BLACK
RED

YELLOW
GREEN
BLUE
BLACK
RED

PCB1

CP102

(VCDC757 ONLY)

PCB7

▪ DD-757 ▪

SPECIFICATIONS

Track Configuration	
The 4-track, 2-channels and a rotary reverse type head stereo cassette deck motors	
1-Electronic governor	
1-High torque DC motor (Reel)	
Mechanism	
1-Motor, 1-Solenoid mechanism	
Heads	
Rec/Playback head	Hard permalloy
Eraser head	Double gap ferrite
Tape Speed 1-7/8 IPS (4.76 cm/sec) (FWD/REV)	±1.0/±1.0%
Wow/Flutter (CCIR Unweighted)	No more than 0.35%
Fast Winding Time (C-60)	About 120 sec
Input Sensitivity Impedance	
REC IN	400 mV/51 kΩ
Output Level/Load Impedance	
PLAY OUT	400 mV/1.5 kΩ
Signal to Noise Ratio (W.CCIR/ARM)	
CrO_2 Tape with Dolby B/C NR	More than 66/76 dB
CrO_2 Tape without Dolby B/C NR	More than 56 dB
Frequency Response (-20 dB REC Dolby NR off)	
Normal Tape	20 Hz - 17.5 kHz, ±3 dB
CrO_2 Tape	20 Hz - 17.5 kHz, ±3 dB
Metal Tape	20 Hz - 17.5 kHz, ±3 dB
Total Harmonic Distortion (3rd, 333 Hz, 0 dB, Normal Tape)	No more than 1.0%
Channel Separation	No more than 38 dB

BLOCK DIAGRAM

Model No. : DD-757



WIRING DIAGRAM

Model No. : DD-757



DISASSEMBLY PROCEDURES

REFER TO PAGES 85 AND 95.

[1] COVER TOP REMOVAL

Remove 6 screws ⓐ and then remove the Cover Top ㊴

[2] FRONT PANEL ASSEMBLY REMOVAL

1. Remove the Cover Top ㊴, referring to the previous step [1].
2. Remove the card cable from wafer (CNT5M) on the Main P.C.Board (PCB1).
3. Disconnect (CNT1, CNT2, CNT3 and CNT4) from Main P.C.Board (PCB1).
4. Remove 7 screws ⓑ and then remove the Front Panel Assembly AA.

[3] MECHANISM ASSEMBLY REMOVAL

1. Remove the Cover Top ㊴, refering to the previous step [1].
2. Remove the Front Panel Assembly AA, referring to the previous step [2].
3. Remove Base Door ⑦ and ⑧ by pressing the hooks of both sides and pulling it toward you gently.
4. Remove 8 screws ⓒ and then remove the Mechanism ㉕ and ㉖.
5. Remove the Lid Cassette ⑨ right and left.
6. Remove 4 screws ⓓ and then remove the Guide Door ⑲.

[4] FRONT P.C.BOARD (PCB2) REMOVAL

1. Remove the Cover Top ㊴, referring to the previous step [1].
2. Do steps [2] and [3].
3. Remove 2 screws ⓔ and then remove the Front P.C.Board (PCB2).

[5] MAIN P.C.BOARD (PCB1) REMOVAL

1. Remove the Cover Top ㊴, referring to the previous step [1].
2. Remove the card cable from wafer (CNT5M) on the Main P.C.Board (PCB1).
3. Disconnect (CNT1, CNT2, CNT3, CNT4 and CNT6) from the Main P.C.Board (PCB1).
4. Remove 2 screws ⓕ and then Main P.C.Board (PCB1).

CIRCUIT DESCRIPTION

CPU(IC105):CXP50112-590Q

1. Pin Description



2. Block Diagram



3. Input and Output Terminal Function

Pin No.	Symbol	Description
1	LINE MUTE	Output for muting the line output. Except play or recording (dubbing), output is "H".
2	REC MUTE	Output for muting recording output. (If recording, then "L")
3	A/B SEL.	Output for controlling to select Deck A or B. (If Deck B, then "H")
4	FF MUTE	Output for muting line output during FF or REW. (If FF or REW, then "H")
5	NR	Output for controlling the noise reduction. (If the NR mode, then "H")
6	B/C	Output for controlling the DOLBY B/C. (If the DOLBY B, then "H")
7	$Cr O_2$	Output for checking a $Cr O_2$ mode on Deck B. (If $Cr O_2$ tape, then "H".)
8	NORMAL	Output for checking a Nor. mode on Deck B. (If Nor. tape, then "H".)
9	NC	Not Used !
10	STROBE	Strobe output to IC104 (HA12157).
11	CLK	Clock output to IC104 (HA12157).
12	DATA	Data output to IC104 (HA12157).
13~28	NC	Not Used !
29	Vss	This pin provides the ground potential.
30	NC	Not Used !
31	Vss	This pin provides the ground potential.
32	RESET	Input for the resetting system.
33	NC	Not Used !
34	Vdd	+5 V power supply for CPU (IC105).
35~38	KEY INPUT	Data input for key scan.
39	DIGI-LINK	Input/Output for controlling DIGI-LINK.
40	POWER ON	Output for power on. (If power on, then "H")
41	CrO2 IN	Input for checking a $Cr O_2$ tape on Deck B. (If $Cr O_2$ tape, then "H")
42	METAL IN	Input for checking a metal tape on Deck B. (If metal tape, then "H")
43	GND	Ground
44	POWER IN	Input for power on for itself. (If power on itself, then "L")
45/46	REVERSE CT/1T	According to reverse mode switch setting, input for selecting the desired reverse mode.
47	A CAP.	Output for driving the capstan of Deck A.
48	A SOL.	Output for driving the solenoid of Deck A.
49	B CAP.	Output for driving the capstan of Deck B
50	B. SOL.	Output for driving the solenoid of Deck B
51	A PACK	Input for checking a tape on Deck A. (If there's a tape, then "L")
52	A REEL	Input for detecting the reel pulse from Deck A.
53	A MODE	Input for detecting the play state on Deck A.
54	B MODE	Input for detecting the play state on Deck B.
55	B PACK	Input for checking a tape on Deck B. (If there's a tape, then "L")
56	B REEL	Input for detecting the reel pulse from Deck B.
57	FWD REC PACK	Input for checking the forward tap of tape. (If there's the tape, then "L")
58	RVS REC PACK	Input for checking the reverse tap of tape. (If there's the tape, then "L")
59/60	NC	Not Used !

Reverse mode	Reverse CT	Reverse 1T
⇄	L	H
⇉	H	L
↻	H	H

Pin No.	Symbol	Description
61	POWER DOWN	Input for checking the power down. (If power down, then "L")
62	AMS IN	Input for checking the balnk space during AMS (Atomatic Music Searching) (If on the blank space, then "H").
63	S1 RL-PLAY	Output for lighting on the LED at relay play mode. (If relay play, then "H")
64	S2 HI-DUB	Output for lighting on the LED at high dubbing mode. (If high dubbing, then "H").
65	S3 NOR-DUB	Output for lighting on the LED at normal dubbing mode. (If normal dubbing, then "H").
66	S4 REC MUTE	Output for lighting on the LED at recoding mute mode. (If recording must, then "H").
67	S5 FWD PLAY	Output for lighting on the LED at forward play mode. (If forward play, then "H")
68	S6 REV PLAY	Output for lighting on the LED at reverse play mode. (If reverse play, then "H")
69	S7 B DECK	Output for lighting on the LED at deck B mode. (If deck B play, then "H")
70	S8 A DECK	Output for lighting on the LED at deck A mode. (If deck A play, then "H")
71	Vss	This pin provides the ground potential.
72	XTAL	Output for crystal oscillator.
73	NC	Not Used !
74	EXTAL	Input for crystal oscillator.
75	Vdd	+5 V power supply for CPU (IC105).
76	NC	Not Used !
77	S9 CD-SYN LED	Output for lighting on the LED at CD synchro mode. (If CD synchro, then "L")
78	NC	Not Used !
79	REC OUT	Output for controlling the record.
80	HI-SPEED	Output for controlling the tape speed. (If hi-speed, then "H")

ALIGNMENT PROCEDURES

Adjustment and Test Points (PCB2)



Before Measurements and Adjustments

The following general conditions apply to the electrical measurements and adjustments unless especially stated otherwise.

- Dolby NR switch off.
- Use 400mV(200 nwb/m) for 0 dB as the standard level of the unit.

1. Test tape

• TCC-155	Azimuth (14kHz, -24 dB)
• TCC-114	Tape speed (3.15 kHz, -10 dB)
• TCC-130	Playback level (Dolby NR ref. tape 400 Hz, 0 dB)
• TCC-185C	Playback frequency response

- Reference Blank Tape.

• Normal	TDK AC-224
• CrO_2	TDK AC-513
• Metal	TDK AC-712

2. Instruments required

- Audio frequency oscillator
- ACVM or dual channel mV-meter
- Wow/Flutter meter
- Oscilloscope

Playback Section

Adjustments	Test tape	Mode	Apply Signal to	Measure on	Read on	Adjust with	Adjust to
Head Azimuth	TCC-155 14 kHz (A.BEX)	FWD Play (A & B Deck)		Line output	AC mV-meter Oscilloscope	Adjusting a right screw of head	Max • Lissajous wave from become a straight, line with an angle 45 deegrees
		REW Play (A & B Deck)				Adjusting a left screw of head	
Playback at normal speed	TCC-114 3.15 kHz −10 dB(A. Bex)	Play (A & B Deck)			Wow and Flutter Meter	A Deck VR102 & B Deck VR101	3150 Hz±30 Hz
Playback at hi-speed (TP7 short)	TCC-114 3.15 kHz −10 dB(A.Bex)					A Deck VR104 & B Deck VR103	4725 Hz±45 Hz
Playback Level	TCC-130 400 Hz, 0 dB(A. Bex)					A Deck VR110,111	400 mV
						B Deck VR107,VR108	400 mV
Playback Frequency Response	TCC-185C 12.5 kHz, 1 kHz, 60 Hz (A. Bex)				AC mV-meter		See graph Fig. 2 freq. response

Recording Section

Adjustments	Test tape	Mode	Apply Signal to	Measure on	Read on	Adjust with	Adjust to
Bias OSC Frequency	AC-712(TDK)	Rec/Pause		TP5	Frequency Counter	L101	105 kHz ±400 Hz

Adjustments	Test tape	Mode	Apply Signal to	Measure on	Read on	Adjust with	Adjust to
Target Value Bias	Metal, AC-712			TP5, TP6		VR113, VR114	AC 10.9 V
	CrO_2, AC-513					VR112	AC 6.8 V
	Normal, AC-224					VR109	AC 6 V
Recording Level	AC-712 (TDK)		400 Hz, 80 mV to Line in	TP1, TP2		VR105, VR106	About 6.7mV
Bias	AC-712 AC-513 AC-224 (TDK)	Rec/Pause	400 Hz to Line	Line out	AC mV-meter	See Target Value Bias	If necessary repeat bias adjustment See graph fig. 1
			4 kHz - 6.3 kHz 10 kHz - 12 kHz 14 kHz - 16 kHz to Line in	Recording number of frequency with the same input voltage and play them back.			
19kHz Suppression	Arbitrary Tape	Rec/Pause	19 kHz to Line	Line out	AC mV-meter	LF Generator	100mV
				Line out	AC mV-meter Oscilloscope	L104/105	Minimize the reading on ACVM.

Note:

*a. Prior to any measurement or adjstment with the tape running, heads and tape guides should be degaussed and cleaned. Reference below the figuer.

*b. The maximum permissible speed variation ±1.0%. Moerover the Wow and Flutter can be read. This value on line out should exceed 0.2%.

*c. The voltage on line out should be 400 mV ± 20 mV. If not, it reduce the LF signal (bias disabled) as many as the reading was too low or too high by VR107/108, VR110/111.

*d. When the channel is adjsted, this may slightly affect the adjutment of the other channel. If the adjustment is correct, the frequency response curve will be similar to curve b in figuer 1, distrortion below 3%.



REC Bias & THD Graph

Fig. 1



Allowable Playback/Recording Frequency Response Zone

Fig. 2

TROUBLESHOOTING






②
Is CNT5 between Main and Front boards normal?
NO
Check the connector and plug.
YES
Is 1 pin's voltage of CNT5M +5V?
NO
Check the circuit around IC106 (7805)
YES
Are CNT3 and CNT4 connected correctly.
NO
Check the connectors and plugs.
YES
Is 4 pins' voltage of CNT3 and CNT4 +12V?
NO
Check the transistors of each deck as follows.
A Deck: Q136, Q139
B Deck: Q130, Q133
YES
Is 8 pins' pulse of CNT3 and CNT4 normal?
NO
Check the transistors of each deck as follows.
A Deck: Q134, Q135
B Deck: Q120, Q123
YES
OK


③
Are CNT1 and CNT2 connected correctly ?
NO
Check the connectors and plugs.
YES
Is the output signal at the pins 1(R), 7(L) of IC101 and IC103 normal ?
NO
Check the circuit around IC101 and IC103.
YES
Is the output signal at the pins 14(R) and 51(L) of IC104 ?
NO
Check the circuit around IC102 and IC104.
YES
Is each base of Q116, Q117, Q118 and Q119 "L" ?
NO
Check the pin1 of IC105 (CPU) and the circuit arround Q116, Q117, Q118 and Q119.
YES
OK



MECHANICAL PARTS LIST

Ref. No.	Description	Parts No.	Q'ty	Version
	PACKAGE			
	Carton Box	049605258203	1	KS
	Carton Box	049605258204	1	A,D,PT INDO
	Cushion Poly	9722041210	1	
	Film Soft PE	9715000120	1	
	CABINET & CHASSIS			
1	Badge, INKEL	048535045411	1	KS
(1)	Badge, SHERWOOD	048535045421	1	A,D,PT INDO
2	Panel Front	048602020011	1	
3	Door, Right	048663001511	1	
4	Door, Left	048663001521	1	
5	Indicator LED	8555052610	2	
6	Window Door	048555052711	2	
7	Base Door, Right	046512001911	1	
8	Base Door, Left	046512001921	1	
9	Lid Cassette	8562006610	1	
10	Door Spring	6555610210	1	
11	Door Spring	6555610220	1	
12	Knob Slide	048545131611	2	
13	Body Front	048521009611	1	
14	Label Mirror	9057095396	2	
15	Button Selector	048545131211	1	
16	Button Function	048543070212	1	
17	Switch Slide	4618008310	2	
18(SW3-13)	Switch Tact	4658004410	11	
19	Guide Door	8523013410	1	
20	Damper Oil	6308002310	2	
21	Lever Eject, Right	7143104220	1	
22	Lever Eject, Left	7143104210	1	
23	Spring Lever "A"	6555013510	1	
24	Spring Lever "B"	6555013520	1	
25	Deck Mecha, R/P	5708015110	1	
26	Deck Mecha, CMAL2Z035A	5708014710	1	
27	Bracket Shield	6165151310	1	
28	Bracket Shield	6165151210	1	
29	Foot	6035104310	2	
30	Chassis Main	6121614920	1	
31	Fastener	6528301710	4	
32	Cushion Foot	6715021230	1	
33	Heatsink	7505202410	1	
34	Heatsink	7505202410	1	
35	Chassis Back	046102044611	1	KS
(35)	Chassis Back	046102044613	1	PT INDO
(35)	Chassis Back	046102044612	1	D
(35)	Chassis Back		1	A
36	Plate Ground	6165143510	1	
37	Stopper Connector	6518002210	1	
38	Connector, System, 13P	4358613501	1	
39	Cover Top	046123017821	1	
	HARDWARE KIT			
S1	Screw, #2BTT 3x8B	8179130083	25	
S2	Screw, #2FTC 3x8B	8129230083	2	
S3	Screw, #2WPTT 3x6Y	8159230061	2	
S4	Screw, #2BTC 3x10B	8109230103	4	
S5	Screw, #2BTC 3x6B	8109230063	2	
	MISCELLANEOUS			
	Connector, Lead Ass'y, 3P, 220mm, Shield	436203227032	1	
	Connector, Lead Ass'y, 10P, 200mm	436210200532	1	
	Connector, Lead Ass'y, 7P, 200mm, Shield	435207208002	1	
	Connector, Lead Ass'y, 13P, 200mm	436213200532	1	
	Card Cable, YS=1.25-17-180-C	4118617185	1	
PCB1	P.C.Board Main	4004001100	1	
PCB2	P.C.Board Front	4004001110	1	

PRODUCT SAFETY NOTICE

Each precaution in this manual should be followed during servicing. Components identified with the IEC symbol ⚠ in the parts list are of special significance to safety. When replacing a component identified with ⚠ , use only the replacement parts designated, or parts with the same ratings of resistance, wattage or voltage that are designated in the parts list in this manual. Leakage-current or resistance measurements must be made to determine that exposed parts are acceptably insulated from the supply circuit before returning the product to the customer.

EXPLODED VIEW

Model No. : DD-757



PRINTED CIRCUIT BOARDS

Model No. : DD-757

MAIN(PCB2)



FRONT(PCB1)



ELECTRICAL PARTS LIST

PRODUCT SAFETY NOTICE : Products marked with ⚠ have special characteristics important to safety.
If you replace any of these components, read carefully the product safety notice in this manual.
Don't degrade the safety of the product through improper servicing.
Resistor/Capacitor tolerance – D : (±0.5%), J : (±5%), K : (±10%), M : (±20%), Z : +80, – 20%)

Ref. No.	Description					Parts No.	Q'ty	Version
PCB1	ASSEMBLY P.C.BOARD MAIN							
	CAPACITORS							
C101	Ceramic Tubular	220	pF	50 V	J	3519221935	1	
C102	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C103	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C104/C105	Electrolytic SG	10	uF	50 V	M	3479310071	2	
C106	Ceramic Tubular	0.1	uF	50 V	Z	3519104935	1	
C107	Electrolytic SG	2200	uF	25 V	M	3409322249	1	
C108/C109	Ceramic Tubular	0.1	uF	50 V	Z	3519104935	2	
C110	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C111	Ceramic Tubular	0.1	uF	50 V	Z	3519104935	1	
C112	Electrolytic SG	220	uF	10 V	M	3479322121	1	
C113	Electrolytic SG	100	uF	16 V	M	3479310131	1	
C114/C115	Ceramic Tubular	270	pF	50 V	J	3519271935	2	
C116-C118	Electrolytic SG	2.2	uF	50 V	M	3479322971	3	
C119	Electrolytic SG	0.1	uF	50 V	M	3479310871	1	
C120	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C121	Electrolytic SG	100	uF	16 V	M	3479310131	1	
C122	Mylar	0.001	uF	100 V	J	3519102120	1	
C123	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C124	Mylar	0.001	uF	100 V	J	3519102120	1	
C125	Mylar	0.0022	uF	100 V	J	3679222120	1	
C126	Mylar	0.0047	uF	100 V	J	3679472120	1	
C127-C129	Mylar	0.0022	uF	100 V	J	3679222120	3	
C130	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C131	Mylar	0.0047	uF	100 V	J	3679472120	1	
C132	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C133/C134	Mylar	0.0022	uF	100 V	J	3679222120	2	
C135-C138	Mylar	0.1	uF	63 V	K	3679104297	4	
C139	Electrolytic SG	10	uF	50 V	M	3479310071	1	
C140/C141	Mylar	0.1	uF	63 V	K	3679104297	2	
C142	Mylar	0.001	uF	100 V	J	3519102120	1	
C143/C144	Mylar	0.022	uF	100 V	J	3679223120	2	
C145	Mylar	0.001	uF	100 V	J	3519102120	1	
C146	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C147/C148	Electrolytic SG	10	uF	50 V	M	3479310071	2	
C149	Electrolytic SG	1	uF	50 V	M	3479310971	1	
C150/C151	Electrolytic SG	10	uF	50 V	M	3479310071	2	
C152/C153	Electrolytic SG	1	uF	50 V	M	3479310971	2	
C154	Ceramic Tubular	220	pF	50 V	J	3519221935	1	
C155	Mylar	0.022	uF	100 V	J	3679223120	1	
C156	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C157	Mylar	0.022	uF	100 V	J	3679223120	1	
C158	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C159/C160	Electrolytic SG	4.7	uF	50 V	M	3479347971	2	
C161	Ceramic Tubular	220	pF	50 V	J	3519221935	1	
C162/C163	Mylar	0.022	uF	100 V	J	3679223120	2	
C164	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C165/C166	Mylar	0.022	uF	100 V	J	3679223120	2	
C167	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C168	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C169	Electrolytic SG	4.7	uF	50 V	M	3479347971	1	
C170/C171	Ceramic Tubular	100	pF	50 V	J	3519101935	2	
C172/C173	Mylar	0.022	uF	100 V	J	3679223120	2	
C174	Ceramic Tubular	560	pF	50 V	J	3519681935	1	
C175	Ceramic Tubular	680	pF	50 V	J	3519681935	1	
C176/C177	Ceramic Tubular	100	pF	50 V	J	3519101935	2	
C178-C181	Ceramic Tubular	560	pF	50 V	J	3519561935	4	
C182	Mylar	0.0056	uF	100 V	J	3679562120	1	
C183	Electrolytic SG	47	uF	16 V	M	3479347031	1	
C184/C185	Ceramic Tubular	220	pF	50 V	J	3519221935	2	
C186	Mylar	0.0022	uF	100 V	J	3679222120	1	
C187	Mylar	0.033	uF	100 V	J	3679333120	1	
C188	Mylar	0.0022	uF	100 V	J	3679222120	1	
C189	Electrolytic SG	100	uF	16 V	M	3479310131	1	
C190	Mylar	0.0056	uF	100 V	J	3679562120	1	
C191	Electrolytic SG	100	uF	25 V	M	3479310141	1	
C192	Ceramic Tubular	0.1	uF	50 V	Z	3519104935	1	
C193	Ceramic Tubular	100	pF	50 V	J	3519101935	1	
C194	Ceramic Tubular	0.1	uF	50 V	Z	3519104935	1	
C195/C196	Ceramic Tubular	100	pF	50 V	J	3519101935	2	
C197	Ceramic Tubular	470	pF	50 V	J	3519471935	1	
C198	Electrolytic SG	10	uF	50 V	M	3479310071	1	
	CONNECTORS							
CNT1	Wafer, 3P					4428516210	1	
CNT2	Wafer, 7P					4428516610	1	
CNT3	Wafer, 13P					4428517210	1	
CNT4	Wafer, 10P					4428516910	1	
CNT5M	Wafer, FFC, 17P					4428509015	1	
CNT6	Wafer, 13P					4428513800	1	
	DIODES							
D101	1N4148, Swithcing					2058322101	1	
D102	Zener, UZ 5.1 BSB					2258599103	1	
D103	Zener, UZ 5.6 BSB					2258599104	1	
D104-D106	1N4148, Swithcing					2058322101	3	
D107	Zener, UZ 7.5 BSC					2258599130	1	
D108	1N4148, Swithcing					2058322101	1	
D109	Zener, UZ 7.5 BSC					2258599130	1	
D110/D111	1N4148, Swithcing					2058322101	2	
D112	1N4003, Rectifier					2258128002	1	
D113/D114	1N4148, Swithcing					2058322101	2	
D115	Zener, UZ 5.1 BSB					2258599103	1	
D116	Zener, UZ 12.0 BSC					2258599116	1	
D117/D118	1N4003, Rectifier					2258128002	2	
	INTEGRATED CIRCUITS							
IC101	NJM2068D					2168020106	1	
IC102	GD4053					2138001117	1	
IC103	NJM2068D					2168020106	1	
IC104	HA12157					2168011135	1	
IC105	CXP50112-590Q					2139322702	1	
IC106	KIA7805P, Regulator					2168606103	1	
	COILS							
L101	OSC Bias, CQN-K5174					2638601350	1	
L102/L103	Inductor, 10 uH					2648610082	2	
L104/L105	Filter, MPX, FB-10D					2658301120	2	
L106/L107	Trap Bias, 389AC-K5049					2658501150	2	
	TRANSISTORS							
Q101	DTC114YS					2208622106	1	
Q102/Q103	DTC114TS					2208622108	2	
Q104	KRA107M/DTA114YS					2238006103	1	
Q105/Q106	DTC114TS					2208622108	2	
Q107	KTC3198Y, NPN					2208606105	1	
Q108-Q111	DTC114TS					2208622108	3	
Q112	MPSA56, PNP					2208206113	1	
Q113	MPSA06Y, NPN					2208606114	1	
Q114	DTC114TS					2208622108	1	
Q115	DTC114YS					2208622106	1	
Q116-Q119	KTD1302, NPN					2208606112	4	
Q120-Q122	KTC3198Y, NPN					2208606105	3	
Q123	MPSA56, PNP					2208206113	1	
Q124-Q127	KTC3198Y, NPN					2208606105	4	
Q128/Q129	MPSA56, PNP					2208206113	2	
Q130-Q132	KTC3198Y, NPN					2208606105	3	
Q133	MPSA56, PNP					2208206113	1	
Q134	KTC3198Y, NPN					2208606105	1	
Q135	MPSA56, PNP					2208206113	1	
Q136	KTC3198Y, NPN					2208606105	1	
Q137/Q138	DTC114TS					2208622108	2	
Q139	MPSA56, PNP					2208206113	1	
Q140	KTD1302, NPN					2208606112	1	
Q141	KRA107M/DTA114YS					2238006103	1	
Q142	DTC114TS					2208622108	1	
Q143	KTC3198Y, NPN					2208606105	1	
Q144	DTC114YS					2208622106	1	
Q145	KTD1302, NPN					2208606112	1	

Ref. No.	Description	Parts No.	Q'ty	Version
Q146	DTC114TS	2208622108	1	
Q147-Q157	DTC114YS	2208622106	11	
Q158	MPSA56, PNP	2208206113	1	
Q159	DTC114YS	2208622106	1	
Q160	KTC2236A/KTC3205, NPN	2228407117	1	
Q161	DTC114YS	2208622106	1	
Q162	KTC2236A/KTC3205, NPN	2228407117	1	
Q163	KTA1015Y/BKTA1266, PNP	2208206105	1	
Q164-Q166	DTC114YS	2208622106	3	
Q167	KTC3198Y, NPN	2208606105	1	
Q168	KTC2236A/KTC3205, NPN	2228407117	1	
Q169	DTC114YS	2208622106	1	
Q170	2SB1367Y/KTB1367, PNP	2028106109	1	
Q171/Q172	KTC3198Y, NPN	2208606105	2	
	RESISTORS			
R102	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R103	Metal Film 220 ohm 1/5 W J	3029221970	1	
R104	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R105	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R106	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R107/R108	Metal Film 220 ohm 1/5 W J	3029221970	2	
R109	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R110	Carbon Film 220 kohm 1/5 W J	3069224970	1	
R111	Metal Film 4.7 ohm 1/5 W J	3029479970	1	
R112	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R113/R114	Metal Film 220 ohm 1/5 W J	3029221970	2	
R115	Metal Film 47 ohm 1W J	3029470470	1	
R116	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R117/R118	Metal Film 220 ohm 1/5 W J	3029221970	2	
R119	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R120	Metal Film 150 ohm 1/5 W J	3029151970	1	
R121/R122	Metal Film 220 ohm 1/5 W J	3029221970	2	
R123	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R124/R125	Metal Film 4.7 kohm 1/5 W J	3029472970	2	
R126	Metal Film 1 kohm 1/5 W J	3029102970	1	
R127-R129	Metal Film 4.7 kohm 1/5 W J	3029472970	3	
R130	Metal Film 1 kohm 1/5 W J	3029102970	1	
R131	Carbon Film 56 kohm 1/5 W J	3069563970	1	D
(R131)	Carbon Film 51 kohm 1/5 W J	3069513970	1	A,KS,PT INDO
R132	Carbon Film 8.2 kohm 1/5 W J	3069822970	1	D
(R132)	Metal Film 3.3 kohm 1/5 W J	3029332970	1	A,KS,PT INDO
R133/R134	Metal Film 1 kohm 1/5 W J	3029102970	2	
R135	Carbon Film 56 kohm 1/5 W J	3069563970	1	D
(R135)	Carbon Film 51 kohm 1/5 W J	3069513970	1	A,KS,PT INDO
R136	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R137	Carbon Film 8.2 kohm 1/5 W J	3069822970	1	D
(R137)	Metal Film 3.3 kohm 1/5 W J	3029332970	1	A,KS,PT INDO
R138	Metal Film 1.5 kohm 1/5 W J	3029152970	1	
R139	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R140	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R141	Carbon Film 100 kohm 1/5 W J	3069104970	1	
R142/R143	Metal Film 1.5 kohm 1/5 W J	3029152970	2	
R144	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R145	Carbon Film 8.2 kohm 1/5 W J	3069822970	1	
R146	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R147	Metal Film 680 ohm 1/5 W J	3029681970	1	
R148	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R149	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R150	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R151	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R152	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R153	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R154	Metal Film 1 kohm 1/5 W J	3029102970	1	
R155	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R156	Metal Film 1.2 kohm 1/5 W J	3029122970	1	
R157	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R158	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R159	Carbon Film 8.2 kohm 1/5 W J	3069822970	1	
R160	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R161	Metal Film 1 kohm 1/5 W J	3029102970	1	
R162	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R163	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R164	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R165	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R166/R167	Metal Film 1.2 kohm 1/5 W J	3029122970	2	
R168	Carbon Film 3.3 Mohm 1/5 W J	3069335970	1	
R169	Metal Film 680 ohm 1/5 W J	3029681970	1	
R170	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R171	Carbon Film 470 kohm 1/5 W J	3069474970	1	
R172	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R173	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R174	Metal Film 560 ohm 1/5 W J	3029561970	1	
R175	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R176	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R177	Metal Film 1.5 kohm 1/5 W J	3029152970	1	
R178	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R179	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R180	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R181	Carbon Film 56 kohm 1/5 W J	3069563970	1	
R182	Metal Film 560 ohm 1/5 W J	3029561970	1	
R183	Carbon Film 120 ohm 1/4 W J	3069121270	1	
R184	Metal Film 680 ohm 1/5 W J	30296819?0	1	
R185	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R186	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R188	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R190	Metal Film 3.9 kohm 1/5 W J	3029392970	1	
R191	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R192	Metal Film 2.7 kohm 1/5 W J	3029272970	1	
R193	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R194	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R195	Carbon Film 18 kohm 1/5 W J	3069183970	1	
R196	Metal Film 2.7 kohm 1/5 W J	3029272970	1	
R197	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R198	Carbon Film 68 kohm 1/5 W J	3069683970	1	
R199	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R200	Metal Film 680 ohm 1/5 W J	3029681970	1	
R201	Carbon Film 68 kohm 1/5 W J	3069683970	1	
R202	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R203	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R204	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R205	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R206	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R207/R208	Carbon Film 22 kohm 1/5 W J	3069223970	2	
R209/R210	Carbon Film 47 kohm 1/5 W J	3069473970	2	
R211	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R212	Metal Film 560 ohm 1/5 W J	3029561970	1	
R213	Metal Film 100 ohm 1/5 W J	3029101970	1	
R214	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R215	Metal Film 560 ohm 1/5 W J	3029561970	1	
R216	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R217/R218	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R219-R223	Carbon Film 100 kohm 1/5 W J	3069104970	5	
R224/R225	Carbon Film 51 kohm 1/5 W J	3069513970	2	
R226	Metal Film 2.2 kohm 1/5 W J	3029222970	1	
R227	Carbon Film 39 kohm 1/5 W J	3069393970	1	
R228	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R229	Carbon Film 12 kohm 1/5 W J	3069123970	1	
R230	Carbon Film 43 kohm 1/5 W J	3069433970	1	
R231	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R232	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R233	Metal Film 2.2 kohm 1/5 W J	3029222970	1	
R234	Carbon Film 43 kohm 1/5 W J	3069433970	1	
R235	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R236	Carbon Film 43 kohm 1/5 W J	3069433970	1	
R237	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R238	Carbon Film 27 kohm 1/5 W J	3069273970	1	
R239	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R240	Carbon Film 68 kohm 1/5 W J	3069683970	1	
R241	Carbon Film 120 kohm 1/5 W J	3069124970	1	
R242	Carbon Film 100 kohm 1/5 W J	3069104970	1	
R243	Carbon Film 91 kohm 1/5 W J	3069913970	1	
R244	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R245	Carbon Film 120 kohm 1/5 W J	3069124970	1	
R246	Carbon Film 150 kohm 1/5 W J	3069154970	1	
R247	Carbon Film 100 kohm 1/5 W J	3069104970	1	
R248	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R249	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R250	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R251	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R252	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R253	Carbon Film 39 kohm 1/5 W J	3069393970	1	
R254	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R255	Carbon Film 27 kohm 1/5 W J	3069273970	1	
R256	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R257	Carbon Film 5.6 kohm 1/5 W J	3069562970	1	
R258	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R259/R260	Carbon Film 22 kohm 1/5 W J	3069223970	2	
R261/R262	Carbon Film 100 kohm 1/5 W J	3069104970	2	
R263/R264	Carbon Film 120 kohm 1/5 W J	3069124970	2	
R265	Carbon Film 150 kohm 1/5 W J	3069154970	1	
R266	Carbon Film 120 kohm 1/5 W J	3069124970	1	
R267-R269	Carbon Film 33 kohm 1/5 W J	3069333970	3	
R270	Metal Film 3.9 kohm 1/5 W J	3029392970	1	
R271	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R272	Metal Film 820 ohm 1/5 W J	3029821970	1	
R273	Metal Film 47 ohm 1/5 W J	3029470970	1	
R274/R275	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R276	Metal Film 1.5 kohm 1/5 W J	3029152970	1	
R277	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R278	Metal Film 47 ohm 1/5 W J	3029470970	1	
R279/R280	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R281/R282	Metal Film 47 ohm 1/5 W J	3029470970	2	
R283	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R284/R285	Metal Film 33 ohm 1/5 W J	3029330970	2	
R286	Metal Film 1 kohm 1/5 W J	3029102970	1	
R288	Metal Film 100 ohm 1/5 W J	3029101970	1	
R289/R290	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R291	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R292/R293	Carbon Film 6.8 kohm 1/5 W J	3069682970	2	
R294/R295	Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R296/R297	Carbon Film 100 kohm 1/5 W J	3069104970	2	
R298/R299	Metal Film 33 ohm 1/5 W J	3029330970	2	
R300-R302	Carbon Film 100 kohm 1/5 W J	3069104970	3	
R303	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R304	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R305	Metal Film 1.5 kohm 1/5 W J	3029152970	1	
R306/R307	Carbon Film 6.8 kohm 1/5 W J	3069682970	2	
R308-R310	Carbon Film 100 kohm 1/5 W J	3069104970	3	
R311/R312	Carbon Film 33 kohm 1/5 W J	3069333970	2	
R313/R314	Carbon Film 100 kohm 1/5 W J	3069104970	2	
R315/R316	Metal Film 10 ohm 1/5 W J	3029100970	2	
R317	Carbon Film 10 kohm 1/5 W J	3069103970	1	
R318	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R319	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R320	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R321	Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R322	Carbon Film 33 kohm 1/5 W J	3069333970	1	
R323	Metal Film 10 ohm 1/5 W J	3029100970	1	
R324	Metal Film 4.7 ohm 1/5 W J	3029479970	1	
R325	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R326/R327	Carbon Film 10 kohm 1/5 W J	3069103970	2	
R328-R330	Metal Film 1 kohm 1/5 W J	3029102970	3	
R331	Metal Film 68 ohm 2W J	3029680570	1	
R332	Carbon Film 47 kohm 1/5 W J	3069473970	1	
R333	Metal Film 470 ohm 1/5 W J	3029471970	1	
R334	Carbon Film 22 kohm 1/5 W J	3069223970	1	
R335	Metal Film 680 ohm 1/5 W J	3029681970	1	
R336	Metal Film 4.7 kohm 1/5 W J	3029472970	1	
R337	Metal Film 220 ohm 1/5 W J	3029221970	1	
R338	Metal Film 470 ohm 1/5 W J	3029471970	1	
R339	Metal Film 47 ohm 1/5 W J	3029470970	1	
	SEMI FIXED RESISTORS			
VR101/102	220 (B)	3248022143	2	
VR103/104	500 (B)	3248050143	2	
VR105-108	10 k(B)	3248010343	4	
VR109	2 k(B)	3248020243	1	
VR110/111	10 k(B)	3248010343	2	
VR112	2 k(B)	3248020243	1	
VR113/114	50 k(B)	3248050343	2	
	MISCELLANEOUS			
XT-1	CST4.19MHz	3938124006	1	
RLY101	Relay, G5V-2-H1	5528040001	1	
	Plate, Ground	6165143510	1	
	Wire, HI-WP #24, Black, 140mm	152624101444	1	
33	Heatsink	7505202410	1	
34	Heatsink	7505202410	1	
36	Plate Ground	6165143510	1	

Ref. No.	Description	Parts No.	Q'ty	Version
PCB2	**ASSEMBLY P.C.BOARD FRONT**			
R401	RES, Carbon Film 15 kohm 1/5 W J	3069153970	1	
R402	RES, Metal Film 1.2 kohm 1/5 W J	3029122970	1	
R403	RES, Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R404	RES, Carbon Film 8.2 kohm 1/5 W J	3069822970	1	
R405	RES, Metal Film 3.3 kohm 1/5 W J	3029332970	1	
R406	RES, Metal Film 1.8 kohm 1/5 W J	3029182970	1	
R407	RES, Carbon Film 8.2 kohm 1/5 W J	3069822970	1	
R408	RES, Metal Film 1.8 kohm 1/5 W J	3029182970	1	
R409/R410	RES, Metal Film 3.3 kohm 1/5 W J	3029332970	2	
R411	RES, Metal Film 1.8 kohm 1/5 W J	3029182970	1	
R412-R414	RES, Metal Film 1.2 kohm 1/5 W J	3029122970	3	
LED1-LED5	LED, SLR-34GC N49, Green	2381040301	5	
LED6/LED7	LED, SLR-34URC N49, Red	2381215704	2	
LED8/LED9	LED, SLR-34GC N49, Green	2381040301	2	
CNT5F	Connector, Wafer, FFC, 17P	4428517826	1	
18(SW3-13)	Switch Tact	4658004410	11	

IC FUNCTIONAL BLOCK DIAGRAM

IC101, IC103 : NJM2068D



IC102 : GD4053B



IC106 : KIA7806P



IC104 : HA12157NT



SCHEMATIC DIAGRAM



NOTES

1. Resistor values are indicated in ohms unless otherwise specified
   [K=1.000 M=1.000.000]
2. Capacitor values are indicated in microfarades unless otherwise specified.
   [p=micro-microfarades]

CAUTION

Safety precaution to be followed during servicing

1) Since those parts marked with ⚠ are critical parts for safety. use only the one described in the parts list

2) Before returning the set to the customer make appropriate leakage current or resistance measurements to determine the exposed parts are properly insulated from the supply circuit.

PIN CONNECTION OF DIODES, TRANSISTORS AND ICS

ZENER IN4003 IN4148 Anode / Cathode	KTD1302 KTC3198/KTC1815 KTA1266/KTA1015Y E C B	MPSA56Y MPSA06Y E C B	DTA114YS DTC114YS DTC114TS B C E	SLR-34URC N49 SLR-34GC N49 Cathode / Anode

G	H	I	J	K	L	M



PLAY BACK SIGNAL

REC SIGNAL

SLR-34URC N49 SLR-34GC N49	2SBB67Y/KTB1367	KTC2236A/KTC3205	KIA7805P	NJM2068D	GD4053B	HA12157NT